

GaAs MMIC SMT DOUBLE-BALANCED MIXER, 1.7 - 4.5 GHz

Typical Applications


The HMC175MS8 is ideal for:

- Mini-Base Stations
- Portable Wireless
- PCMCIA

Features

- Ultra Small Package: MSOP8
- Conversion Loss: 8 dB
- LO / IF Isolation: 32 dB
- LO / RF Isolation: 30 dB
- IP3 (Input): +18 dBm

Functional Diagram



General Description


The HMC175MS8 is a miniature double-balanced mixer in an 8-lead plastic surface mount Mini Small Outline Package (MSOP). The device can be used as an upconverter or downconverter. The mixer provides exceptional isolation and Intermodulation performance for applications in high signal density environments. This device can also be used as a biphaser modulator or demodulator. The MSOP8 is the smallest footprint available for a complete double-balanced mixer (0.118" x 0.190" x 0.040").

Electrical Specifications, $T_A = +25^\circ C$, LO Drive = +13 dBm


Parameter	Broadband			PCS Band			ISM Band			Units
	Min.	Typ.	Max.	Min.	Typ.	Max.	Min.	Typ.	Max.	
Frequency Range, RF & LO	1.7 - 4.5			1.7 - 2.0			2.2 - 2.6			GHz
Frequency Range, IF	DC - 1.0			DC - 1.0			DC - 1.0			GHz
Conversion Loss		8	11		9	11		8	10	dB
Noise Figure (SSB)		8	11		9	11		8	10	dB
LO to RF Isolation	25	30		35	40		30	35		dB
LO to IF Isolation	27	32		28	32		28	32		dB
IP3 (Input)	15	20		15	18		15	18		dBm
1 dB Gain Compression (Input)	9	12		9	11		9	11		dBm

GaAs MMIC SMT DOUBLE-BALANCED MIXER, 1.7 - 4.5 GHz


Conversion Gain vs Temperature @ LO = +13 dBm




Isolation @ LO = +13 dBm




Conversion Gain vs LO Power




IF Bandwidth @ LO = +13 dBm



Return Loss @ LO = +13 dBm




P1dB vs Temperature @ LO = +13 dBm




GaAs MMIC SMT DOUBLE-BALANCED MIXER, 1.7 - 4.5 GHz


Input IP3 vs. LO Drive




Input IP3 vs. Temperature @ LO = +13 dBm



Input IP2 vs. LO Drive



Input IP2 vs. Temperature @ LO = +13 dBm



MxN Spurious Outputs

RF Frequency = 2.3 GHz @ -10 dBm					
LO Frequency = 2.4 GHz @ 13 dBm					
mRF	nLO				
	0	1	2	3	4
0	xx	1	12	12	37
1	4	0	27	39	38
2	74	53	56	60	67
3	78	>105	73	72	79
4	>105	>105	>105	>105	>105

All values in dBc below IF power level.

Harmonics of LO

LO Freq. (GHz)	nLO Spur at RF Port			
	1	2	3	4
1.8	37	32	63	53
2.2	35	30	37	63
2.6	32	28	33	55
3	30	29	53	52
3.1	29	30	56	51
3.6	29	39	52	53
4.2	27	46	48	61


LO = +13 dBm
Values in dBc below input LO level measured at RF Port.

GaAs MMIC SMT DOUBLE-BALANCED MIXER, 1.7 - 4.5 GHz

Absolute Maximum Ratings


RF / IF Input	+13 dBm
LO Drive	+27 dBm
Storage Temperature	-65 to +150 °C
Operating Temperature	-40 to +85 °C

Outline Drawing



GaAs MMIC SMT DOUBLE-BALANCED MIXER, 1.7 - 4.5 GHz

Evaluation Circuit Board



List of Material

Item	Description
J1 - J3	PC Mount SMA RF Connector
U1	HMC175MS8 Mixer
PCB*	101650 Evaluation Board
* Circuit Board Material: Rogers 4350	

The circuit board used in the final application should use RF circuit design techniques. Signal lines should have 50 ohm impedance while the package ground leads and exposed paddle should be connected directly to the ground plane similar to that shown. A sufficient number of VIA holes should be used to connect the top and bottom ground planes. The evaluation circuit board shown is available from Hittite upon request.

GaAs MMIC SMT DOUBLE- BALANCED MIXER, 1.7 - 4.5 GHz

Notes: