TOSHIBA Bipolar Linear Integrated Circuit Silicon Monolithic

TA8262H

Max Power 43 W BTL × 4CH Audio Power IC

The TA8262H is 4 ch BTL audio power amplifier for car audio application.

This IC can generate more high power: POUT MAX = 43 W as it is included the pure complementary PNP and NPN transistor output stage.

It is designed low distortion ratio for 4 ch BTL audio power amplifier, built-in Stand-by Function, Muting Function, Clip detector, and diagnosis circuit.

Additionally, the AUX. amplifier is built-in, it can make the beep signal etc. output to 2 channels (OUT1 and 4).

It contains various kind of protectors for car audio use.

Features

- High power
 - : POUT MAX (1) = 43 W (typ.)
 - $(V_{CC} = 14.4 \text{ V}, \text{JEITA max}, \text{RL} = 4 \Omega)$
 - : POUT MAX (2) = 40 W (typ.)
 - $(V_{CC} = 13.7 \text{ V}, \text{JEITA max}, \text{R}_{L} = 4 \Omega)$
 - : POUT (1) = 28 W (typ.)
 - $(V_{CC} = 14.4 \text{ V}, \text{ f} = 1 \text{ kHz}, \text{ THD} = 10\%, \text{ RL} = 4 \Omega)$
 - $: P_{OUT} (2) = 24 W (typ.)$
 - $(V_{CC} = 13.2 \text{ V}, \text{ f} = 1 \text{ kHz}, \text{ THD} = 10\%, \text{ RL} = 4 \Omega)$
- Built-in clip detector & diagnosis circuit. (pin 25)
- Low distortion ratio
 - : THD = 0.02% (typ.)

$$(V_{CC} = 13.2 \text{ V}, \text{ f} = 1 \text{ kHz}, P_{OUT} = 5 \text{ W}, \text{ RL} = 4 \Omega)$$

- Low noise
 - : $V_{NO} = 0.10 \text{ mVrms}$ (typ.)
 - (V_{CC} = 13.2 V, $R_g = 0 \Omega$, $G_V = 26 dB$, $BW = 20 Hz \sim 20 kHz$)
- Built-in stand-by switch function (pin 2)
- Built-in muting function (pin 24)
- Built-in AUX. amplifier from single input (pin 16) to 2 channels output; OUT1 and 4
- Built-in various protection circuit
 Thermal shut down, over voltage, out to GND, out to VCC, out to out short
- Operating supply voltage: VCC (opr) = 9~18 V



Weight: 9.8 g (typ.)

Block Diagram



Caution and Application Method (description is made only on the single channel)

1. Voltage gain adjustment

This IC has no NF (negative feedback) terminals. Therefore, the voltage gain can't adjusted, but it makes the device a space and total costs saver.



Figure 1 Block diagram

The voltage gain of Amp. 1 The voltage gain of Amp. 2A, B The voltage gain of BLT Connection : GV (BTL) = 6dBTherefore, the total voltage gain is decided by expression below. $GV = GV_1 + GV_2 + GV (BTL) = 0 + 20 + 6 = 26dB$

2. Stand-by SW function (pin 2)

By means of controlling pin 2 (Stand-by terminal) to High and Low, the power supply can be set to ON and OFF.

The threshold voltage of pin 2 is set at about 3 VBE (typ.), and the Power Supply current is about 2 μA (typ.) at the stand-by state.

|--|

Stand-By	Power	V _(SB) (V)			
ON	OFF	0~1.5			
OFF	ON	3~V _{CC}			



Figure 2 With pin 2 set to High, power is turned ON

Adjustage of stand-by SW

- (1) Since V_{CC} can directly be controlled to ON or OFF by the microcomputer, the switching relay can be omitted.
- (2) Since the control current is microscopic, the switching relay of small current capacity is satisfactory for switching



Figure 3

3. Muting function (pin 24)

By means of controlling pin 24 less than 0.5 V, it can make the audio muting condition. The muting time constant is decided by R_1 and C_4 and these parts is related the pop noise at power ON/OFF.The series resistance; R_1 must be set up less than 15 k Ω , we recommend 10 k Ω . The muting function have to be controlled by a transistor, FET and μ -COM port which has $I_{MUTE} \geq 250 \ \mu A$ ability.

Terminal 24 must not be pulled up and it shall be controlled by OPEN/LOW.









4. AUX. input (pin 16)

The pin 16 is for input terminal of AUX. amplifier. The total gain is 0dB by using of AUX. amplifier. Therefore, the µ-COM can directly drive the AUX. amplifier. BEEP sound or voice synthesizer signal can be input to pin 16 directly.



Figure 6 AUX input

5. Diagnosis output (pin 25)

The diagnosis output terminal of pin 25 has open collector output structure on chip as shown in Figure 7. In unusual case that output terminal of Power Amp. is condition of output to V_{CC} or output to GND short and over voltage input mode, it is possible to protect all the system of apparatus as well as power IC protection.

In case of being unused this function, use this IC as open-connection on pin 25.



pin 25: Open collector output (active low)

Figure 7

6. Output clip detection function (pin 25)

The output clip detection terminal of pin 25 has the open collector output structure on chip as shown in Figure 8. In case that the output waveform is clipping, the clip detection circuit is operated and NPN Tr. is turned on.

It is possible to improve the audio quality with controlling the volume, tone control circuit through L.P.F. smoothing circuit as shown in Figure 8.

In case of being unused this function, use this IC as open connection on pin 25.

(Application)











7. Cross talk

The cross talk characteristics of the IC is not good between OUT1 and 2, OUT3 and 4. So we recommend to use by below method.

OUT1, 2	L-ch (or R-ch)
OUT3, 4	R-ch (or L-ch)

And, please refer to below table in case of applying the AUX. IN because it is out to OUT1 and 4.

ex) in case of the Signal from AUX. IN to front speakers.

OUT1	Front	L-ch (or P-ch)	AUX. OUT		
OUT2	Rear		—		
OUT3	Rear	P ch (or L ch)	—		
OUT4	Front		AUX. OUT		

Maximum Ratings (Ta = 25°C)

Characteristics	Symbol	Rating	Unit
Peak supply voltage (0.2 s)	V _{CC (surge)}	50	V
DC supply voltage	V _{CC (DC)}	25	V
Operating supply voltage	V _{CC (opr)}	18	V
Output current (peak)	I _{O (peak)}	9	А
Power dissipation	P _D (Note 1)	250	W
Operating temperature	T _{opr}	-40~85	°C
Storage temperature	T _{stg}	-55~150	°C

Note 1: Package thermal resistance $\theta_{j-T} = 0.5^{\circ}C/W$ (typ.) (Ta = 25°C, with infinite heat sink)

Electrical Characteristics (unless otherwise specified, V_{CC} = 13.2 V, f = 1 kHz, R_L = 4 Ω , Ta = 25°C)

Characteristics	Symbol	Test Circuit	Test Condition	Min	Тур.	Max	Unit
Quiescent current	ICCQ	_	V _{IN} = 0		200	400	mA
Output power	P _{OUT} MAX (1)	_	V _{CC} = 14.4 V, MAX power	Ι	43		W
	P _{OUT} MAX (2)	_	V _{CC} = 13.7 V, MAX power	_	40		
	Р _{ОUT} (1)	-	V _{CC} = 14.4 V, THD = 10%	_	28	_	
	P _{OUT} (2)	—	THD = 10%	22	24	_	
Total harmonic distortion	THD	_	P _{OUT} = 5 W	_	0.02	0.2	%
Voltage gain	GV	_	V _{OUT} = 0.775 Vrms (0dBm)	24	26	28	dB
Voltage gain ratio	ΔG _V	_	V _{OUT} = 0.775 Vrms (0dBm)	-1.0	0	1.0	dB
Output noise voltage	V _{NO} (1)	_	R _g = 0 Ω, DIN45405	_	0.12	_	mVrms
	V _{NO} (2)	_	R _g = 0 Ω, BW = 20 Hz~20 kHz	_	0.10	0.35	
Ripple rejection ratio	R.R.	_	f _{rip} = 100 Hz, R _g = 620 Ω V _{rip} = 0.775 Vrms (0dBm)	40	50	_	dB
Cross talk	C.T.	_	R _g = 620 Ω, V _{OUT} = 0.775 Vrms (0dBm)	_	65	_	dB
Output offset voltage	VOFFSET	_	_	-100	0	100	mV
Input resistance	R _{IN}	_	_	_	90	_	kΩ
Stand-by current	I _{SB}	_	Stand-by condition	_	2	10	μA
Stand-by control voltage	V _{SB} H	_	Power: on	3.0	_	V _{CC}	v
	V _{SB} L	_	Power: off	0	_	1.5	
Mute control voltage (Note 2)	V _M H	_	Mute: off		OPEN		
	V _M L	—	Mute: on, R ₁ = 10 kΩ	0	_	0.5	V
Mute attenuation	ATT M	_	Mute: on, V _{OUT} = 7.75 Vrms (20dBm) at Mute: off.	80	90	_	dB

Note 2: Muting function have to be controlled by open and Low Logic, which Logic is a transistor, FET and μ -COM port of I_{MUTE} \geq 250 μ A ability.

This means that the Mute control terminal: pin 24 must not be pulled-up.

Test Circuit













Package Dimensions

HZIP25-P-1.27E

Unit : mm



Weight: 9.8 g (typ.)