Monolithic Digital IC



LB1882V

Three-Phase Brushless Motor Driver

Overview

The LB1882V is a three-phase brushless motor driver IC that is particularly well-suited for driving spindle motors in portable AV equipment such as DAT, CD and MD products.

Features

- Current linear drive: allows external capacitances to be minimized.
- Motor voltage control: reduces power dissipation.
- Support for motor drive at power supply voltages as low as 1.8 V
- Built-in torque ripple correction circuit
- Built-in saturation prevention circuit
- Built-in AGC circuit
- Built-in thermal shutdown circuit
- Built-in current limiter
- Built-in FG amplifier

Specifications

Absolute Maximum Ratings at Ta = $25^{\circ}C$

Package Dimensions

unit: mm

3175A-SSOP24



Parameter	Symbol	Conditions	Ratings	Unit
	V _{CC} 1 max		8	V
Maximum supply voltage	V _{CC} 2 max		12	V
	V _S max		V _{CC} 1	V
Maximum output current	I _O max		1.0	A
Allowable power dissipation	Pd max		0.5	W
Operating temperature	Topr		-20 to +75	°C
Storage temperature	Tstg		-55 to +150	°C

Operating Conditions at $Ta = 25^{\circ}C$

Parameter	Symbol	Conditions	Ratings	Unit
	V _{CC} 1		1.8 to 6.0	V
Supply voltage	V _{CC} 2		3 to 10	V
	VS		Up to V _{CC} 1	V

Parameter	Symbol	Conditions	min	typ	max	Unit	Note
	I _{CC} 1			5	8	mA	
Current drain	I _{CC} 2				2	mA	
	۱ _S	I _S – I _L			1	mA	
	ICC 10Q	V _{STBY} = 0 V			10	μA	
Output quiescent current	ICC 20Q	V _{STBY} = 0 V			10	μA	
	I _{SOQ}	V _{STBY} = 0 V			10	μA	
Output saturation voltage	V _{OU (sat)} 1	V_{RF} = 40 mV, R_L = 100 Ω (Y)	25		65	mV	
upper side	V _{OU (sat)} 2	V_{RF} = 100 mV, R_L = 100 Ω (Y)	25		65	mV	
Output residual voltage	V _{OD (sat)} 1	V_{RF} = 40 mV, R_L = 100 Ω (Y)	200		280	mV	
lower side	V _{OD (sat)} 2	V_{RF} = 100 mV, R_L = 100 Ω (Y)	285		365	mV	
Hall amplifier input offset voltage	V _{Hoffset}		-5		+5	mV	*
Hall amplifier common-mode input voltage range	V _{HCOM}		1.2		2.5	V	
Standby pin high level voltage	V _{STBYH}		2.0			V	
Standby pin low level voltage	V _{STBYL}				0.4	V	
Standby pin input current	I _{LSTBY}	$V_{STBY} = 4.5 V$			120	μA	
Standby pin leakage current	I _{LSTBY}	V _{STBY} = 0 V	-30			μA	
FRC pin high level voltage	V _{FRCH}		1.6			V	
FRC pin low level voltage	V _{FRCL}				0.4	V	
FRC pin input current	I _{IFRC}	V _{FRC} = 4.5 V			100	μΑ	
FRC pin leakage current	ILFRC	V _{FRC} = 0 V	-30			μΑ	
Thermal shutdown operating temperature	T _{TSD}		150	180	210	°C	*
Thermal shutdown hysteresis	ΔT_{TSD}			15		°C	*
[FG Amplifier]							
Common-mode input voltage range	V _{ICR}		1.2		3.3	V	
Input offset voltage	V _{IO}		-5		+5	mV	*
Output saturation voltage	V _{SINK}	$R_L = 10 \text{ k}\Omega$			0.2	V	
Output current (sink)	I _{SINK}				2	mV	

Electrical Characteristics at Ta = 25°C, $V_{CC}1$ = 2.5 V, $V_{CC}2$ = 4.5 V, V_S = 1 V

Note: * Items marked with an asterisk are design target values and are not tested.

Pin Assignment



Block Diagram and Sample Application Circuit



Unit (resistance: Ω , capacitance: F)

Truth Table

	Source	Input			Forward/reverse	
	Sink	U	V	W	control	
	W phase \rightarrow V phase	ц	Н	L	L	
1	V phase \rightarrow W phase	11			Н	
2 -	W phase \rightarrow U phase		L	L	L	
	U phase \rightarrow W phase	11			Н	
3 -	V phase \rightarrow W phase		L	Н	L	
	W phase \rightarrow V phase	L			Н	
4 -	U phase \rightarrow V phase		н	L	L	
	V phase \rightarrow U phase				Н	
5	V phase \rightarrow U phase		L	н	L	
	U phase \rightarrow V phase				Н	
6	U phase \rightarrow W phase		Н	н	L	
	W phase \rightarrow U phase				Н	

Inputs: "H" means that the input 1 potential for the corresponding phase is at least 0.2 V higher than the input 2 potential. "L" means that the input 1 potential for the corresponding phase is at least 0.2 V lower than the input 2 potential. Forward/reverse control: "H": 1.6 V to V_{CC}2 "L": 0 V to 0.4 V

Pin Functions

Unit (resistance: Ω)

Pin No.	Symbol	Pin voltage	Equivalent circuit	Pin function
2	V _S	≤ V _{CC} 1		Power supply that provides the motor voltage and determines the output amplitude This voltage must be lower than V_{CC} 1.
3	V _{CC} 2	\ge V _{CC} 1 3 V to 10 V		Power supply that provides the voltage for the source side pre-drive PNP transistor and the FG amplifier
4	V _{CC} 1	1.8 V to 6 V		Power supply that provides all voltages other than the motor voltage, the source side pre-drive voltage and the FG amplifier voltage
5	TRC		VCC1 100 #A 200 W 200 200 200 200 200 200	Coil output waveform lower side saturation waveform detection
6	FILTER		СС1	The coil output saturation prevention function operates using an RC filter (a resistor between this pin and the TRC pin and a capacitor between this pin and ground) connected at this pin. Motor speed (r.p.m.) control can then be achieved by adjusting the voltage on pin V_S . The torque ripple correction amount can be adjusted by adjusting this RC constant.

Continued on next page.

Continued from preceding page.

Unit (resistance: Ω)

Pin No.	Symbol	Pin voltage	Equivalent circuit	Pin function
7	FC		V _{CC} 1 7 2.5k 5k 5k 5k 601707	Frequency characteristics correction The capacitor connected between this pin and ground stops closed-loop oscillation in the current control system.
8	V _H		Vcc1 B 2k B A0170B	The Hall elements are connected between this pin and V_{CC} 1. The AGC circuit adjusts the Hall bias current so that the coil output slope remains fixed. Since the Hall amplifier common-mode voltage range is reduced when a low voltage is used for V_{CC} 1, the Hall elements should be connected in parallel.
9	AGC		VCC1 VCC1 (9) 3300 A01709	A capacitor is inserted between this pin and ground. The AGC circuit controls the Hall bias current so that the coil output slope remains fixed.
10 11	FG _{IN} ⁺ FG _{IN} ⁻	1.2 V min 3.3 V max	Vcc2	FG amplifier input
12	FG _{OUT}	V _{CC} 2 max	VCC2	FG amplifier output

Continued on next page.

LB1882V

		01.0	Unit (resistance: Ω)			
Pin No.	Symbol	Pin voltage	Equivalent circuit	Pin function		
13	GND			Ground for all circuits other than the output circuits		
14	ST, BY	V _{CC} 2 max	VCC2 VCC2 50k 14 50k 50k M A01712	All circuits stop when this pin falls below 0.4 V or is open. In this state, the circuit current will be 10 μ A or lower. Set this pin to 2 V or higher to operate the LB1882V in the motor drive state.		
15	FRC	V _{CC} 2 max	VCC2 VCC1 100 #A 100k 100k 100k 100k 401713	Motor forward/reverse switching Low level: Forward (0 to 0.4 V) High level: Reverse (1.6 V to V _{CC} 2)		
16 17 18 19 20 21	W _{IN} 2 W _{IN} 1 V _{IN} 2 V _{IN} 1 U _{IN} 2 U _{IN} 1	1.2 V min 2.5 V max (V _{CC} 1 is 2.5 V when Ta is 25°C.)	21 2k 200 19 17 1k 16 17 1k 16 17 1k 16 17 10 10 10 10 10 10 10 10 10 10	W-phase Hall device input The logic high level is the state where $W_{IN}1 > W_{IN}2$. V-phase Hall device input The logic high level is the state where $V_{IN}1 > V_{IN}2$. U-phase Hall device input The logic high level is the state where $U_{IN}1 > U_{IN}1$.		
22 23 24 1	RF U _{OUT} V _{OUT} W _{OUT}		VS 3.9 23 24 1 	Output transistor ground Detecting the voltage on this pin is used to implement fixed current drive and the current limiter function. U-phase output V-phase output W-phase output		

Continued from preceding page.

LB1882V Operating Principles

The LB1882V implements a current linear drive method, and controls the motor speed with the motor power supply voltage by always preventing coil output saturation and holding the output saturation voltage fixed.

- 1. Control system (See page 8)
 - The TRC pin outputs a signal consisting of the coil output voltage lower-side envelope plus the diode rising voltage.
 - The TRC waveform, after the high-frequency components are reduced by a low-pass filter consisting of an RC circuit connected to the FILTER pin, is input to the FILTER pin. The cutoff frequency is $1/2\pi$ ·RC.
 - The FILTER pin voltage is input to the control amplifier plus side. The control amplifier minus side is connected to the reference voltage and the control amplifier operates to hold the FILTER pin at the same potential as this reference voltage. As long as this reference voltage exceeds the output transistor saturation voltage, the coil output will operate in the unsaturated state.
 - The output current (the RF current) operates as a fixed current drive, since lower-side the RF voltage, is held at a fixed level by the second stage of the control amplifier.
 - Note: The low-frequency components that are not removed by the TRC pin RC filter function as motor torque ripple correction signals.
- 2. Drive system (See page 8.)
 - The Hall element output is wave shaped by the first stage of the Hall amplifier.
 - The Hall amplifier output waveform is synthesized by the matrix amplifier, which creates a waveform phase delayed by 30°.
 - This waveform is voltage-to-current converted and is then further current amplified and output as the coil current by the power amplifier. Since the upper and lower transistor drive ratios differ here (the upper transistor drive ratio is larger), the upper side voltage waveform is saturated, and the lower-side voltage waveform is unsaturated.
 - Note: The AGC circuit controls the Hall bias current so that the matrix amplifier output waveform has a fixed amplitude.

Control System Signal Flow



- No products described or contained herein are intended for use in surgical implants, life-support systems, aerospace equipment, nuclear power control systems, vehicles, disaster/crime-prevention equipment and the like, the failure of which may directly or indirectly cause injury, death or property loss.
- Anyone purchasing any products described or contained herein for an above-mentioned use shall:
 - ① Accept full responsibility and indemnify and defend SANYO ELECTRIC CO., LTD., its affiliates, subsidiaries and distributors and all their officers and employees, jointly and severally, against any and all claims and litigation and all damages, cost and expenses associated with such use:
 - ② Not impose any responsibility for any fault or negligence which may be cited in any such claim or litigation on SANYO ELECTRIC CO., LTD., its affiliates, subsidiaries and distributors or any of their officers and employees jointly or severally.
- Information (including circuit diagrams and circuit parameters) herein is for example only; it is not guaranteed for volume production. SANYO believes information herein is accurate and reliable, but no guarantees are made or implied regarding its use or any infringements of intellectual property rights or other rights of third parties.

This catalog provides information as of July, 1998. Specifications and information herein are subject to change without notice.