

TOSHIBA PHOTO IC Si MONOLYTHIC PHOTO IC

TPS830

HIGH-SPEED OPTICAL REMOTE CONTROLLERS

CORDLESS CONTROLLERS FOR VIDEO-GAMES


ELECTRONIC ORGANIZERS AND OTHER NEW

PORTABLE INFORMATION TOOLS

IR DATA COMMUNICATION

Unit : mm

- The TPS830 is a photo IC which includes a photodiode, I-V converter, band-pass filter and AGC amplifier on a single chip.
- The device's carrier frequency is as follows
: $f_0 = 455 \text{ kHz}$ (Typ.)
- The device's supply voltage is as follows
: $V_{CC} = 5 \text{ V}$
- Visible light cut-off frequency : $\lambda > 700 \text{ nm}$
- The TLN105B and TLN221 are available as infrared LEDs for remote controllers.



Weight : 0.3 g (Typ.)

MAXIMUM RATINGS ($T_a = 25^\circ\text{C}$)

CHARACTERISTIC	SYMBOL	RATING	UNIT
Supply Voltage	V_{CC}	7	V
Output Current	I_O	± 10	μA
Operating Temperature Range	T_{opr}	$-20 \sim 60$	$^\circ\text{C}$
Storage Temperature Range	T_{stg}	$-30 \sim 100$	$^\circ\text{C}$
Soldering Temperature Range (5 s)	T_{sol}	260	$^\circ\text{C}$

980910EBA1

● TOSHIBA is continually working to improve the quality and the reliability of its products. Nevertheless, semiconductor devices in general can malfunction or fail due to their inherent electrical sensitivity and vulnerability to physical stress. It is the responsibility of the buyer, when utilizing TOSHIBA products, to observe standards of safety, and to avoid situations in which a malfunction or failure of a TOSHIBA product could cause loss of human life, bodily injury or damage to property. In developing your designs, please ensure that TOSHIBA products are used within specified operating ranges as set forth in the most recent products specifications. Also, please keep in mind the precautions and conditions set forth in the TOSHIBA Semiconductor Reliability Handbook.

● The products described in this document are subject to the foreign exchange and foreign trade laws.

● The information contained herein is presented only as a guide for the applications of our products. No responsibility is assumed by TOSHIBA CORPORATION for any infringements of intellectual property or other rights of the third parties which may result from its use. No license is granted by implication or otherwise under any intellectual property or other rights of TOSHIBA CORPORATION or others.


● The information contained herein is subject to change without notice.

OPTO-ELECTRICAL CHARACTERISTICS ($V_{CC} = 5\text{ V}$, $T_a = 25^\circ\text{C}$, $C = 1000\text{ pF}$: Note 1)

CHARACTERISTIC	SYMBOL	TEST CONDITION	MIN.	TYP.	MAX.	UNIT
Supply Voltage	V_{CC}	—	3	5	7	V
Supply Current	I_{CC}	$E = 0$	—	1.2	3.0	mA
Electromagnetic Sensitivity	E_S	(Note 5)	—	250	—	V_{p-p}/m
Transmission Range	L (Note 3)	The burst wave shown in (Note 4) is transmitted by a standard transmitter. (Note 2)	3	6	—	m
High-Level Output Voltage	V_{OH}	External light intensity $< 500\text{ lx}$ Output Current $< 10\text{ }\mu\text{A}$	4.0	—	—	V
Low-Level Output Voltage	V_{OL}		—	—	0.5	V
ON Pulse Width	T_{ON}	External light intensity $< 500\text{ lx}$ Output Current $< 10\text{ }\mu\text{A}$	16	25	40	μs
OFF Pulse Width	T_{OFF}		—	63	—	μs
Carrier Frequency	f_o	—	—	455	—	kHz
Peak Sensitivity Wavelength	λ_P	—	—	900	—	nm
Radiation Angle	θ_H	Horizontal angle, $L/2$ (Note 6)	± 55	± 63	—	$^\circ$
	θ_V	Vertical angle, $L/2$ (Note 6)	± 25	± 30	—	$^\circ$


(Note 1) : Measurements for the TPS830 are based on a standard circuit that includes a 1000 pF capacitor between V_O and GND to prevent oscillation.

(Note 2) : Standard Transmitter



In the figure above, the transmitter shall be set as the output V_{OUT} will be 80 mVpp. The TPS703 in this application has a short circuit current $I_{sc} = 1.24\text{ }\mu\text{A}$ measured at $E = 0.1\text{ mW/cm}^2$. (E is the radiant incidence using a CIE standard light source A)

(Note 3) : Transmission Range L



Maximum distance at which burst waves can be received from the transmitter unit, and at which data can be processed by the receiver unit.


Note that when signals other than the recommended burst wave are transmitted, transmission range may be reduced or a malfunction may occur.

(*) TLN105B is used as an LED for standard transmitter.


When selecting TLN221, transmission range is 1.2 times than TLN105B.

Example : 6 m (@TLN105B) $\Rightarrow$ 7.2 m (@TLN221)

(Note 4) : Burst Wave




(Note 5) : Electromagnetic Sensitivity




Mount the device between two parallel boards separated by a distance of d .
Apply voltages modulated using frequencies ranging from 10 kHz to 50 MHz across the boards and read off the voltage at which noise is generated in the output from the device.

(*) Using under strong electromagnetic fields may affect the device.
Please evaluate devices under such environment before it is actually used.

(Note 6) : Radiation Angle



Circuit Block Diagram



PRECAUTIONS

1. If a lead is formed, it should be formed at a distance of 2 mm from the body of the device. Forming the lead should not cause stress to the body of the device. Soldering must be performed after lead forming.
2. Insert a bypass condenser of up to $0.01\ \mu\text{F}$ between V_{CC} and GND near the device to stabilize the power supply line.
3. Within $100\ \mu\text{s}$ of V_{CC} turning on, the output voltage changes to stabilize the inner circuit.

