

# Coreless Coil Current Transducer

## RH 100 .. 1000-P

$I_{PN} = 100 .. 1000 A$

For the electronic measurement of currents: AC, pulsed, mixed, with a galvanic isolation between the primary circuit (high power) and the secondary circuit (electronic circuit).



### Electrical data

		Type
Primary nominal r.m.s. current		
$I_{PN}$ (A)		
100		RH 100-P
200		RH 200-P
500		RH 500-P
1000		RH 1000-P
$V_{OUT}$	Output voltage(r.m.s)@ $\pm I_{PN}$ , $R_L = 10 k\Omega$ , $T_A = 25^\circ C$	4 V
$V_C$	Supply voltage ( $\pm 5 \%$ )	$\pm 15$ V
$V_d$	R.m.s. voltage for AC isolation test, 50/60Hz, 1 mn	> 2.5 kV
$I_c$	Current consumption	10 mA
$R_{IS}$	Isolation resistance@ 500 V DC	> 500 M $\Omega$
$R_L$	Load resistance	$\geq 100$ K $\Omega$

### Accuracy-Dynamic performance data

$e_L$	Linearity (0 .. $\pm I_{PN}$ )	$\leq \pm 0.5$ % of $I_{PN}$
$V_{OE}$	Electrical offset voltage, $T_A = 25^\circ C$	$\pm 5$ mV
$V_{OT}$	Thermal drift of $V_{OE}$	$\leq \pm 0.3$ mV/K
$TCE_G$	Thermal drift of the gain (% of reading)	$\pm 0.03$ %/K
$t_r$	Response time @ 90% of $I_p$	1 $\mu s$
f	Frequency bandwidth ( $\pm 3$ dB)	20Hz .. 100KHz

### General data

$T_A$	Ambient operating temperature	-10 .. +75 $^\circ C$
$T_S$	Ambient storage temperature	-15 .. +80 $^\circ C$
m	Mass	20 g
	Min. internal creepage distance/clearance	$\varnothing 11 \pm 0.5$ mm

### Features

- No magnetic core
- Rogowski Coil principle
- Highly accurate integration circuit
- Voltage output

### Advantages

- Wide sensing range
- Wide frequency range
- Quick response
- No hysteresis error
- No insertion impedance
- Small size and lightweight

### Applications

- Observing complicated current waveforms
- High speed and high current sensing such as IGBT
- Welding
- Power unit
- Electric power regulator
- Discharge tube
- Antenna
- Monitoring for irruptive current

Notes :

040714/1

## RH 100 .. 1000-P (in mm)

