

# M02066

## 3.3 Volt Laser Driver IC for Applications to 3 Gbps Data Sheet

### Applications Information

**Please use this data sheet in conjunction with the technical information:**

M02066 Application Notes:	Note 0011 Rev 03, Note 0010 Rev 02
BCC Package Application Note:	AN0004 Rev 01
Bare Die Application Note:	Note 0024 Rev 02

## 3.3 Volt Laser Driver for Applications to 3 Gbps

## TABLE OF CONTENTS

Features .....	3
Applications .....	3
Description .....	3
Connections .....	3
Table 1 Ordering Information .....	4
Table 2 Pin Descriptions - BCC+24 .....	5
Table 3 Pin Description - TQFP 32 .....	6
Table 4 Pad Descriptions - Bare Die .....	7
Table 5 Absolute Maximum Ratings .....	8
Table 6 Recommended Operating Conditions .....	9
Table 7 AC Characteristics .....	9
Table 8 DC Characteristics .....	10
Functional Diagram .....	11
Functional Description .....	11
Overview .....	11
Modulator .....	11
Mean Power Control .....	12
Table 9 MPC Loop Bandwidth .....	12
Safety Logic .....	13
Data Input Latch .....	13
Enable Control .....	13
Current Monitors .....	13
Typical Eye Diagram .....	13
Temperature Compensation .....	14
TQFP32 Package Information .....	15
Table 10 Package Dimensions .....	15
BCC+24 Package Information .....	16
Table 11 Features .....	16
Bare Die Information .....	17
Table 12 Pad Centers .....	17
Disclaimer .....	18
Contact Information .....	19

### 3.3 Volt Laser Driver for Applications to 3 Gbps

## FEATURES

- ❑ High speed operation; suitable for applications to 3 Gbps.
- ❑ Typical rise/fall times of 90 ps.
- ❑ DC or AC coupled modulation drive.
- ❑ Differential data and clock inputs to minimize pattern dependent jitter.
- ❑ Independently Programmable Laser Bias and Modulation currents.
- ❑ Bias current to 100 mA and modulation current to 85 mA at  $V_{CC} = 3.3\text{ V}$
- ❑ Automatic Laser Power Control, with programmable temperature compensation and 'Slow-Start'.
- ❑ Bias and modulation current monitor
- ❑ Operates with +3.3 Volt supply
- ❑ Functionally compatible with MAX 3869
- ❑ The M02066-21 and M02066-51 are available in a BCC+24 package. The M02066-82 is available in a TQFP32 package.

## APPLICATIONS

- ☐ Short reach SONET/SDH
- ☐ Metro SONET/SDH
- ☐ Datacomms Modules
- ☐ Add/Drop Multiplexers
- ☐ Digital Cross Connects



## DESCRIPTION

The M02066 is a highly integrated, programmable laser driver intended for SONET/SDH applications with FEC to 3 Gbps. Using differential PECL data and clock inputs, the M02066 supplies the bias and modulation current required to drive an edge-emitting laser. The modulation output can be DC-coupled to the laser diode, giving a significant power saving over AC-coupled operation.

The M02066 includes automatic power control to maintain a constant average laser output power over temperature and life. In addition, the modulation current can be temperature compensated to minimize variation in extinction ratio over temperature.

Output flags indicate laser end of life as well as failure of the APC circuitry to maintain average output power.

## CONNECTIONS



**Note:** The M02066-21 and M02066-51 differ only in their Duty Cycle Distortion and Total Output Jitter specifications.

**3.3 Volt Laser Driver for Applications to 3 Gbps****TABLE 1 ORDERING INFORMATION**

Part Number	Pin Package
M02066-21	BCC+24 package with 20 ps or less DCD
M02066-51	BCC+24 package with 50 ps or less DCD
M02066-82	TQFP32 package with 80 ps or less DCD
M02066-EVME	BCC+24 electrical evaluation board
M02066-T-EVM	Optical evaluation board, TO-can laser

## 3.3 Volt Laser Driver for Applications to 3 Gbps

TABLE 2 \_\_\_\_\_ PIN DESCRIPTIONS - BCC+24

Pin No	Name	Function
1	CEN	Clock enable input (TTL/CMOS). Set HIGH or not connected to use CLK inputs, LOW when not using CLK inputs
2	DIS	Bias and modulation output disable (TTL/CMOS). LOW for normal operation
3	GND	Ground
4	MON	Monitor output, connect a resistor between this pin and $V_{CC}$ to monitor the sum of bias and modulation currents
5	$\overline{\text{FAIL}}$	Mean power control failure indicator (TTL/CMOS). Goes LOW when control loop is no longer able to maintain constant current at PD
6	$\overline{\text{OCA}}$	Over-current alarm (TTL/CMOS). Goes LOW when $I_{\text{BIAS}}$ exceeds the preset bias current limit
7	$V_{CC}$	Power supply
8	BIAS	Laser bias current output
9	$V_{CC}$	Power supply
10	OUT+	Positive modulation current output. Sinks current when $D_{\text{IN}}$ is HIGH
11	OUT-	Negative modulation current output. Sinks current when $\overline{D}_{\text{IN}}$ is HIGH
12	$\text{GND}_A$	Ground for output stage. (inductor to ground)
13	PD	Monitor photo diode input. This input is connected to the monitor photodiode anode for automatic power control. A resistor between this pin and ground sets the mean optical power
14	$C_{\text{MPC}}$	Mean power control loop dominant pole capacitor
15	GND	Ground
16	$\text{TC}_{\text{SLOPE}}$	Connecting a resistor between this pin and ground sets the temperature coefficient of $I_{\text{MODSET}}$ (using the internal IC temperature)
17	$\text{TC}_{\text{START}}$	Secondary temperature coefficient of $I_{\text{MOD}}$ . A resistor on this pin to ground sets the temperature at which the temperature compensation starts
18	$\text{MOD}_{\text{SET}}$	Modulation current set. Connect a resistor between this pin and ground to set
19	$\text{OCA}_{\text{SET}}$	Over current alarm set. Connect a resistor between this pin and ground to set
20	$V_{CC}$	Power supply
21	$D_{\text{IN}}$	Positive data input (PECL). Self biased
22	$\overline{D}_{\text{IN}}$	Negative data input (PECL). Self biased
23	CLK	Positive clock input (PECL). Self biased. Connect to $V_{CC}$ if not used
24	$\overline{\text{CLK}}$	Negative clock input (PECL). Self biased. Can be disconnected if not used

Note: Center pad (pad 25) is not connected but should be soldered to a ground pad for thermal dissipation

## 3.3 Volt Laser Driver for Applications to 3 Gbps

TABLE 3 \_\_\_\_\_ PIN DESCRIPTION - TQFP 32

Pin No	Name	Function
1, 4, 7, 16, 18, 21, 25, 32	V <sub>CC</sub>	Power supply
2	D <sub>IN</sub>	Positive data input (PECL). Self biased
3	$\overline{D}_{IN}$	Negative data input (PECL). Self biased
5	CLK	Positive clock input (PECL). Self biased. Connect to V <sub>CC</sub> if not used
6	$\overline{CLK}$	Negative clock input (PECL). Self biased. Can be disconnected if not used
8	CEN	Clock enable input (TTL/CMOS). Set HIGH or not connected to use CLK inputs, LOW when not using CLK inputs
9	ENA	Bias and modulation output enable (TTL/CMOS). HIGH for normal operation
10	GND	Ground
11	BIAS <sub>MON</sub>	Bias monitor and temperature- dependent bias current limit. Connect a resistor between this pin and V <sub>CC</sub> to monitor
12	MOD <sub>MON</sub>	Modulation current monitor. Connect a resistor between this pin and V <sub>CC</sub> to monitor
13	$\overline{FAIL}$	Mean power control failure indicator (TTL/CMOS). Goes LOW when control loop is no longer able to maintain constant current at I <sub>PIN</sub>
14	$\overline{OCA}$	Over-current alarm (TTL/CMOS). Goes LOW when I <sub>BIAS</sub> exceeds the preset bias current limit
15	GND	Ground
17	BIAS	Laser bias current output
19	OUT+	Positive modulation current output. Sinks current when D <sub>IN</sub> is HIGH
20	OUT-	Negative modulation current output. Sinks current when $\overline{D}_{IN}$ is HIGH
22	GND <sub>A</sub>	Ground for output stage (inductor to ground)
23	GND <sub>A</sub>	Ground for output stage (inductor to ground)
24	PD	Monitor photo diode input. This input is connected to the monitor photodiode anode for automatic power control.
26	C <sub>MPC</sub>	Mean power control dominant pole capacitor
27	NC	Not connected and may be grounded for compatibility with MAX3869
28	TC <sub>SLOPE</sub>	Connecting a resistor between this pin and ground sets the temperature coefficient of I <sub>MODSET</sub> (using the internal IC temperature)
29	MPC <sub>SET</sub>	A resistor between this pin and ground sets the mean optical power
30	MOD <sub>SET</sub>	Modulation current set. Connect a resistor between this pin and ground to set
31	OCA <sub>SET</sub>	Over current alarm set. Connect a resistor between this pin and ground to set

Note: TC<sub>START</sub> is internally connected to 0 V in the TQFP32

## 3.3 Volt Laser Driver for Applications to 3 Gbps

TABLE 4 \_\_\_\_\_ PAD DESCRIPTIONS - BARE DIE

Pad No	Name	Function
1	CEN	Clock enable input (TTL/CMOS). Set HIGH or not connected to use CLK inputs, LOW when not using CLK inputs
2	ENA	Bias and modulation output enable (TTL/CMOS). HIGH for normal operation
3	DIS	Bias and modulation output disable (TTL/CMOS). LOW for normal operation
4, 8, 10, 25, 27, 30, 34, 39, 44	GND	Ground
5	BIAS <sub>MON</sub>	Bias monitor and temperature- dependent bias current limit. Connect a resistor between this pin and V <sub>CC</sub> to monitor
6	MOD <sub>MON</sub>	Modulation current monitor. Connect a resistor between this pin and V <sub>CC</sub> to monitor
7	$\overline{\text{FAIL}}$	Mean power control failure indicator (TTL/CMOS). Goes LOW when control loop is no longer able to maintain constant current at I <sub>PIIN</sub>
9	$\overline{\text{OCA}}$	Over-current alarm (TTL/CMOS). Goes LOW when I <sub>BIAS</sub> exceeds the preset bias current limit
11, 14, 19, 33, 35, 38, 40, 43	V <sub>CC</sub>	Power supply
12	BIAS	Laser bias current output
13, 20, 21	GND <sub>A</sub>	Ground for output stage (inductor to ground)
15, 16	OUT+	Positive modulation current output. Sinks current when D <sub>IN</sub> is HIGH
17, 18	OUT-	Negative modulation current output. Sinks current when $\overline{\text{D}}_{\text{IN}}$ is HIGH
22	PD	Monitor photo diode input. This input is connected to the monitor photodiode anode for automatic power control.
24	C <sub>MPC</sub>	Mean power control dominant pole capacitor
26	TC <sub>SLOPE</sub>	Connecting a resistor between this pin and ground sets the temperature coefficient of I <sub>MODSET</sub> (using the internal IC temperature)
28	TC <sub>START</sub>	Secondary temperature coefficient of I <sub>MOD</sub> . A resistor on this pin to ground sets the temperature at which the temperature compensation starts
29	MPC <sub>SET</sub>	A resistor between this pin and ground sets the mean optical power
31	MOD <sub>SET</sub>	Modulation current set. Connect a resistor between this pin and ground to set
32	OCA <sub>SET</sub>	Over current alarm set. Connect a resistor between this pin and ground to set
36	D <sub>IN</sub>	Positive data input (PECL). Self biased
37	$\overline{\text{D}}_{\text{IN}}$	Negative data input (PECL). Self biased
41	CLK	Positive clock input (PECL). Self biased. Connect to V <sub>CC</sub> if not used
42	$\overline{\text{CLK}}$	Negative clock input (PECL). Self biased. Can be disconnected if not used

## 3.3 Volt Laser Driver for Applications to 3 Gbps

TABLE 5 ABSOLUTE MAXIMUM RATINGS

Parameter	Rating	Units
Power supply ( $V_{CC}$ -GND)	-0.5 to +6.0	V
Operating ambient	-40 to +85	°C
Storage temperature	-65 to +150	°C
Maximum laser bias current	120	mA
Maximum laser modulation current (through OUT+/OUT2+, OUT-/OUT2-)	100	mA

These are the absolute maximum ratings at or beyond which the IC can be expected to fail or be damaged. Reliable operation at these extremes for any length of time is not implied.



## 3.3 Volt Laser Driver for Applications to 3 Gbps

TABLE 6 RECOMMENDED OPERATING CONDITIONS

Parameter	Rating	Units
Power supply ( $V_{CC}$ -GND)	$3.3 \pm 10\%$	V
Junction temperature (die)	-40 to + 120	°C
Operating ambient	-40 to + 85	°C

TABLE 7 AC CHARACTERISTICS

Parameter	Conditions.	Min.	Typ.	Max.	Unit.
Differential input voltage	$= 2 \times (D_{IN\ HIGH} - D_{IN\ LOW})$ (clock inputs follow same relationship)	300	—	1860	mV
Modulation current range		2.5	—	85	mA
Modulation current with output disabled	DIS=HIGH	—	—	300	μA
Programmable range for modulation current temperature coefficient	Adjustable	500	—	$10^4$	ppm/°C
Programmable temperature at which modulation current TC compensation enables	Programmed by choice of $R_{TCSET}$	20	—	60	°C
Modulation output rise time	20% to 80% into $25\ \Omega$ <sup>(1)</sup>	—	90	—	ps
Modulation output fall time	20% to 80% into $25\ \Omega$	—	90	—	ps
Overshoot of modulation output current	Into $25\ \Omega$ load	-10	—	+10	%
Modulation output pulse width distortion	Measured using alternating 1-0 pattern			20 <sup>(2)</sup>	ps
Modulation output pulse width distortion	Measured using alternating 1-0 pattern			50 <sup>(3)</sup>	ps
Modulation output pulse width distortion	Measured using alternating 1-0 pattern			80 <sup>(4)</sup>	ps
Modulation output random jitter	rms 12 kHz to 20 MHz	—	—	4	mUI
Total output jitter (data input latch enabled)	Peak-to-peak. Measured into $25\ \Omega$ load using 1867 MHz Bessel filter: $2^{23}$ -1 PRBS at 2.488 Gbps; using clock inputs (includes PWD, random and deterministic)	—	—	42 <sup>(2)</sup>	ps
Total output jitter (data input latch enabled)	Peak-to-peak. Measured into $25\ \Omega$ load using 1867 MHz Bessel filter: $2^{23}$ -1 PRBS at 2.488 Gbps; using clock inputs (includes PWD, random and deterministic)	—	—	72 <sup>(3)</sup>	ps
Total output jitter (data input latch enabled)	Peak-to-peak. Measured into $25\ \Omega$ load using 1867 MHz Bessel filter: $2^{23}$ -1 PRBS at 2.488 Gbps; using clock inputs (includes PWD, random and deterministic)	—	—	100 <sup>(4)</sup>	ps

( $V_{CC} = +3.3\ V \pm 10\%$ ,  $T_A = 40\ ^\circ\text{C}$  to  $+85\ ^\circ\text{C}$ , unless otherwise noted)

(1)  $I_{MOD} = 28\ \text{mA}$

(2) Applies only to the M02066-21.

(3) Applies only to the M02066-51.

(4) Applies only to the M02066-82.

## 3.3 Volt Laser Driver for Applications to 3 Gbps

TABLE 8 \_\_\_\_\_ DC CHARACTERISTICS

Parameter	Conditions	Min.	Typ.	Max.	Units
Supply current	$I_{BIAS} = 50 \text{ mA}$ $I_{MOD} = 50 \text{ mA}$ Excluding $I_{BIAS}$ and $I_{MOD}$	-	57	-	mA
Supply current	$I_{BIAS} = 100 \text{ mA}$ $I_{MOD} = 85 \text{ mA}$ Excluding $I_{BIAS}$ and $I_{MOD}$	-	70	75	mA
Bias current adjust range	Limited by $OCA_{SET}$ across temperature range	2	-	100	mA
Bias current with output disabled	$Tx\_Disable = HIGH$	-	-	300	$\mu A$
Maximum bias current limit	$T_A = +85^\circ C$ (adjustable)	100 <sup>(1)</sup>	-	-	mA
Change in $OCA_{SET}$ over temperature		-	200	-	$\mu A/^\circ C$
Monitor diode reverse bias voltage		-	2.1	-	V
Monitor diode current adjustment range		10	-	1500	$\mu A$
TTL/CMOS input HIGH voltage (CEN, DIS)		2.0	-	-	V
TTL/CMOS input LOW voltage (CEN, DIS)		-	-	0.8	V
CMOS output HIGH voltage (FAIL, $\overline{OCA}$ )		2.4	-	-	V
CMOS output LOW voltage (FAIL, $\overline{OCA}$ )		-	-	0.4	V
Differential input impedance	Data and clock inputs	2.5	-	-	$k\Omega$
Common-mode input voltage		$V_{CC}-1.7$		$V_{CC}-(V_{IN}(Diff)/4)$	V
Self-biased common mode input voltage	Data and clock inputs	$V_{CC}-1.7$	-	$V_{CC}-0.47$	V


(  $V_{CC} = +3.3 \text{ V} \pm 10\%$ ,  $T_A = 40^\circ C$  to  $+85^\circ C$ , unless otherwise noted)

(1)  $R_{OCA_{SET}} = 0 \Omega$

### 3.3 Volt Laser Driver for Applications to 3 Gbps

## FUNCTIONAL DIAGRAM

**Fig. 3**




## FUNCTIONAL DESCRIPTION

## Overview

The M02066 laser driver consists of a high-speed modulation driver and a laser bias generator with mean power control (MPC). It is optimized for high speed, low power operation at 3.3V supply. To minimize the pattern-dependent jitter of the input signal, the device accepts an input clock signal for data retiming. This feature can be enabled using the external CEN pin.

**Fig. 4**



### **Modulator**

The M02066 modulation output is optimized for driving a 25  $\Omega$  load; the minimum required voltage at OUT+ and OUT- is 0.6V. To interface with the laser diode, a matching resistor (RD) is required for impedance matching. An RC shunt network is necessary to compensate for the laser diode parasitic inductance, thereby improving the optical eye.

Typical values are  $R_{SHUNT} = 39 \Omega$ ,  $C_{SHUNT} = 3.9 \text{ pF}$ .

These values will need to be optimized for a specific laser. Any capacitive loading at the cathode of a laser diode will degrade the optical output performance. An inductor is used to isolate the BIAS pin from the laser cathode. See Fig. 3.

The modulator output stage is designed to drive up to 85mA in either AC-coupled or DC-coupled mode. DC-coupled performance depends on the laser used.

R<sub>MODSET</sub> determines the modulation current according to the following formula:  $I_{MOD} = 350/R_{MODSET}$

Fig. 4 shows the modulation current for a given  $R_{MODSET}$  resistor.

## 3.3 Volt Laser Driver for Applications to 3 Gbps

## FUNCTIONAL DESCRIPTION

**Mean Power Control**

To maintain constant average optical power, the M02066 incorporates a control loop to compensate for the changes in laser threshold current over temperature and lifetime. A monitor photodiode mounted in the laser package is used to convert the optical power into a photocurrent. The MPC loop adjusts the laser bias current so that the voltage at PD is matched to an on-chip reference voltage. The external resistor ( $R_{MPCSET}$ ) sets the optical power.

$$R_{MPCSET} = 1.28/I_{PIN}$$


$I_{PIN}$  is the mean current from the monitor photodiode at the required mean laser power level (see laser datasheet). The time constant of the loop is determined by  $C_{MPC}$ . In some applications the internal capacitance at  $C_{MPC}$  may be sufficient and an external  $C_{MPC}$  will not be required.

**TABLE 9 MPC LOOP BANDWIDTH**

$C_{MPC}$	6 dB cutoff frequency
0	17 MHz
1 nF	100 kHz
10 nF	10 kHz
100 nF	1 kHz


(at 6 dB cut off frequency) vs  $C_{MPC}$  (for nominal process)

Fig. 5 shows the bias current vs  $R_{MPCSET}$  over the full operating temperature range.



There are two safety features integrated into the MPC loop; an Over-Current Alarm and an MPC loop failure alarm.

The **Over-Current Alarm** (OCA) circuit limits the maximum bias current generated by the M02066. The bias current limit is set by an external resistor to ground,  $R_{OCA}$ . When this limit is exceeded the OCA pin is asserted LOW. Fig. 6 shows the maximum bias current limit vs  $R_{OCA}$ .



## 3.3 Volt Laser Driver for Applications to 3 Gbps

## FUNCTIONAL DESCRIPTION

**Safety Logic**

Safety logic is provided in order to limit the maximum bias current. The bias current at which the safety logic trips is set by an external resistor to ground ( $R_{OCA}$ ) from the  $OCA_{SET}$  pin. When the bias current limit is reached alarm flag OCA is asserted LOW. A loop failure alarm is also provided to detect when the bias current can no longer be adjusted to achieve the desired average optical power.

**Data Input Latch**

To minimize input data pattern-dependent jitter, a differential clock signal can be connected to the data input latch. If CEN is HIGH, the input data is retimed by the rising edge of CLK+. If CEN is LOW, the input data is directly connected to the output stage. If CEN is left floating it will be pulled HIGH by the internal circuitry. When this latch function is not used, connect CLK+ to  $V_{CC}$  and leave CLK- unconnected.

**Enable Control**

The M02066 incorporates a dual laser driver enable function. When ENA is LOW or DIS is HIGH, both the bias and modulation currents are off. DIS and ENA are available on the M02066 die only, DIS is available on the BCC package only, ENA is available on the TQFP package.


**Current Monitors**

The M02066 features bias and modulation current monitor outputs. The  $BIAS_{MON}$  output sinks a current equal to nominally 1/60 of the laser bias current ( $I_{BIAS}$ ). The  $MOD_{MON}$  output sinks a current equal to nominally 1/60 of the laser peak to peak modulation current ( $I_{MOD}$ ).  $BIAS_{MON}$  and  $MOD_{MON}$  should be connected through a pull-up resistor to  $V_{CC}$ . Choose a pull-up resistor value that ensures a voltage at  $BIAS_{MON}$  greater than  $V_{CC} - 1.6V$  and a voltage at  $MOD_{MON}$  greater than  $V_{CC} - 1.0V$ . These pins should be tied to  $V_{CC}$  if not used.

## TYPICAL EYE DIAGRAM

Fig. 7

2.5 Gbps optical eye @ -3 dBm  
(1.87 GHz filter)



## 3.3 Volt Laser Driver for Applications to 3 Gbps

## FUNCTIONAL DESCRIPTION

**Temperature Compensation**

The reduction in slope efficiency of typical laser diodes caused by increased temperature can be compensated by utilising the  $TC_{START}$  and  $TC_{SLOPE}$  features of the M02066. Under closed loop conditions the average optical power will be maintained by the Mean Power Control loop, compensating for factors such as temperature and age.

However, as the laser slope efficiency reduces with increasing temperature the laser diode will require a greater peak to peak current swing in order to maintain the same peak to peak optical output swing. To this end the M02066 senses temperature and can be programmed to increase the modulation current amplitude accordingly.

Two external resistors are used to program the temperature compensation.

The temperature ( $TC_{START}$ ) at which the compensation begins to take effect is set by a resistor ( $R_{TC_{START}}$ ) from the  $TC_{START}$  pin to ground. The rate of increase of modulation current with temperature (beyond  $TC_{START}$ ) is set by a resistor ( $R_{TC_{SLOPE}}$ ) from the  $TC_{SLOPE}$  pin to ground.


As a safety feature, the M02066 limits the increased modulation current to twice the initial (ambient) modulation current.

The effects of the two programming resistors are shown schematically in the Temperature Compensation graph below.

If using the TQFP package; only  $TC_{SLOPE}$  is programmable,  $TC_{START}$  is connected to 0 V.

For more details on temperature compensation see the appropriate applications note.

## TEMPERATURE COMPENSATION



## 3.3 Volt Laser Driver for Applications to 3 Gbps

## TQFP32 PACKAGE INFORMATION

Fig. 9




TABLE 10

TQFP32 PACKAGE DIMENSIONS

Dim	Tol.	5 x 5 x 1.0 mm	Dim	Tol.	5 x 5 x 1.0 mm
N	Lead count	32	e	Typ.	0.50
A	Max.	1.20	b	±0.05	0.22
A1	±0.05	0.05	0	***	0° - 7°
A2	±0.05	1.00	01	±4°	6°
A3	±0.05	0.4365	R	Max.	0.15
D	±0.15	7.00	R1	Typ.	0.15
D1	±0.05	5.00	aaa	Max.	0.08
E	±0.15	7.00	ccc	Max.	0.08
E1	±0.05	5.00	F1	±0.10	2.67
L	+0.15/-0.15	0.60	F2	±0.10	2.67
L1	Ref.	1.00			

## BCC+24 PACKAGE INFORMATION

**Fig. 10**

**TABLE 11** \_\_\_\_\_ **FEATURES**

	DIE	BCC+24	TQFP
ENA	YES	NO	YES
DIS	YES	YES	NO
BIAS <sub>MON</sub>	YES	(1)	YES
MOD <sub>MON</sub>	YES	(1)	YES
TEMPCOMP	YES	YES	(2)
SIZE (mm)	1.79 x 1.72	4 x 4	5 x 5

(2)  $R_{TCSTART} = 0 \Omega$  (internally bonded)  $R_{TCSLOPE}$  can be used on pin 28.



## 3.3 Volt Laser Driver for Applications to 3 Gbps

## BARE DIE INFORMATION

Fig. 11




TABLE 12 PAD CENTERS

PIN	X	Y	PIN	X	Y	PIN	X	Y	PIN	X	Y
CEN	-727	550	BIAS	-550	-711	V <sub>CC</sub>	727	-550	GND	550	711
ENA	-727	440	GND <sub>A</sub>	-440	-711	C <sub>MPC</sub>	727	-440	V <sub>CC</sub>	440	711
DIS	-727	330	V <sub>CC</sub>	-330	-711	GND	727	-33-	D <sub>IN</sub>	330	711
GND	-727	220	*OUTP	-210	-711	TC <sub>SLOPE</sub>	727	-220	D <sub>IN</sub>	220	711
BIAS <sub>MON</sub>	-727	110	*OUTP	-210	-711	GND	727	-110	V <sub>CC</sub>	110	711
MOD <sub>MON</sub>	-727	0	*OUTN	100	-711	TC <sub>START</sub>	727	0	GND	0	711
FAIL	-727	-110	*OUTN	100	-711	MPC <sub>SET</sub>	727	110	V <sub>CC</sub>	-110	711
GND	-727	-220	V <sub>CC</sub>	220	-711	GND	727	220	CLK	-220	711
OCA	-727	-330	GND <sub>A</sub>	330	-711	MOD <sub>SET</sub>	727	330	CLK	-330	711
GND	-727	-440	GND <sub>A</sub>	440	-711	OCA <sub>SET</sub>	727	440	V <sub>CC</sub>	-440	711
V <sub>CC</sub>	-727	-550	PD	550	-711	V <sub>CC</sub>	727	550	GND	-550	711

Note: \* Single pad/double bond

### 3.3 Volt Laser Driver for Applications to 3 Gbps

---

**DISCLAIMER**

© 2003, 2004 Mindspeed Technologies™, Inc. All rights reserved.

Information in this document is provided in connection with Mindspeed Technologies™ ("Mindspeed™") products. These materials are provided by Mindspeed as a service to its customers and may be used for informational purposes only. Except as provided in Mindspeed's Terms and Conditions of Sale for such products or in any separate agreement related to this document, Mindspeed assumes no liability whatsoever. Mindspeed assumes no responsibility for errors or omissions in these materials. Mindspeed may make changes to specifications and product descriptions at any time, without notice. Mindspeed makes no commitment to update the information and shall have no responsibility whatsoever for conflicts or incompatibilities arising from future changes to its specifications and product descriptions. No license, express or implied, by estoppel or otherwise, to any intellectual property rights is granted by this document.

THESE MATERIALS ARE PROVIDED "AS IS" WITHOUT WARRANTY OF ANY KIND, EITHER EXPRESS OR IMPLIED, RELATING TO SALE AND/OR USE OF MINDSPEED PRODUCTS INCLUDING LIABILITY OR WARRANTIES RELATING TO FITNESS FOR A PARTICULAR PURPOSE, CONSEQUENTIAL OR INCIDENTAL DAMAGES, MERCHANTABILITY, OR INFRINGEMENT OF ANY PATENT, COPYRIGHT OR OTHER INTELLECTUAL PROPERTY RIGHT. MINDSPEED FURTHER DOES NOT WARRANT THE ACCURACY OR COMPLETENESS OF THE INFORMATION, TEXT, GRAPHICS OR OTHER ITEMS CONTAINED WITHIN THESE MATERIALS. MINDSPEED SHALL NOT BE LIABLE FOR ANY SPECIAL, INDIRECT, INCIDENTAL, OR CONSEQUENTIAL DAMAGES, INCLUDING WITHOUT LIMITATION, LOST REVENUES OR LOST PROFITS, WHICH MAY RESULT FROM THE USE OF THESE MATERIALS.

Mindspeed products are not intended for use in medical, lifesaving or life sustaining applications. Mindspeed customers using or selling Mindspeed products for use in such applications do so at their own risk and agree to fully indemnify Mindspeed for any damages resulting from such improper use or sale.

**Headquarters**

---

**Newport Beach**

Mindspeed Technologies  
4000 MacArthur Boulevard, East Tower  
Newport Beach, CA 92660  
Phone: (949) 579-3000  
Fax: (949) 579-3020

**MINDSPEED™**

[www.mindspeed.com](http://www.mindspeed.com)