



TERMINAL CODE

- 1 V_{UPC}
- 2 U_{FO}
- 3 U_P
- 4 V_{UP1}
- 5 V_{VPC}
- 6 V_{FO}
- 7 V_P
- 8 V_{VP1}
- 9 NC
- 10 NC
- 11 NC
- 12 NC
- 13 V_{NC}
- 14 V_{N1}
- 15 NC
- 16 U_N
- 17 V_N
- 18 NC
- 19 F_O

Outline Drawing and Circuit Diagram

| Dim. | Inches | Millimeters |
|------|-----------|-------------|
| A | 3.54 | 90.0 |
| B | 1.97 | 50.0 |
| C | 0.98 | 25.0 |
| D | 3.15 | 80.0 |
| E | 0.20 | 5.0 |
| F | 0.39 | 10.0 |
| G | 0.08 | 2.0 |
| H | 0.17 Dia. | 4.3 Dia. |
| J | 0.81 | 20.5 |
| K | 0.91 | 23.0 |

| Dim. | Inches | Millimeters |
|------|----------|-------------|
| L | 0.47 | 12.0 |
| M | 0.012 | 0.3 |
| N | 0.57 | 14.6 |
| P | 0.26 | 6.7 |
| Q | 0.02 | 0.5 |
| R | 0.56 | 14.2 |
| S | 0.02 Sq. | 0.5 Sq. |
| T | 0.08 | 2.0 |
| U | 0.51 | 13.0 |
| V | 0.65 | 16.5 |



Description:

Powerex Intellimod™ Photo Voltaic Intelligent Power Modules are isolated base modules designed for single phase power switching applications. Built-in control circuits provide optimum gate drive and protection for the IGBT and free-wheel diode power devices.

Features:

- Complete Output Power Circuit
- Gate Drive Circuit
- Protection Logic
 - Short Circuit
 - Over Temperature Using On-chip Temperature Sensing
 - Under Voltage
- Low Loss Using Full Gate CSTBT IGBT Chip

Applications:

- PV Inverters
- PV UPS
- PV Power Supplies

Ordering Information:

Example: Select the complete part number from the table below -i.e. PM75B4L1C060 is a 600V, 75 Ampere PV-IPM.

| Type | Current Rating Amperes | V _{CEs} Volts (x 10) |
|------|---------------------------|----------------------------------|
| PM | 75 | 60 |



Powerex, Inc., 173 Pavilion Lane, Youngwood, Pennsylvania 15697 (724) 925-7272 www.pwr.com

PM75B4L1C060
Photo Voltaic IPM
H-Bridge
75 Amperes/600 Volts

Absolute Maximum Ratings, $T_j = 25^\circ\text{C}$ unless otherwise specified

| Characteristics | Symbol | PM75B4L1C060 | Units |
|--|------------------------|--------------|------------------|
| Power Device Junction Temperature | T_j | -20 to 150 | $^\circ\text{C}$ |
| Storage Temperature | T_{stg} | -40 to 125 | $^\circ\text{C}$ |
| Mounting Torque, M4 Mounting Screws (Typical) | — | 15 | in-lb |
| Module Weight (Typical) | — | 135 | Grams |
| Supply Voltage, Surge (Applied between P-N) | $V_{\text{CC(surge)}}$ | 500 | Volts |
| Operation of Short Circuit Protections (Applied between P-N, $V_D = 13.5 \sim 16.5\text{V}$, Inverter Part, $T_j = 125^\circ\text{C}$ Start) | $V_{\text{CC(prot.)}}$ | 450 | Volts |
| Isolation Voltage (60Hz, Sinusoidal, RMS, Charged Part to Base, AC 1 Minute) | V_{ISO} | 2500 | Volts |

Inverter Part

| | | | |
|--|------------------|-----|---------|
| Collector-Emitter Voltage ($V_D = 15\text{V}$, $V_{\text{CIN}} = 15\text{V}$) | V_{CES} | 600 | Volts |
| Collector Current ($T_C = 25^\circ\text{C}$) | I_C | 75 | Amperes |
| Collector Current (Pulse) | I_{CRM} | 150 | Amperes |
| Total Power Dissipation ($T_C = 25^\circ\text{C}$) | P_{tot} | 201 | Watts |
| Emitter Current ($T_C = 25^\circ\text{C}$, FWDi Current) | I_E | 75 | Amperes |
| Emitter Current (Pulse, FWDi Current) | I_{ERM} | 150 | Amperes |

Control Part

| | | | |
|---|------------------|----|-------|
| Supply Voltage (Applied between $V_{\text{UP1}}-V_{\text{UPC}}$, $V_{\text{VP1}}-V_{\text{VPC}}$, $V_{\text{N1}}-V_{\text{Nc}}$) | V_D | 20 | Volts |
| Input Voltage (Applied between U_P-V_{UPC} , V_P-V_{VPC} , $U_N-V_N-W_N-BR-V_{\text{Nc}}$) | V_{CIN} | 20 | Volts |
| Fault Output Supply Voltage (Applied between $U_{\text{FO}}-V_{\text{UPC}}$, $V_{\text{FO}}-V_{\text{VPC}}$, F_O-V_{Nc}) | V_{FO} | 20 | Volts |
| Fault Output Supply Current (Sink Current at U_{FO} , V_{FO} , F_O Terminals) | I_{FO} | 20 | mA |

PM75B4L1C060
Photo Voltaic IPM
H-Bridge
 75 Amperes/600 Volts

Electrical and Mechanical Characteristics, $T_j = 25^\circ\text{C}$ unless otherwise specified

| Characteristics | Symbol | Test Conditions | Min. | Typ. | Max. | Units |
|---|---------------|--|------|------|------|------------------|
| Inverter Part | | | | | | |
| Collector-Emitter Saturation Voltage | $V_{CE(sat)}$ | $V_D = 15V, I_C = 75A, V_{CIN} = 0V,$ Pulsed, $T_j = 25^\circ\text{C}$ | — | 2.2 | 2.7 | Volts |
| | | $V_D = 15V, I_C = 75A, V_{CIN} = 0V,$ Pulsed, $T_j = 125^\circ\text{C}$ | — | 2.2 | 2.7 | Volts |
| Emitter-Collector Voltage | V_{EC} | $I_E = 75A, V_D = 15V, V_{CIN} = 15V$ | — | 2.4 | 3.3 | Volts |
| Switching Times | t_{on} | | 0.1 | 0.5 | 1.2 | μs |
| | t_{rr} | $V_D = 15V, V_{CIN} = 0 \leftrightarrow 15V$ | — | 0.1 | 0.2 | μs |
| | $t_{C(on)}$ | $V_{CC} = 300V, I_C = 75A,$ | — | 0.15 | 0.3 | μs |
| | t_{off} | $T_j = 125^\circ\text{C},$ Inductive Load | — | 1.1 | 2.0 | μs |
| | $t_{C(off)}$ | | — | 0.2 | 0.4 | μs |
| Collector-Emitter Cutoff Current | I_{CES} | $V_{CE} = V_{CES}, V_D = 15V, V_{CIN} = 15V, T_j = 25^\circ\text{C}$ | — | — | 1.0 | mA |
| | | $V_{CE} = V_{CES}, V_D = 15V,$ | — | — | 10 | mA |
| | | $V_{CIN} = 15V, T_j = 125^\circ\text{C}$ | — | — | — | — |
| Control Part | | | | | | |
| Circuit Current | I_D | $V_D = 15V, V_{CIN} = 15V, V_{N1}-V_{NC}$ | — | 6.5 | 12 | mA |
| | | $V_D = 15V, V_{CIN} = 15V, V_{P1}-V_{PC}$ | — | 1.6 | 4 | mA |
| Input ON Threshold Voltage | $V_{th(on)}$ | Applied between $U_P-V_{UPC},$ | 1.2 | 1.5 | 1.8 | Volts |
| Input OFF Threshold Voltage | $V_{th(off)}$ | $V_P-V_{VPC}, U_N- V_N- W_N-Br-V_{NC}$ | 1.7 | 2.0 | 2.3 | Volts |
| Short Circuit Trip Level | SC | $-20^\circ\text{C} \leq T_j \leq 125^\circ\text{C}, V_D = 15V$ | 112 | — | — | Amperes |
| Short Circuit Current Delay Time | $t_{off(SC)}$ | $V_D = 15V$ | — | 0.2 | — | μs |
| Over Temperature Protection | OT | Trip Level | 135 | — | — | $^\circ\text{C}$ |
| (Detect Temperature of IGBT) | $OT_{(hys)}$ | Hysteresis | — | 20 | — | $^\circ\text{C}$ |
| Supply Circuit Under-voltage Protection | UV_t | Trip Level | 11.5 | 12.0 | 12.5 | Volts |
| | UV_r | Reset Level | — | 12.5 | — | Volts |
| Fault Output Current | $I_{FO(H)}$ | $V_D = 15V, V_{FO} = 15V$ | — | — | 0.01 | mA |
| | $I_{FO(L)}$ | $V_D = 15V, V_{FO} = 15V$ | — | 10 | 15 | mA |
| Fault Output Pulse Width*2 | t_{FO} | $V_D = 15V$ | 1.0 | 1.8 | — | ms |

*2 Fault output is given only when the internal SC, OT and UV protections schemes of either upper or lower device operate to protect it.
 Fault output of SC protection given pulse. Fault output of OT, UV protection given pulse while over trip level.



Powerex, Inc., 173 Pavilion Lane, Youngwood, Pennsylvania 15697 (724) 925-7272 www.pwr.com

PM75B4L1C060
Photo Voltaic IPM
H-Bridge
 75 Amperes/600 Volts

Thermal Characteristics, $T_j = 25^\circ\text{C}$ unless otherwise specified

| Characteristic | Symbol | Condition | Min. | Typ. | Max. | Units |
|-------------------------------------|----------------|--|------|-------|------|-----------------------|
| Junction to Case Thermal Resistance | $R_{th(j-c)Q}$ | Inverter IGBT (Per 1 Element)*1 | — | — | 0.62 | $^\circ\text{C/Watt}$ |
| | $R_{th(j-c)D}$ | Inverter FWDi (Per 1 Element)*1 | — | — | 1.06 | $^\circ\text{C/Watt}$ |
| Contact Thermal Resistance | $R_{th(c-f)}$ | Case to Fin (Per 1 Element)*1, Thermal Grease Applied | — | 0.060 | — | $^\circ\text{C/Watt}$ |

Recommended Conditions for Use

| Characteristic | Symbol | Condition | Value | Units |
|---------------------------------|----------------|--|----------------|---------------|
| Inverter Supply Voltage | V_{CC} | Applied across P-N Terminals | ≤ 450 | Volts |
| Control Supply Voltage*3 | V_D | Applied between V_{UP1} - V_{UPC} , V_{VP1} - V_{VPC} , V_{N1} - V_{NC} | 15.0 ± 1.5 | Volts |
| Input ON Voltage | $V_{CIN(on)}$ | Applied between U_P - V_{UPC} , | ≤ 0.8 | Volts |
| Input OFF Voltage | $V_{CIN(off)}$ | V_P - V_{VPC} , U_N - V_{N1} - W_N -Br- V_{NC} | ≥ 9.0 | Volts |
| PWM Input Frequency | f_{PWM} | Using Application Circuit Input Signal of IPM, 3-Phase Sinusoidal PWM VVVF Inverter | ≤ 20 | kHz |
| Arm Shoot-through Blocking Time | t_{DEAD} | For IPMs Each Input Signals | ≥ 2.0 | μs |

*1 When using this value, $R_{th(s-a)}$ should be measured just under the chips.

*3 With ripple satisfying the following conditions: dv/dt swing $\leq 5\text{V}/\mu\text{s}$; variation $\leq 2\text{V}$ peak-to-peak.