


200 mA very low quiescent current linear regulator IC

Datasheet - production data



Features

- Input voltage from 1.5 to 5.5 V
- Ultra low dropout voltage (200 mV typ. at 200 mA load)
- Very low quiescent current (20 μ A typ at no load, 0.03 μ A typ in off mode)
- Output voltage tolerance: $\pm 0.5\%$ (A version) or $\pm 2.0\%$ @ 25 °C (standard version)
- 200 mA guaranteed output current
- High PSRR (80 dB@1 kHz, 50 db@100 kHz)
- Wide range of output voltages available on request: from 0.8 V up to 5.0 V in 50 mV step
- Logic-controlled electronic shutdown
- Internal soft-start
- Optional output voltage discharge feature
- Compatible with ceramic capacitor $C_{OUT} = 0.47 \mu F$
- Internal constant current and thermal protections
- Available in DFN 1x1-4L
- Operating temperature range: -40 °C to 125 °C

Applications

- Mobile phones
- Personal digital assistants (PDAs)
- Digital still cameras (DSC)
- Cordless phones and similar battery-powered systems
- Portable media players

Description

The LD39020 high accuracy voltage regulator provides 200 mA of maximum current from an input voltage ranging from 1.5 V to 5.5 V, with a typical dropout voltage of 200 mV.

It is available in DFN 1x1-4L package, allowing the maximum space saving.

The device is stabilized with a ceramic capacitor on the output. The ultra low drop voltage, low quiescent current and low noise features, together with the internal soft-start circuit, make the LD39020 suitable for low power battery-operated applications.

An enable logic control function puts the LD39020 in shutdown mode allowing a total current consumption lower than 0.1 μ A. Constant current and thermal protection are provided.

Contents

| | | |
|-----------|-----------------------------------|-----------|
| 1 | Diagram | 5 |
| 2 | Pin configuration | 6 |
| 3 | Typical application | 7 |
| 4 | Maximum ratings | 8 |
| 5 | Electrical characteristics | 9 |
| 6 | Application information | 12 |
| 6.1 | Soft start function | 12 |
| 6.2 | Output discharge function | 12 |
| 6.3 | Input and output capacitors | 12 |
| 7 | Typical characteristics | 13 |
| 8 | Package mechanical data | 18 |
| 8.1 | DFN4 1x1 package info | 19 |
| 9 | Order codes | 22 |
| 10 | Revision history | 25 |

List of tables


| | |
|---|----|
| Table 1: Pin description | 6 |
| Table 2: Absolute maximum ratings | 8 |
| Table 3: Thermal data..... | 8 |
| Table 4: ESD Performance | 8 |
| Table 5: Electrical characteristics for LD39020T, LD39020DT | 9 |
| Table 6: Electrical characteristics for LD39020AT, LD39020ADT | 10 |
| Table 7: DFN 1x1-4L mechanical data | 20 |
| Table 8: Order codes | 22 |
| Table 9: Document revision history | 25 |

List of figures

| | |
|--|----|
| Figure 1: Block diagram | 5 |
| Figure 2: Pin connection (top view) | 6 |
| Figure 3: Typical application circuits | 7 |
| Figure 4: Output voltage vs. temperature ($I_{OUT} = 1 \text{ mA}$) | 13 |
| Figure 5: Output voltage vs. temperature ($I_{OUT} = 200 \text{ mA}$) | 13 |
| Figure 6: Line regulation vs. temperature | 13 |
| Figure 7: Load regulation vs. temperature | 13 |
| Figure 8: Quiescent current vs. temperature ($I_{OUT} = 0 \text{ mA}$) | 14 |
| Figure 9: Quiescent current vs. temperature ($I_{OUT} = 200 \text{ mA}$) | 14 |
| Figure 10: Shutdown current vs. temperature | 14 |
| Figure 11: Quiescent current vs. load current | 14 |
| Figure 12: Quiescent current vs. input voltage | 14 |
| Figure 13: Dropout voltage vs temperature | 14 |
| Figure 14: Supply voltage rejection vs. frequency | 15 |
| Figure 15: Supply voltage rejection vs. input voltage | 15 |
| Figure 16: Output noise spectral density | 15 |
| Figure 17: Stability area vs (C_{OUT} , ESR) | 15 |
| Figure 18: Enable startup ($V_{OUT} = 1 \text{ V}$) | 15 |
| Figure 19: Enable startup ($V_{OUT} = 5 \text{ V}$) | 15 |
| Figure 20: Turn-on time ($V_{OUT} = 1 \text{ V}$) | 16 |
| Figure 21: Turn-off time ($V_{OUT} = 1 \text{ V}$) | 16 |
| Figure 22: Turn-on time ($V_{OUT} = 5 \text{ V}$) | 16 |
| Figure 23: Turn-off time ($V_{OUT} = 5 \text{ V}$) | 16 |
| Figure 24: Line transient ($V_{OUT} = 1 \text{ V}$) | 16 |
| Figure 25: Line transient ($V_{OUT} = 5 \text{ V}$) | 16 |
| Figure 26: Load transient ($V_{OUT} = 1 \text{ V}$) | 17 |
| Figure 27: Load transient ($V_{OUT} = 5 \text{ V}$) | 17 |
| Figure 28: DFN 1x1-4L drawing | 19 |
| Figure 29: DFN 1x1-4L footprint | 21 |

1 Diagram

Figure 1: Block diagram



The output discharge MOSFET is optional.

2 Pin configuration

Figure 2: Pin connection (top view)





Table 1: Pin description

| Pin n° | Symbol | Function |
|-------------|--------|---|
| 1 | OUT | Output voltage |
| 2 | GND | Common ground |
| 3 | EN | Enable pin logic input: Low = shutdown, High = active |
| 4 | IN | Input voltage |
| Thermal pad | GND | Connect to GND on the PCB |

3 Typical application

Figure 3: Typical application circuits



4 Maximum ratings

Table 2: Absolute maximum ratings

| Symbol | Parameter | Value | Unit |
|-----------|--------------------------------------|-------------------------|------|
| V_{IN} | Input voltage | - 0.3 to 7 | V |
| V_{OUT} | Output voltage | - 0.3 to $V_{IN} + 0.3$ | V |
| V_{EN} | Enable input voltage | - 0.3 to 7 | V |
| I_{OUT} | Output current | Internally limited | mA |
| P_D | Power dissipation | Internally limited | mW |
| T_{STG} | Storage temperature range | - 40 to 150 | °C |
| T_{OP} | Operating junction temperature range | - 40 to 125 | °C |



Absolute maximum ratings are those values beyond which damage to the device may occur. Functional operation under these conditions is not implied. All values are referred to GND

Table 3: Thermal data

| Symbol | Parameter | Value | Unit |
|------------|-------------------------------------|-------|------|
| R_{thJA} | Thermal resistance junction-ambient | 250 | °C/W |

Table 4: ESD Performance

| Symbol | Parameter | Test conditions | Value | Unit |
|--------|------------------------|-----------------|-------|------|
| ESD | ESD Protection voltage | HBM | 4 | kV |
| | | MM | 400 | V |
| | | CDM | 500 | V |

5 Electrical characteristics

$T_J = 25^\circ\text{C}$, $V_{IN} = V_{OUT(NOM)} + 1\text{ V}$, $C_{IN} = C_{OUT} = 1\text{ }\mu\text{F}$, $I_{OUT} = 1\text{ mA}$, $V_{EN} = V_{IN}$, unless otherwise specified.

Table 5: Electrical characteristics for LD39020T, LD39020DT

| Symbol | Parameter | Test conditions | Min. | Typ. | Max. | Unit |
|------------------|---------------------------------------|---|------|------|------|---------------------|
| V_{IN} | Operating input voltage | | 1.5 | | 5.5 | V |
| V_{OUT} | V_{OUT} accuracy | $I_{OUT} = 1\text{ mA}$, $T_J = 25^\circ\text{C}$ | -2 | | 2 | % |
| | | $I_{OUT} = 1\text{ mA}$, $-40^\circ\text{C} < T_J < 125^\circ\text{C}$ | -3 | | 3 | % |
| ΔV_{OUT} | Static line regulation ⁽¹⁾ | $V_{OUT(NOM)} + 1\text{ V} \leq V_{IN} \leq 5.5\text{ V}$, $I_{OUT} = 10\text{ mA}$ | | 0.02 | | %/V |
| | | $-40^\circ\text{C} < T_J < 125^\circ\text{C}$ | | | 0.2 | |
| ΔV_{OUT} | Static load regulation | $I_{OUT} = 0\text{ mA}$ to 200 mA | | 10 | | mV |
| | | $-40^\circ\text{C} < T_J < 125^\circ\text{C}$ | | | 0.01 | %/mA |
| V_{DROP} | Dropout voltage | $I_{OUT} = 30\text{ mA}$, $V_{OUT} = 2.8\text{ V}$ | | 35 | | mV |
| | | $I_{OUT} = 200\text{ mA}$, $V_{OUT} = 2.8\text{ V}$ $-40^\circ\text{C} < T_J < 125^\circ\text{C}$ | | 200 | 350 | |
| e_N | Output noise voltage | 10 Hz to 100 kHz , $I_{OUT} = 10\text{ mA}$ | | 45 | | μV_{RMS} |
| SVR | Supply voltage rejection | $V_{IN} = V_{OUT(NOM)} + 1\text{ V} \pm V_{RIPPLE}$ $V_{RIPPLE} = 0.2\text{ V}$ Freq. $= 1\text{ kHz}$ $I_{OUT} = 30\text{ mA}$ | | 80 | | dB |
| | | $V_{IN} = V_{OUT(NOM)} + 1\text{ V} \pm V_{RIPPLE}$ $V_{RIPPLE} = 0.2\text{ V}$ Freq. $= 100\text{ kHz}$ $I_{OUT} = 30\text{ mA}$ | | 55 | | |
| I_Q | Quiescent current | $I_{OUT} = 0\text{ mA}$ | | 20 | 40 | μA |
| | | $I_{OUT} = 200\text{ mA}$ | | 100 | | |
| $I_{Standby}$ | Standby Current | V_{IN} input current in OFF MODE: $V_{EN} = \text{GND}$ | | 0.03 | 1 | μA |
| I_{SC} | Short circuit current | $R_L = 0$ | 250 | 350 | | mA |
| R_{ON} | Output voltage discharge MOSFET | (only on LD39020DT) | | 100 | | Ω |
| V_{EN} | Enable input logic low | $V_{IN} = 1.5\text{ V}$ to 5.5 V $-40^\circ\text{C} < T_J < 125^\circ\text{C}$ | | | 0.4 | V |
| | Enable input logic high | $V_{IN} = 1.5\text{ V}$ to 5.5 V $-40^\circ\text{C} < T_J < 125^\circ\text{C}$ | 1 | | | |
| I_{EN} | Enable pin input current | $V_{EN} = V_{IN}$ | | | 100 | nA |
| $TON^{(2)}$ | Turn on time | | | 100 | | μs |
| T_{SHDN} | Thermal shutdown | | | 160 | | $^\circ\text{C}$ |

Electrical characteristics

LD39020

| Symbol | Parameter | Test conditions | Min. | Typ. | Max. | Unit |
|------------------|------------------|--|------|------|------|------|
| | Hysteresis | | | 20 | | |
| C _{OUT} | Output capacitor | Capacitance (see <i>Figure 17: "Stability area vs (C_{OUT}, ESR)</i>) | 0.47 | | 22 | μF |

Notes:

⁽¹⁾Not applicable for V_{out(nom)} > 4.5 V

⁽²⁾Turn-on time is time measured between the enable input just exceeding V_{EN} high value and the output voltage just reaching 95 % of its nominal value

T_J = 25 °C, V_{IN} = V_{OUT(NOM)} + 1 V, C_{IN} = C_{OUT} = 1 μF, I_{OUT} = 1 mA, V_{EN} = V_{IN}, unless otherwise specified.

Table 6: Electrical characteristics for LD39020AT, LD39020ADT

| Symbol | Parameter | Test conditions | Min. | Typ. | Max. | Unit |
|----------------------|--|--|------|------|------|-------------------|
| V _{IN} | Operating input voltage | | 1.5 | | 5.5 | V |
| V _{OUT} | V _{OUT} accuracy | I _{OUT} = 1 mA, T _J = 25 °C | -0.5 | | 0.5 | % |
| | | I _{OUT} = 1 mA, -40 °C < T _J < 125 °C | -1.5 | | 1.5 | % |
| ΔV _{OUT} | Static line regulation ⁽¹⁾ | V _{OUT(NOM)} + 1 V ≤ V _{IN} ≤ 5.5 V, I _{OUT} = 10 mA | | 0.02 | | %/V |
| | | -40 °C < T _J < 125 °C | | | 0.2 | |
| ΔV _{OUT} | Static load regulation | I _{OUT} = 0 mA to 200 mA | | 10 | | mV |
| | | -40 °C < T _J < 125 °C | | | 0.01 | %/mA |
| V _{DROP} | Dropout voltage | I _{OUT} = 30 mA, V _{OUT} = 2.8 V | | 35 | | mV |
| | | I _{OUT} = 200 mA, V _{OUT} = 2.8 V -40 °C < T _J < 125 °C | | 200 | 350 | |
| e _N | Output noise voltage | 10 Hz to 100 kHz, I _{OUT} = 10 mA | | 45 | | μV _{RMS} |
| SVR | Supply voltage rejection | V _{IN} = V _{OUT(NOM)} + 1 V +/- V _{RIPPLE} V _{RIPPLE} = 0.2 V Freq. = 1 kHz I _{OUT} = 30 mA | | 80 | | dB |
| | | V _{IN} = V _{OUT(NOM)} + 1 V +/- V _{RIPPLE} V _{RIPPLE} = 0.2 V Freq. = 100 kHz I _{OUT} = 30 mA | | 55 | | |
| I _Q | Quiescent current | I _{OUT} = 0 mA | | 20 | 40 | μA |
| | | I _{OUT} = 200 mA | | 100 | | |
| I _{Standby} | Standby current | V _{IN} input current in OFF MODE: V _{EN} = GND | | 0.03 | 1 | μA |
| I _{SC} | Short circuit current | R _L = 0 | 250 | 350 | | mA |
| R _{ON} | Output voltage discharge MOSFET | (only on LD39020ADT) | | 100 | | Ω |

| Symbol | Parameter | Test conditions | Min. | Typ. | Max. | Unit |
|----------------|--------------------------|---|------|------|------|--------------------|
| V_{EN} | Enable input logic low | $V_{IN} = 1.5 \text{ V to } 5.5 \text{ V}$ $-40 \text{ }^{\circ}\text{C} < T_J < 125 \text{ }^{\circ}\text{C}$ | | | 0.4 | V |
| | Enable input logic high | $V_{IN} = 1.5 \text{ V to } 5.5 \text{ V}$ $-40 \text{ }^{\circ}\text{C} < T_J < 125 \text{ }^{\circ}\text{C}$ | 1 | | | |
| I_{EN} | Enable pin input current | $V_{EN} = V_{IN}$ | | | 100 | nA |
| $T_{ON}^{(2)}$ | Turn on time | | | 100 | | μs |
| T_{SHDN} | Thermal shutdown | | | 160 | | $^{\circ}\text{C}$ |
| | Hysteresis | | | 20 | | |
| C_{OUT} | Output capacitor | Capacitance (see <i>Figure 17: "Stability area vs (COUT, ESR)</i>) | 0.47 | | 22 | μF |

Notes:(1) Not applicable for $V_{out(nom)} > 4.5 \text{ V}$ (2) Turn-on time is time measured between the enable input just exceeding V_{EN} high value and the output voltage just reaching 95 % of its nominal value

6 Application information

6.1 Soft start function

The LD39020 has an internal soft start circuit. By increasing the startup time up to 100 μ s, without the need of any external soft start capacitor, this feature is able to keep the regulator inrush current at startup under control.

6.2 Output discharge function

The LD39020 integrates a MOSFET connected between Vout and GND. This transistor is activated when the EN pin goes to low logic level and has the function to quickly discharge the output capacitor when the device is disabled by the user.

The device is available with or without auto-discharge feature.

See [Table 8: "Order codes"](#) for more details.

6.3 Input and output capacitors

The LD39020 requires external capacitors to assure the regulator control loop stability.

Any good quality ceramic capacitor can be used but, the X5R and the X7R are suggested since they guarantee a very stable combination of capacitance and ESR overtemperature.

Locating the input/output capacitors as closer as possible to the relative pins is recommended.

The LD39020 requires an input capacitor with a minimum value of 1 μ F.

This capacitor must be located as closer as possible to the input pin of the device and returned to a clean analog ground.

The control loop of the LD39020 is designed to work with an output ceramic capacitor.

This capacitor must meet the requirements of minimum capacitance and equivalent series resistance (ESR), as shown in Fig17. To assure stability, the output capacitor must maintain its ESR and capacitance in the stable region, over the full operating temperature range.

The LD39020 shows stability with a minimum effective output capacitance of 220 nF.

However, to keep stability in all operating conditions (temperature, input voltage and load variations), a minimum output capacitor of 0.47 μ F is recommended.


The suggested combination of 1 μ F input and output capacitors offers a good compromise among the stability of the regulator, optimum transient response and total PCB area occupation.

7

Typical characteristics

($C_{IN} = C_{OUT} = 1 \mu F$, V_{EN} to V_{IN} , $T_J = 25^\circ C$ unless otherwise specified)


**Figure 4: Output voltage vs. temperature
($I_{OUT} = 1 \text{ mA}$)**



$V_{IN}=4.3V, I_{OUT}=1\text{mA}$

AM13855V1


**Figure 5: Output voltage vs. temperature
($I_{OUT} = 200 \text{ mA}$)**



$V_{IN}=4.3V, I_{OUT}=200\text{mA}$

AM13856V1


Figure 6: Line regulation vs. temperature



$V_{IN}=4.3V \text{ to } 5.5V, I_{OUT}=10\text{mA}$

AM13857V1

Figure 7: Load regulation vs. temperature



$V_{IN}=4.3V, I_{OUT}=0 \text{ to } 200\text{mA}$

AM13858V1







Figure 8: Quiescent current vs. temperature (I_{OUT} = 0 mA)**Figure 9: Quiescent current vs. temperature (I_{OUT} = 200 mA)****Figure 10: Shutdown current vs. temperature****Figure 11: Quiescent current vs. load current****Figure 12: Quiescent current vs. input voltage****Figure 13: Dropout voltage vs temperature**










Figure 14: Supply voltage rejection vs. frequency**Figure 15: Supply voltage rejection vs. input voltage****Figure 16: Output noise spectral density****Figure 17: Stability area vs (C_{OUT}, ESR)****Figure 18: Enable startup (V_{OUT} = 1 V)****Figure 19: Enable startup (V_{OUT} = 5 V)**

Figure 20: Turn-on time (VOUT = 1 V)


$V_{IN} = V_{EN} =$ from 0V to 5.5V, $I_{OUT} = 0.2A$, $V_{OUT} = 1V$, $T_r = 5\mu s$

Figure 21: Turn-off time (VOUT = 1 V)


$V_{IN} = V_{EN} =$ from 5.5V to 0V, $I_{OUT} = 0.2A$, $V_{OUT} = 1V$, $T_f = 5\mu s$

Figure 22: Turn-on time (VOUT = 5 V)


$V_{IN} = V_{EN} =$ from 0V to 5.5V, $I_{OUT} = 0.2A$, $V_{OUT} = 5V$, $T_r = 5\mu s$

Figure 23: Turn-off time (VOUT = 5 V)


$V_{IN} = V_{EN} =$ from 5.5V to 0V, $I_{OUT} = 0.2A$, $V_{OUT} = 5V$, $T_f = 5\mu s$

Figure 24: Line transient (VOUT = 1 V)

$V_{IN} = V_{EN} =$ from 2V to 3V, $I_{OUT} = 10mA$, $V_{OUT} = 1V$, $T_r = T_f = 5\mu s$


Figure 25: Line transient (VOUT = 5 V)

$V_{IN} = V_{EN} =$ from 5.1V to 5.5V, $I_{OUT} = 10mA$, $V_{OUT} = 5V$, $T_r = T_f = 5\mu s$

Figure 26: Load transient (VOUT = 1 V)

$V_{IN}=V_{EN}=2V$, I_{OUT} =from 0 to 0.2A , $V_{OUT}=1V$, $t_i=t_f=5\mu s$

AM13877V1

Figure 27: Load transient (VOUT = 5 V)

$V_{IN}=V_{EN}=5.5V$, I_{OUT} =from 0 to 0.2A , $V_{OUT}=5V$, $t_i=t_f=5\mu s$

AM13878V1


8 Package mechanical data

In order to meet environmental requirements, ST offers these devices in different grades of ECOPACK® packages, depending on their level of environmental compliance.

ECOPACK® specifications, grade definitions and product status are available at: www.st.com. ECOPACK® is an ST trademark.

8.2 DFN4 1x1 package info

Figure 28: DFN 1x1-4L drawing




8405587_A

Table 7: DFN 1x1-4L mechanical data

| Dim. | mm. | | |
|------|------|------|------|
| | Min. | Typ. | Max. |
| A | 0.34 | 0.37 | 0.40 |
| A1 | 0 | 0.02 | 0.05 |
| A3 | | 0.10 | |
| b | 0.17 | 0.22 | 0.27 |
| D | 0.95 | 1.00 | 1.05 |
| D2 | 0.43 | 0.48 | 0.53 |
| E | 0.95 | 1.00 | 1.05 |
| E2 | 0.43 | 0.48 | 0.53 |
| e | | 0.65 | |
| L | 0.20 | 0.25 | 0.30 |
| K | 0.15 | | |

Figure 29: DFN 1x1-4L footprint

**Notes:**

- 1) This footprint is able to ensure insulation up to 10 Vrms (according to CEI IEC 664-1)
- 2) The device must be positioned within $\oplus | 0.02 | A | B$

8405587_A

9 Order codes

Table 8: Order codes

| Order code | Output voltage (V) | Auto-discharge | Tolerance (%) | Marking |
|---------------------------------|--------------------|----------------|---------------|---------|
| LD39020ADTPU08R ⁽¹⁾ | 0.8 | Yes | 0.5 | A1 |
| LD39020DTPU08R | | | 2 | 08 |
| LD39020ATPU08R ⁽¹⁾ | | No | 0.5 | B1 |
| LD39020TPU08R ⁽¹⁾ | | | 2 | C1 |
| LD39020ADTPU095R ⁽¹⁾ | 0.95 | Yes | 0.5 | A2 |
| LD39020DTPU095R | | | 2 | 95 |
| LD39020ATPU095R ⁽¹⁾ | | No | 0.5 | B2 |
| LD39020TPU095R ⁽¹⁾ | | | 2 | C2 |
| LD39020ADTPU10R ⁽¹⁾ | 1 | Yes | 0.5 | A3 |
| LD39020DTPU10R | | | 2 | 10 |
| LD39020ATPU10R ⁽¹⁾ | | No | 0.5 | B3 |
| LD39020TPU10R ⁽¹⁾ | | | 2 | C3 |
| LD39020ADTPU11R ⁽¹⁾ | 1.1 | Yes | 0.5 | A4 |
| LD39020DTPU11R | | | 2 | 11 |
| LD39020ATPU11R ⁽¹⁾ | | No | 0.5 | B4 |
| LD39020TPU11R ⁽¹⁾ | | | 2 | C4 |
| LD39020ADTPU12R ⁽¹⁾ | 1.2 | Yes | 0.5 | A5 |
| LD39020DTPU12R | | | 2 | 12 |
| LD39020ATPU12R ⁽¹⁾ | | No | 0.5 | B5 |
| LD39020TPU12R ⁽¹⁾ | | | 2 | C5 |
| LD39020ADTPU13R | 1.3 | Yes | 0.5 | AP |
| LD39020DTPU13R | | | 2 | 13 |
| LD39020ATPU13R ⁽¹⁾ | | No | 0.5 | BP |
| LD39020TPU13R ⁽¹⁾ | | | 2 | CP |
| LD39020ADTPU15R ⁽¹⁾ | 1.5 | Yes | 0.5 | A6 |
| LD39020DTPU15R | | | 2 | 15 |
| LD39020ATPU15R ⁽¹⁾ | | No | 0.5 | B6 |
| LD39020TPU15R ⁽¹⁾ | | | 2 | C6 |
| LD39020ADTPU18R ⁽¹⁾ | 1.8 | Yes | 0.5 | A7 |
| LD39020DTPU18R | | | 2 | 18 |
| LD39020ATPU18R ⁽¹⁾ | | No | 0.5 | B7 |
| LD39020TPU18R ⁽¹⁾ | | | 2 | C7 |

| Order code | Output voltage (V) | Auto-discharge | Tolerance (%) | Marking |
|---------------------------------|--------------------|----------------|---------------|---------|
| LD39020ADTPU20R ⁽¹⁾ | 2 | Yes | 0.5 | A8 |
| LD39020DTPU20R | | | 2 | 20 |
| LD39020ATPU20R ⁽¹⁾ | 2 | No | 0.5 | B8 |
| LD39020TPU20R ⁽¹⁾ | | | 2 | C8 |
| LD39020ADTPU21R ⁽¹⁾ | 2.1 | Yes | 0.5 | A9 |
| LD39020DTPU21R | | | 2 | 21 |
| LD39020ATPU21R ⁽¹⁾ | 2 | No | 0.5 | B9 |
| LD39020TPU21R ⁽¹⁾ | | | 2 | C9 |
| LD39020ADTPU25R ⁽¹⁾ | 2.5 | Yes | 0.5 | AA |
| LD39020DTPU25R | | | 2 | 25 |
| LD39020ATPU25R ⁽¹⁾ | 2 | No | 0.5 | BA |
| LD39020TPU25R ⁽¹⁾ | | | 2 | CA |
| LD39020ADTPU27R ⁽¹⁾ | 2.7 | Yes | 0.5 | AB |
| LD39020DTPU27R | | | 2 | 27 |
| LD39020ATPU27R ⁽¹⁾ | 2 | No | 0.5 | BB |
| LD39020TPU27R ⁽¹⁾ | | | 2 | CB |
| LD39020ADTPU28R ⁽¹⁾ | 2.8 | Yes | 0.5 | AC |
| LD39020DTPU28R | | | 2 | 28 |
| LD39020ATPU28R ⁽¹⁾ | 2 | No | 0.5 | BC |
| LD39020TPU28R ⁽¹⁾ | | | 2 | CC |
| LD39020ADTPU285R ⁽¹⁾ | 2.85 | Yes | 0.5 | AD |
| LD39020DTPU285R | | | 2 | 85 |
| LD39020ATPU285R ⁽¹⁾ | 2 | No | 0.5 | BD |
| LD39020TPU285R ⁽¹⁾ | | | 2 | CD |
| LD39020ADTPU29R ⁽¹⁾ | 2.9 | Yes | 0.5 | AE |
| LD39020DTPU29R | | | 2 | 29 |
| LD39020ATPU29R ⁽¹⁾ | 2 | No | 0.5 | BE |
| LD39020TPU29R ⁽¹⁾ | | | 2 | CE |
| LD39020ADTPU30R ⁽¹⁾ | 3 | Yes | 0.5 | AF |
| LD39020DTPU30R | | | 2 | 30 |
| LD39020ATPU30R ⁽¹⁾ | 3 | No | 0.5 | BF |
| LD39020TPU30R ⁽¹⁾ | | | 2 | CF |
| LD39020ADTPU31R ⁽¹⁾ | 3.1 | Yes | 0.5 | AG |
| LD39020DTPU31R | | | 2 | 31 |
| LD39020ATPU31R ⁽¹⁾ | 3 | No | 0.5 | BG |
| LD39020TPU31R ⁽¹⁾ | | | 2 | CG |

Order codes
LD39020

| Order code | Output voltage (V) | Auto-discharge | Tolerance (%) | Marking |
|--------------------------------|--------------------|----------------|---------------|---------|
| LD39020ADTPU32R ⁽¹⁾ | 3.2 | Yes | 0.5 | AH |
| LD39020DTPU32R ⁽¹⁾ | | | 2 | 32 |
| LD39020ATPU32R ⁽¹⁾ | | No | 0.5 | BH |
| LD39020TPU32R ⁽¹⁾ | | | 2 | CH |
| LD39020ADTPU33R ⁽¹⁾ | 3.3 | Yes | 0.5 | AJ |
| LD39020DTPU33R | | | 2 | 33 |
| LD39020ATPU33R ⁽¹⁾ | | No | 0.5 | BJ |
| LD39020TPU33R ⁽¹⁾ | | | 2 | CJ |
| LD39020ADTPU36R ⁽¹⁾ | 3.6 | Yes | 0.5 | AK |
| LD39020DTPU36R | | | 2 | 36 |
| LD39020ATPU36R ⁽¹⁾ | | No | 0.5 | BK |
| LD39020TPU36R ⁽¹⁾ | | | 2 | CK |
| LD39020ADTPU40R ⁽¹⁾ | 4 | Yes | 0.5 | AL |
| LD39020DTPU40R | | | 2 | 40 |
| LD39020ATPU40R ⁽¹⁾ | | No | 0.5 | BL |
| LD39020TPU40R ⁽¹⁾ | | | 2 | CL |
| LD39020ADTPU47R ⁽¹⁾ | 4.7 | Yes | 0.5 | AM |
| LD39020DTPU47R | | | 2 | 47 |
| LD39020ATPU47R ⁽¹⁾ | | No | 0.5 | BM |
| LD39020TPU47R ⁽¹⁾ | | | 2 | CM |
| LD39020ADTPU50R ⁽¹⁾ | 5 | Yes | 0.5 | AN |
| LD39020DTPU50R | | | 2 | 50 |
| LD39020ATPU50R ⁽¹⁾ | | No | 0.5 | BN |
| LD39020TPU50R ⁽¹⁾ | | | 2 | CN |

Notes:
⁽¹⁾Available on request.

10 Revision history

Table 9: Document revision history

| Date | Revision | Changes |
|-------------|----------|---|
| 04-Dec-2013 | 1 | Initial release. |
| 02-Apr-2014 | 2 | Updated Table 8: "Order codes". |

Please Read Carefully

Information in this document is provided solely in connection with ST products. STMicroelectronics NV and its subsidiaries ("ST") reserve the right to make changes, corrections, modifications or improvements, to this document, and the products and services described herein at any time, without notice.

All ST products are sold pursuant to ST's terms and conditions of sale.

Purchasers are solely responsible for the choice, selection and use of the ST products and services described herein, and ST assumes no liability whatsoever relating to the choice, selection or use of the ST products and services described herein.

No license, express or implied, by estoppel or otherwise, to any intellectual property rights is granted under this document. If any part of this document refers to any third party products or services it shall not be deemed a license grant by ST for the use of such third party products or services, or any intellectual property contained therein or considered as a warranty covering the use in any manner whatsoever of such third party products or services or any intellectual property contained therein.

UNLESS OTHERWISE SET FORTH IN ST'S TERMS AND CONDITIONS OF SALE ST DISCLAIMS ANY EXPRESS OR IMPLIED WARRANTY WITH RESPECT TO THE USE AND/OR SALE OF ST PRODUCTS INCLUDING WITHOUT LIMITATION IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE (AND THEIR EQUIVALENTS UNDER THE LAWS OF ANY JURISDICTION), OR INFRINGEMENT OF ANY PATENT, COPYRIGHT OR OTHER INTELLECTUAL PROPERTY RIGHT.

ST PRODUCTS ARE NOT DESIGNED OR AUTHORIZED FOR USE IN: (A) SAFETY CRITICAL APPLICATIONS SUCH AS LIFE SUPPORTING, ACTIVE IMPLANTED DEVICES OR SYSTEMS WITH PRODUCT FUNCTIONAL SAFETY REQUIREMENTS; (B) AERONAUTIC APPLICATIONS; (C) AUTOMOTIVE APPLICATIONS OR ENVIRONMENTS, AND/OR (D) AEROSPACE APPLICATIONS OR ENVIRONMENTS. WHERE ST PRODUCTS ARE NOT DESIGNED FOR SUCH USE, THE PURCHASER SHALL USE PRODUCTS AT PURCHASER'S SOLE RISK, EVEN IF ST HAS BEEN INFORMED IN WRITING OF SUCH USAGE, UNLESS A PRODUCT IS EXPRESSLY DESIGNATED BY ST AS BEING INTENDED FOR "AUTOMOTIVE, AUTOMOTIVE SAFETY OR MEDICAL" INDUSTRY DOMAINS ACCORDING TO ST PRODUCT DESIGN SPECIFICATIONS. PRODUCTS FORMALLY ESCC, QML OR JAN QUALIFIED ARE DEEMED SUITABLE FOR USE IN AEROSPACE BY THE CORRESPONDING GOVERNMENTAL AGENCY.

Resale of ST products with provisions different from the statements and/or technical features set forth in this document shall immediately void any warranty granted by ST for the ST product or service described herein and shall not create or extend in any manner whatsoever, any liability of ST.

ST and the ST logo are trademarks or registered trademarks of ST in various countries.

Information in this document supersedes and replaces all information previously supplied.

The ST logo is a registered trademark of STMicroelectronics. All other names are the property of their respective owners.

© 2014 STMicroelectronics - All rights reserved

STMicroelectronics group of companies

Australia - Belgium - Brazil - Canada - China - Czech Republic - Finland - France - Germany - Hong Kong - India - Israel - Italy - Japan -
Malaysia - Malta - Morocco - Philippines - Singapore - Spain - Sweden - Switzerland - United Kingdom - United States of America

www.st.com