



ELECTRONICS, INC.  
 44 FARRAND STREET  
 BLOOMFIELD, NJ 07003  
 (973) 748-5089  
<http://www.nteinc.com>

## NTE1110 Integrated Circuit Audio Power Amp, 2W

**Description:**

The NTE1110 is a 2 Watt Audio Power Amp packaged in a 16-Lead DIP plastic package with a heat sink fin.

**Absolute Maximum Ratings:** ( $T_A = +25^\circ\text{C}$  unless otherwise specified)

Supply Voltage, $V_{CC}$ .....	12V
Supply Current, $I_{CC}$ .....	1.5A
Power Dissipation ( $T_A = +45^\circ\text{C}$ ), $P_d$ .....	1.1W
Derate Above $+45^\circ\text{C}$ .....	14.1mW/ $^\circ\text{C}$
Power Dissipation ( $T_A = +45^\circ\text{C}$ , 50 x 50 x 1mm Al), $P_d$ .....	1.7W
Derate Above $+45^\circ\text{C}$ .....	21.4mW/ $^\circ\text{C}$
Operating Temperature Range, $T_{opg}$ .....	-10 to $+75^\circ\text{C}$
Storage Temperature Range, $T_{stg}$ .....	-20 to $+125^\circ\text{C}$

**Electrical Characteristics:** ( $T_A = +25^\circ\text{C}$ ,  $V_{CC} = 9V$  unless otherwise specified)

Parameter	Symbol	Test Conditions	Min	Typ	Max	Unit	
Zero-Signal Supply Current	$I_{CC}$		20	30	60	mA	
<b>Pre-Amplifier</b>							
Closed-Loop Voltage Gain Play Mode	$G_{VC} 1$	$f = 1k$	-	35	-	dB	
			Recorded Mode	-	20	-	dB
Open-Loop Voltage Gain	$G_{VO} 1$	$f = 1k$		55	60	-	dB
			$V_{CC} = 4V$	42	50	-	dB
Input Resistance (Play Mode)	$R_i 1$	$f = 1k$	-	60	-	k $\Omega$	
Linearity (Record Mode)	$V_O 1$	$f = 1k$		0.3	0.5	-	$V_{rms}$
			$V_{CC} = 4V$	0.3	-	-	$V_{P-P}$
Input Referred Noise Voltage	$N_i 1$	DIN. EQ., $R_g = 1k\Omega$	-	0.8	2.0	$\mu V$	
AGC Figure of Merit	AGC		-	40	-	dB	

**Electrical Characteristics (Cont'd):** ( $T_A = +25^\circ\text{C}$ ,  $V_{CC} = 9\text{V}$  unless otherwise specified)

Parameter	Symbol	Test Conditions	Min	Typ	Max	Unit	
<b>Tone-Amplifier</b>							
Closed-Loop Voltage Gain Play Mode	$G_{VC\ 2}$	$f = 1\text{k}$	-	40	-	dB	
			Recorded Mode	-	20	-	dB
Open-Loop Voltage Gain	$G_{VO\ 2}$	$f = 1\text{k}$		50	60	-	dB
			$V_{CC} = 4\text{V}$	45	55	-	dB
Input Resistance (Play Mode)	$R_i\ 2$	$f = 1\text{k}$	-	80	-	$\text{k}\Omega$	
Linearity (Play Mode)	$V_O\ 2$	$f = 1\text{k}$ , $R_i = 330\Omega$		0.3	0.5	-	$V_{\text{rms}}$
			$V_{CC} = 4\text{V}$	0.3	-	-	$V_{\text{P-P}}$
Input Referred Noise Voltage (Play Mode)	$N_i\ 1$	Tone: Flat, $R_g = 0\Omega$	-	-	3.16	$\mu\text{V}$	
<b>Power-Amplifier</b>							
Closed-Loop Voltage Gain	$G_{VC\ 3}$	$f = 1\text{k}$	-	25	-	dB	
Open-Loop Voltage Gain	$G_{VO\ 3}$	$f = 1\text{k}$		34	40	-	dB
			$V_{CC} = 4\text{V}$	30	33	-	dB
Power Output (Closed-Loop)	$P_O$	$f = 1\text{K}$ , $\text{THD} \leq 1\%$	1.5	-	-	W	

**Pin Connection Diagram**



