

USB High-Side Power Switch


■ FEATURES

- 70mΩ (5V Input) High-Side MOSFET Switch.
- 500mA Continuous Load Current per Channel.
- 75µA Typical On-State Supply Current.
- 1µA Typical Off-State Supply Current.
- Current-Limit / Short Circuit Protection.
- Thermal Shutdown Protection under Overcurrent Condition.
- Undervoltage Lockout Ensures that Switch is off at Start Up.
- Output can be Forced Higher than Input (Off-State).
- Open-Drain Fault Flag.
- Slow Turn ON and Fast Turn OFF.
- Enable Active-High or Active-Low.

■ APPLICATIONS

- USB Power Management.
- Hot Plug-In Power Supplies.
- Battery-Charger Circuit.

■ TYPICAL APPLICATION CIRCUIT




One-Port Self-Powered Hub

■ ORDERING INFORMATION

AIC1525-XXX


PACKAGE TYPE
 N: PLASTIC DIP
 S: SMALL OUTLINE
 TEMPERATURE RANGE
 C: 0°C~70°C
 CONTROL POLARITY
 0: ACTIVE LOW
 1: ACTIVE HIGH

ORDER NUMBER	PIN CONFIGURATION
AIC1525-0CN AIC1525-1CN (PLASTIC DIP)	TOP VIEW 
AIC1525-0CS AIC1525-1CS (PLASTIC SO)	

■ ABSOLUTE MAXIMUM RATINGS

Supply Voltage (V_{IN})	7.0V
Fault Flag Voltage (V_{FLG})	7.0V
Fault Flag Current (I_{FLG})	50mA
Control Input (V_{CTL})	-0.3V ~15V
Operating Temperature Range	-20°C~80°C
Storage Temperature Range	-65°C ~ 150°C


■ TEST CIRCUIT





ELECTRICAL CHARACTERISTICS ($V_{IN}=5V$, $T_a=25^{\circ}C$, unless otherwise specified.)

PARAMETERS	CONDITIONS	MIN.	TYP.	MAX.	UNIT
Supply Current	$V_{CTL} = \text{Logic "0"}$, OUT=Open	0.75	5		μA
	$V_{CTL} = \text{Logic "1"}$, OUT=Open	75	100		
Control Input Voltage	$V_{CTL} = \text{Logic "0"}$		1.7	0.8	V
	$V_{CTL} = \text{Logic "1"}$	2.4	2.0		
Control Input Current	$V_{CTL} = \text{Logic "0"}$	0.01	1		μA
	$V_{CTL} = \text{Logic "1"}$	0.01	1		
Control Input Capacitance		1			pF
Output MOSFET Resistance		70	100		$\text{m}\Omega$
Output Turn-On Rise Delay	$R_L = 10\Omega$ each Output	100			μs
Output Turn-On Rise Time	$R_L = 10\Omega$ each Output	1000	4000		μs
Output Turn-Off Delay	$R_L = 10\Omega$ each Output	0.8	20		μs
Output Turn-Off Fall Time	$R_L = 10\Omega$ each Output	0.7	20		μs
Output Leakage Current			10		μA
Current Limit Threshold		0.7	1.0	1.25	A
Overtemperature Shutdown Threshold	T_J Increasing	135			$^{\circ}\text{C}$
	T_J Decreasing	125			
Error Flag Output Resistance	$V_{IN} = 5\text{V}$, $I_L = 10\text{ mA}$	10	25		Ω
	$V_{IN} = 3.3\text{V}$, $I_L = 10\text{mA}$	15	40		
Error Flag Off Current	$V_{FLG} = 5\text{V}$	0.01	1		μA
UVLO Threshold	V_{IN} Increasing	2.6			V
	V_{IN} Decreasing	2.4			


■ BLOCK DIAGRAM




■ TYPICAL PERFORMANCE CHARACTERISTICS



ON-State Supply Current vs. Supply Voltage




UVLO Threshold Voltage vs. Temperature




■ TYPICAL PERFORMANCE CHARACTERISTICS (Continued)


ON-State Supply Current vs. Temperature




OFF-State Supply Current vs. Temperature





OFF State Current vs. Supply Voltage








CTL Threshold Voltage vs. Supply Voltage





TYPICAL PERFORMANCE CHARACTERISTICS (Continued)



■ PIN DESCRIPTION

- PIN 1: CTL - TTL compatible control input. It controls the power switch turn-on/turn-off. Active High for AIC1525-1 and active low for AIC1525-0.
- PIN 2: FLG - An active-low and open-drain fault flag output for power switch. It can indicate current limit if CTL is

- active. In normal mode operation, it also can indicate thermal shutdown or undervoltage.
- PIN 3: GND - Chip power ground.
- PIN 4: NC - Not internally connected.
- PIN 5, 7: IN - Power supply Input.
- PIN 6, 8: OUT - MOSFET switch output.

■ APPLICATION INFORMATIONS

● Error Flag

An open-drained output of an N-channel MOSFET, the FLG output is pulled low to signal the following fault conditions: input undervoltage, output current limit, and thermal shutdown.

control supply transients. Without a bypass capacitor, an output short may cause sufficient ringing on the input (from supply lead inductance) to damage internal control circuitry.

● Current Limit

The current limit threshold is preset internally. It protects the output MOSFET switches from damage due to undesirable short circuit conditions or excess inrush current often encountered during hot plug-in. The low limit of the current limit threshold of the AIC1525 allows a minimum current of 0.5A through the MOSFET switches. A current limit condition will signal the error flag.

● Transient Droop Requirements

USB support dynamic attachment (hot plug-in) of peripherals. A current surge is caused by the input capacitance of downstream device. Ferrite beads are recommended in series with all power and ground connector pins. Ferrite beads reduce EMI and limit the inrush current during hot-attachment by filtering high-frequency signals.

● Short Circuit Transient

Bulk capacitance provides the short-term transient current needed during a hot-attachment event. With a 33 μ F, 16V tantalum or 100 μ F, 10V electrolytic capacitor mounted close to downstream connector should provide transient drop protection.

● Printed Circuit Layout


The power circuitry of USB printed circuit boards requires a customized layout to maximize thermal dissipation and to minimize voltage drop and EMI.

● Thermal Shutdown

When the chip temperature exceeds 135°C, the thermal shutdown function turns off MOSFET switch and signals the error flag. A hysteresis of 10°C prevents the MOSFET from turning back on until the chip temperature drops to below 125°C.


● Supply Filtering

A 0.1 μ F to 1 μ F bypass capacitor from IN to GND, located near the device, is strongly recommended to


One-Port Self-Powered Hub


■ PHYSICAL DIMENSIONS

- 8 LEAD PLASTIC SO (unit: mm)



SYMBOL	MIN	MAX
A	1.35	1.75
A1	0.10	0.25
B	0.33	0.51
C	0.19	0.25
D	4.80	5.00
E	3.80	4.00
e	1.27(TYP)	
H	5.80	6.20
L	0.40	1.27

- 8 LEAD PLASTIC DIP (unit: mm)



SYMBOL	MIN	MAX
A1	0.381	—
A2	2.92	4.96
b	0.35	0.56
C	0.20	0.36
D	9.01	10.16
E	7.62	8.26
E1	6.09	7.12
e	2.54 (TYP)	
eB	—	10.92
L	2.92	3.81