

| | | |
|--------------|---------|--|
| SANYO | No.4228 | 2SK1412 |
| | | N-Channel MOS Silicon FET High-Voltage High-Speed Switching Applications |

Features

- Low ON resistance, low input capacitance, very high-speed switching.
- High reliability (Adoption of HVP process).
- Micaless package facilitating mounting.

Absolute Maximum Ratings at Ta = 25°C


| | | | unit |
|-----------------------------|-----------|--|------------|
| Drain to Source Voltage | V_{DSS} | 1500 | V |
| Gate to Source Voltage | V_{GSS} | ± 20 | V |
| Drain Current(DC) | I_D | 0.1 | A |
| Drain Current(Pulse) | I_{DP} | $PW \leq 10\mu s, \text{ duty cycle} \leq 1\%$ | A |
| Allowable Power Dissipation | P_D | 2.0 | W |
| | | $T_c = 25^\circ C$ | W |
| Channel Temperature | T_{ch} | 150 | $^\circ C$ |
| Storage Temperature | T_{stg} | -55 to +150 | $^\circ C$ |

Electrical Characteristics at Ta = 25°C


| | | | min | typ | max | unit |
|--|---------------|--------------------------------|------|-----|-----------|----------|
| D-S Breakdown Voltage | $V_{(BR)DSS}$ | $I_D = 1mA, V_{GS} = 0$ | 1500 | | | V |
| Zero Gate Voltage Drain Current | I_{DSS} | $V_{DS} = 1200V, V_{GS} = 0$ | | | 100 | μA |
| Gate to Source Leakage Current | I_{GSS} | $V_{GS} = \pm 20V, V_{DS} = 0$ | | | ± 100 | nA |
| Cutoff Voltage | $V_{GS(off)}$ | $V_{DS} = 10V, I_D = 1mA$ | 1.5 | | 3.5 | V |
| Forward Transfer Admittance | $ Y_{fs} $ | $V_{DS} = 20V, I_D = 50mA$ | 50 | 100 | | mS |
| Static Drain to Source on State Resistance | $R_{DS(on)}$ | $I_D = 50mA, V_{GS} = 10V$ | 140 | 200 | | Ω |
| Input Capacitance | C_{iss} | $V_{DS} = 20V, f = 1MHz$ | | 40 | | pF |
| Output Capacitance | C_{oss} | $V_{DS} = 20V, f = 1MHz$ | | 12 | | pF |
| Reverse Transfer Capacitance | C_{rss} | $V_{DS} = 20V, f = 1MHz$ | | 3.0 | | pF |
| Turn-ON Delay Time | $t_{d(on)}$ | See specified Test Circuit. | | 15 | | ns |
| Rise Time | t_r | " | | 25 | | ns |
| Turn-OFF Delay Time | $t_{d(off)}$ | " | | 50 | | ns |
| Fall Time | t_f | " | | 350 | | ns |
| Diode Forward Voltage | V_{SD} | $I_S = 0.1A, V_{GS} = 0$ | | 1.0 | 1.5 | V |

(Note) Be careful in handling the 2SK1412 because it has no protection diode between gate and source.

Switching Time Test Circuit















Package Dimensions 2078



S: Source
D: Drain
G: Gate

SANYO: TO-220FI





- No products described or contained herein are intended for use in surgical implants, life-support systems, aerospace equipment, nuclear power control systems, vehicles, disaster/crime-prevention equipment and the like, the failure of which may directly or indirectly cause injury, death or property loss.
- Anyone purchasing any products described or contained herein for an above-mentioned use shall:
 - ① Accept full responsibility and indemnify and defend SANYO ELECTRIC CO., LTD., its affiliates, subsidiaries and distributors and all their officers and employees, jointly and severally, against any and all claims and litigation and all damages, cost and expenses associated with such use.
 - ② Not impose any responsibility for any fault or negligence which may be cited in any such claim or litigation on SANYO ELECTRIC CO., LTD., its affiliates, subsidiaries and distributors or any of their officers and employees jointly or severally.
- Information (including circuit diagrams and circuit parameters) herein is for example only; it is not guaranteed for volume production. SANYO believes information herein is accurate and reliable, but no guarantees are made or implied regarding its use or any infringements of intellectual property rights or other rights of third parties.