



LB9051

Switching Type Hall IC

Overview

The LB9051 is a Hall IC that is operated in the presence of an alternating magnetic field and produces a digital output. The LB9051 contains a silicon Hall generator, an amplifier, a Schmitt trigger circuit on chip and especially suited for detection of magnetism (ex. detection of the rotation of a small magnet-used substance).

Applications

- Detection of magnetism.
- Contactless switch.
- Detection of the rotation, position of a magnetic substance.


Features

- Operated in the presence of an alternating magnetic field.
- Wide operating voltage range (3.6 to 16V).
- Output capable of direct driving a TTL, MOS IC.
- High sensitivity (sensitive to low magnetism).

Package Dimensions

unit:mm

3105-SIH



Specifications

Absolute Maximum Ratings at Ta = 25°C

Parameter	Symbol	Conditions	Ratings	Unit
Maximum supply voltage	V _{CC} max		18	V
Maximum supply current	I _{CC} max		8	mA
Maximum output current	I _O max		20	mA
Allowable power dissipation	Pd max	Ta=80°C	100	mW
Operating temperature	Topr		-40 to +85	°C
Storage temperature	Tstg		-55 to +125	°C

Electrical Characteristics at Ta = 25°C

Parameter	Symbol	Conditions	Ratings			Unit
			min	typ	max	
Release point	B _{LH}	V _{CC} =12V, V _O : L → H	-300			Gauss
Operate point	B _{HL}	V _{CC} =12V, V _O : H → L			300	Gauss
Output low-level voltage	V _{OL1}	V _{CC} =16V, I _O =12mA, B=300Gauss			0.4	V
	V _{OL2}	V _{CC} =3.6V, I _O =12mA, B=300Gauss			0.4	V
Output high-level voltage	V _{OH1}	V _{CC} =16V, I _O =-30μA, B=-300Gauss	14.6			V
	V _{OH2}	V _{CC} =3.6V, I _O =-30μA, B=-300Gauss	2.2			V

Continued on next page.

■ Any and all SANYO products described or contained herein do not have specifications that can handle applications that require extremely high levels of reliability, such as life-support systems, aircraft's control systems, or other applications whose failure can be reasonably expected to result in serious physical and/or material damage. Consult with your SANYO representative nearest you before using any SANYO products described or contained herein in such applications.

■ SANYO assumes no responsibility for equipment failures that result from using products at values that exceed, even momentarily, rated values (such as maximum ratings, operating condition ranges, or other parameters) listed in products specifications of any and all SANYO products described or contained herein.

SANYO Electric Co., Ltd. Semiconductor Company

TOKYO OFFICE Tokyo Bldg., 1-10, 1 Chome, Ueno, Taito-ku, TOKYO, 110-8534 JAPAN


22801TN (KT)/8047TA, TS No.2635-1/3

LB9051


Continued from preceding page.

Parameter	Symbol	Conditions	Ratings			Unit
			min	typ	max	
Output short current	$-I_{OS}$	$V_{CC}=16V, V_O=0V, B=-300Gauss$	0.4		0.9	mA
Supply current	I_{CC1}	$V_{CC}=16V$			6	mA
	I_{CC2}	$V_{CC}=3.6V$			5.5	mA

Pin Assignment and Block Diagram




Location of the Hall Generator and Cross-sectional View of the Hall IC



The Hall generator is located in the dashed area.

Magnetic Flux to Electric Voltage Transduce Characteristic



- Specifications of any and all SANYO products described or contained herein stipulate the performance, characteristics, and functions of the described products in the independent state, and are not guarantees of the performance, characteristics, and functions of the described products as mounted in the customer's products or equipment. To verify symptoms and states that cannot be evaluated in an independent device, the customer should always evaluate and test devices mounted in the customer's products or equipment.
- SANYO Electric Co., Ltd. strives to supply high-quality high-reliability products. However, any and all semiconductor products fail with some probability. It is possible that these probabilistic failures could give rise to accidents or events that could endanger human lives, that could give rise to smoke or fire, or that could cause damage to other property. When designing equipment, adopt safety measures so that these kinds of accidents or events cannot occur. Such measures include but are not limited to protective circuits and error prevention circuits for safe design, redundant design, and structural design.
- In the event that any or all SANYO products(including technical data, services) described or contained herein are controlled under any of applicable local export control laws and regulations, such products must not be exported without obtaining the export license from the authorities concerned in accordance with the above law.
- No part of this publication may be reproduced or transmitted in any form or by any means, electronic or mechanical, including photocopying and recording, or any information storage or retrieval system, or otherwise, without the prior written permission of SANYO Electric Co., Ltd.
- Any and all information described or contained herein are subject to change without notice due to product/technology improvement, etc. When designing equipment, refer to the "Delivery Specification" for the SANYO product that you intend to use.
- Information (including circuit diagrams and circuit parameters) herein is for example only ; it is not guaranteed for volume production. SANYO believes information herein is accurate and reliable, but no guarantees are made or implied regarding its use or any infringements of intellectual property rights or other rights of third parties.

This catalog provides information as of February, 2001. Specifications and information herein are subject to change without notice.