

Software:

```

$MOD751

; **** Tianma 320 x 240 programming code ****
; * The processor clock speed is 16MHz.
; * Cycle time is .750ms.
; Demo software to display a bonsai
; tree bitmap image and 4 lines of
; text on a 320 x 240 LCD.

org 00h
ljmp start ;program start

org 100h

; Initialize the 32241
; Text page 0000h 04afh
; Graphics page 04b0h 2a2fh

start:

    mov r1,#40h ;system set
    lcall comm32
    mov dptr,#msg1 ;ss param
    lcall data32
    mov r1,#44h ;scroll
    lcall comm32
    mov dptr,#msg2 ;scroll param
    lcall data32
    mov r1,#5dh ;csr form
    lcall comm32
    mov dptr,#msg3 ;csr param
    lcall data32
    mov r1,#4ch ;csrdir
    lcall comm32
    mov r1,#5ah ;hdot scr
    lcall comm32
    mov dptr,#msg18 ;hdot param
    lcall data32
    mov r1,#5bh ;overlay
    lcall comm32
    mov dptr,#msg4 ;ovrly param
    lcall data32
    mov r1,#59h ;disp on/off
    lcall comm32
    mov dptr,#msg5 ;disp param
    lcall data32

; clear the text page
    lcall clrtext

; display bitmap
    mov r1,#46h ;set cursor
    lcall comm32
    mov dptr,#msg6
    lcall data32
    mov r1,#42h ;mwrite
    lcall comm32
    mov dptr,#msg12
    lcall data32

```

```

; display text
    mov r1,#46h ;set cursor
    lcall comm32
    mov dptr,#msg7
    lcall data32
    mov r1,#42h ;mwrite
    lcall comm32
    mov dptr,#msg14
    lcall data32
    mov r1,#46h ;set cursor
    lcall comm32
    mov dptr,#msg8
    lcall data32
    mov r1,#42h ;mwrite
    lcall comm32
    mov dptr,#msg15
    lcall data32
    mov r1,#46h ;set cursor
    lcall comm32
    mov dptr,#msg9
    lcall data32
    mov r1,#42h ;mwrite
    lcall comm32
    mov dptr,#msg16
    lcall data32
    mov r1,#46h ;set cursor
    lcall comm32
    mov dptr,#msg10
    lcall data32
    mov r1,#42h ;mwrite
    lcall comm32
    mov dptr,#msg17
    lcall data32
    sjmp $ ;stop

; **** SUBROUTINES ****

; comm32 sends the byte in R1 to the
; 32241 display as a command

comm32:
    setb p3.2 ;a0=1=command
comm321:
    mov a,r1 ;get data byte
    mov p1,a
    clr p3.0 ;CS the display
    clr p3.1 ;strobe
    setb p3.1
    setb p3.0
    ret

; write32 sends the byte in R1 to the
; 32241 display as a data byte.

write32:
    clr p3.2 ;a0=0=data
    sjmp comm321

; data32 sends the message pointed to
; by the DPTR to the 32241 display.

data32:
    clr a ;get the byte
    movc a,@a+dptra
    cjne a,#0a1h,data321;done?
    ret

```

```

data321:
    mov     r1,a
    lcall   write32      ;send it
    inc     dptr
    sjmp   data32       ;next byte

; Clear text RAM on the 3224
clrtext:
    mov     r1,#46h      ;set cursor
    lcall   comm32
    mov     dptr,#msg13  ;cursor param
    lcall   data32
    mov     r1,#42h      ;mwrite
    lcall   comm32
    mov     dptr,#msg11  ;all spaces
    lcall   data32
    mov     r1,#46h      ;set cursor
    lcall   comm32
    mov     dptr,#msg6
    lcall   data32
    ret

*****TABLES AND DATA*****
; Initialization parameters for 3224.

msg1:
    db      30h,87h,07h,27h ;system set
    db      39h,0efh,28h,0h,01ah

msg2:
    db      0,0,0efh,0b0h  ;scroll
    db      04h,0efh,0,0
    db      0,0,01ah

msg3:
    db      04h,86h,01ah  ;csr form

msg4:
    db      01h,01ah      ;overlay param

msg5:
    db      16h,01ah      ;disp on/off

msg6:
    db      0b0h,04h,01ah ;set cursor to
                         ;graphics page

msg7:
    db      31h,2h,01ah   ;set cursor
                         ;text page
                         ;1st line

msg8:
    db      59h,2,01ah    ;2nd line

msg9:
    db      81h,2,01ah    ;3rd line

msg10:
    db      0a9h,2,01ah   ;4th line

; 1200 spaces for text page clear
; The following table is not listed
; here, except for the first 8 bytes,
; but consists of 1200 bytes

```

; all of which are 20h

```

msg11:
    db      '
    db      01ah

msg18: db      0,01ah      ;hscr param
        ; 320x240 bonsai tree graphic
        ; The following table is not listed
        ; here. It consists of 9600 bytes
        ; which constitute a full screen
        ; bit map image of a bonsai tree.
        ; You may add a few bytes before the
        ; 01ah termination byte for testing
        ; purposes or include a complete
        ; bitmap image

msg12:
    db      01ah

msg13:
    db      0,0,01ah      ;set cursor
                      ;to text page

msg14:
    db      'HANTRONIX'
    db      01ah

msg15:
    db      'Crystal Clear and'
    db      01ah

msg16:
    db      'Visibly Superior'
    db      01ah

msg17:
    db      'LCD Modules'
    db      01ah
    end

```