


FEATURES

- PIN photodiode for CATV/Analog applications
- High Responsivity
- Wide Bandwidth
- Low Modulation Distortion
- High Optical Return Loss: >40dB
- High Frequency Response: >2.5GHz

APPLICATIONS

- Analog Transmission Systems
- AM and FM CATV systems



DESCRIPTION

The FID3S2KX is a PIN photodiode module with a single mode fiber pigtail specifically designed for multichannel analog transmission systems. The photodiode uses a planar structure to achieve low dark current, high responsivity and high reliability. The coupling optics in the package is designed for very low optical reflection. The package is hermetically sealed.

ABSOLUTE MAXIMUM RATINGS ($T_C=25^{\circ}\text{C}$, Unless otherwise specified)

Parameter	Symbol	Limits		Unit
		Min.	Max.	
Storage Temperature	T_{stg}	-40	+85	$^{\circ}\text{C}$
Operating Case Temperature	T_{op}	-40	+85	$^{\circ}\text{C}$
PIN Reverse Voltage	V_R	0	20	V
PIN Forward Current	I_F	-	10	mA
PIN Reverse Current	I_R	-	5	mA

OPTICAL & ELECTRICAL CHARACTERISTICS ($T_C=25^{\circ}\text{C}$, $\lambda=1,310$ and $1,500\text{nm}$, Unless otherwise specified)

Parameter	Symbol	Conditions	Limits			Unit
			Min.	Typ.	Max.	
PIN Responsivity	R	$V_R=1\text{V}$	0.8	0.90	-	A/W
Dark Current	I_D	$V_R=5\text{V}$	-	0.1	1.0	nA
Cut-off Frequency	f_c	$V_R=5\text{V}$, $R_L=50\Omega$, $\text{Pin}=-3\text{dBm}$, -3dB from 500kHz	1.5	2.0	-	GHz
			Note 4	2.5	-	
Capacitance	C_t	$V_R=5\text{V}$, $f=1\text{MHz}$,	-	0.8	1.0	pF
2nd Order Intermodulation Distortion	IMD2	Note 1	-	-	-65	dBc
3rd Order Intermodulation Distortion	IMD3		-	-	-80	dBc
Optical Return Loss	ORL		40	45	-	dB

Note 1: 2 Tone/2 Laser test. Modulation index=70%/ch. Total average optical power=0dBm. Frequency=244MHz and 250MHz.

Note 2: Recommended $V_R=10\text{V}$ when $\text{Pin}>0\text{dBm}$ or $f>1\text{GHz}$.

Note 3: All optical parameters are measured including the optical connector.

Note 4: Lead length (Air gap between stem base and PCB) < 2mm.

Fig. 1 Responsivity vs. Wavelength




Fig. 2 Dark Current vs. Reverse Voltage




Fig. 3 Capacitance vs. Reverse Voltage






Fig. 4 Frequency Response






**Fig. 5 2nd Order Intermodulation
Distortion Characteristics**



"KX" PACKAGE

UNIT: mm



For further information please contact:

Eudyna Devices USA Inc.

2355 Zanker Rd.
San Jose, CA 95131-1138, U.S.A.
TEL: (408) 232-9500
FAX: (408) 428-9111
www.us.eudyna.com

Eudyna Devices Europe Ltd.

Network House
Norreys Drive
Maidenhead, Berkshire SL6 4FJ
United Kingdom
TEL: +44 (0) 1628 504800
FAX: +44 (0) 1628 504888

Eudyna Devices Asia Pte Ltd.

Hong Kong Branch
Rm. 1101, Ocean Centre, 5 Canton Rd.
Tsim Sha Tsui, Kowloon, Hong Kong
TEL: +852-2377-0227
FAX: +852-2377-3921

Eudyna Devices Inc.

Sales Division
1, Kanai-cho, Sakae-ku
Yokohama, 244-0845, Japan
TEL: +81-45-853-8156
FAX: +81-45-853-8170

CAUTION

Eudyna Devices Inc. products contain **gallium arsenide (GaAs)** which can be hazardous to the human body and the environment. For safety, observe the following procedures:

- Do not put this product into the mouth.
- Do not alter the form of this product into a gas, powder, or liquid through burning, crushing, or chemical processing as these by-products are dangerous to the human body if inhaled, ingested, or swallowed.
- Observe government laws and company regulations when discarding this product. This product must be discarded in accordance with methods specified by applicable hazardous waste procedures.

Eudyna Devices Inc. reserves the right to change products and specifications without notice. The information does not convey any license under rights of Eudyna Devices Inc. or others.

© 2004 Eudyna Devices USA Inc.
Printed in U.S.A.