



44 FARRAND STREET  
BLOOMFIELD, NJ 07003  
(973) 748-5089

## NTE1559 Integrated Circuit FM IF Amp, Demod

### Functions:

- FM IF Amplifier
- Quadrature Detector
- Audio Amplifier
- Muting Circuit
- Signal-Meter Driver
- AFC
- Center-Meter Driver
- Muting Controller (Bandwidth & Level)
- Center-Meter Short Circuit for AM Band (Pin15)
- IF Amp Killer for AM Band (Pin15)

### Features:

- High Signal-to-Noise Ratio
- High Sensitivity
- Large Muting Attenuation
- Stable Operation using Full-Balanced Differential
- Triplex Amplifier
- High Linearity of Signal Meter
- Operational Input Level of Muting is Adjustable by Controlling External Resistance

### Absolute Maximum Ratings:

Supply Voltage, $V_{CC}$ .....	15V
Power Dissipation, $P_T$ .....	590mW
Operating Temperature Range, $T_{opr}$ .....	-20° to +70°C
Storage Temperature Range, $T_{stg}$ .....	-55° to +125°C

**Electrical Characteristics:** ( $T_A = +25^\circ C$ ,  $V_{CC} = 13V$ ,  $f_C = 10.7MHz$ ,  $f_m = 400Hz$ ,  $f = 75kHz$  dev. unless otherwise specified)

Parameter	Symbol	Test Conditions	Min	Typ	Max	Unit
Operating Current	$I_{CCmax}$	$V_{in} = 100dB\mu$ , 2V supplied to Pin5, +150kHz detuned	—	30.5	39.3	mA
Limiting Sensitivity	$V_{in(lim)}$	Input level lower by 3dB than ( $V_{o(AF)}$ under 100dB $\mu$ of input voltage)	—	33	37	dB $\mu$
Recovered AF Voltage	$V_{o(AF)}$	$V_{in} = 100dB\mu$	280	380	510	mV
Total Harmonic Distortion	THD	$V_{in} = 100dB\mu$	—	0.01	0.08	%
Signal-to-Noise Ratio	S/N	$V_{in} = 100dB\mu$	83	88	—	dB
AM Rejection	AMR	$V_{in} = 100dB\mu$ , $f_m = 1kHz$ , MOD = 30%	45	60	—	dB
Muting Attenuation	$Mute(ATT)$	(Output Voltage under 100dB $\mu$ if $V_{in}$ and with Pin5 Open) = 0dB, 2V fed to Pin5 via $12k\Omega$	83	100	—	dB

**Electrical Characteristics (Cont'd):** ( $T_A = +25^\circ\text{C}$ ,  $V_{CC} = 13\text{V}$ ,  $f_c = 10.7\text{MHz}$ ,  $f_m = 400\text{Hz}$ ,  $f = 75\text{kHz}$  dev. unless otherwise specified)

Parameter	Symbol	Test Conditions	Min	Typ	Max	Unit
Muting Bandwidth	$BW_{(\text{Mute})}$	The sum of plus and minus side $\Delta f_c$ 's for $V_{12} = 1.4\text{V}$ under $100\text{dB}\mu$ if $V_{in}$	60	100	160	$\text{kHz}$
Muting Sensitivity	$V_{in(\text{Mute})}$	Without muting level control, Pin16 Open, $V_{12} = 1.4\text{V}$	36	43	60	$\text{dB}\mu$
Muting Sensitivity Control Range	$\Delta V_{in(\text{Mute})}$	Max Input Level for Muting Level Control	75	—	—	$\text{dB}\mu$
Meter Driven Voltage (1)	$V_{13-0}$	$V_{in} = 0\text{dB}\mu$	—	0	—	$\text{V}$
Meter Driven Voltage (2)	$V_{13-70}$	$V_{in} = 70\text{dB}\mu$	0.9	1.6	—	$\text{V}$
Meter Driven Voltage (3)	$V_{13-110}$	$V_{in} = 110\text{dB}\mu$	4.5	5.5	—	$\text{V}$
Recovered AF Voltage Attenuation (for AM Band)	$V_{O(\text{AM})}$	$V_{in} = 100\text{dB}\mu$ , Pin15 Open, 13V supplied to Pin15 via $4.7\text{k}\Omega$	60	81	—	$\text{dB}$
Center-Meter Voltage (For AM Band)	$V_{CM(\text{AM})}$	$V_{in} = 100\text{dB}\mu$ , +150kHz detuned, the voltage difference of Pin7 and Pin10 with 13V supplied to Pin15	-30	+7	+30	$\text{mV}$

**Pin Connection Diagram**

