



44 FARRAND STREET
BLOOMFIELD, NJ 07003
(973) 748-5089

NTE7117 Integrated Circuit Switched-Mode Power Supply Controller

Description:

The NTE7117 is a control circuit in an 8-Lead DIP type package designed for use in switched-mode power supplies. It contains an internal temperature-compensated supply, PWM, sawtooth oscillator, over-current sense latch, and output stage. This device is intended for low cost SMPS applications where extensive housekeeping functions are not required.

Features:

- Pulse Width Modulator
- Current Limiting (Cycle-by-Cycle)
- Sawtooth Generator
- Stabilized Power Supply
- Double-Pulse Protection
- Internal Temperature-Compensated Reference

Applications:

- Switch-Mode Power Supplies
- DC Motor Controller Inverter
- DC/DC Converter

Absolute Maximum Ratings:

Supply Voltage, V _{CC}	18V
Output Current, I _{OUT}	40mA
Output Duty Cycle	98%
Maximum Total Power Dissipation, P _D	750mW
Operating Temperature Range, T _A	0° to +70°C

DC Electrical Characteristics: (V_{CC} = 12V, T_A = +25°C unless otherwise specified)

Parameter	Symbol	Test Conditions	Min	Typ	Max	Unit
Reference Section						
Internal Reference Voltage	V _{REF}	T _A = +25°C	3.69	3.75	3.84	V
		T _A = 0° to +70°C	3.66	—	3.87	V
Internal Zener Reference	V _Z	I _L = 7mA	7.8	8.2	8.8	V
Temperature Coefficient of V _{REF}			—	±100	—	ppm/°C
Temperature Coefficient of V _Z			—	±100	—	ppm/°C
Oscillator Section						
Frequency Range	f	T _A = 0° to +70°C	50	—	100k	Hz
Initial Accuracy		R _T and C _T Constant	—	5	—	%
Duty Cycle Range		f ₀ = 20kHz	0	—	98	%

DC Electrical Characteristics (Cont'd): ($V_{CC} = 12V$, $T_A = +25^\circ C$ unless otherwise specified)

Parameter	Symbol	Test Conditions		Min	Typ	Max	Unit
Current Limiting							
Input Current	I_{IN}	Pin6 = 250mV	$T_A = +25^\circ C$	—	-2	-10	μA
			$T_A = 0^\circ$ to $+70^\circ C$	—	—	-20	μA
Single Pulse Inhibit Delay		Inhibit Delay Time for 20% Overdrive	$I_{OUT} = 20mA$	—	0.88	1.10	μs
			$I_{OUT} = 40mA$	—	0.7	0.8	μs
Current Limit Trip Level				0.4	0.5	0.6	V
Error Amplifier							
Open-Loop Gain				—	60	—	dB
Feedback Resistor				10k	—	—	Ω
Small-Signal Bandwidth	BW			—	3	—	MHz
Output Voltage Swing, High	V_{OH}			6.2	—	—	V
Output Voltage Swing, Low	V_{OL}			—	—	0.7	V
Output Stage							
Output Current	I_{OUT}	$T_A = 0^\circ$ to $+70^\circ C$		20	—	—	mA
Saturation Voltage	V_{CE}	$T_A = 0^\circ$ to $+70^\circ C$	$I_C = 20mA$	—	—	0.4	V
			$I_C = 40mA$	—	—	0.5	V
Supply Voltage/Current							
Supply Current	I_{CC}	$I_Z = 0$, Voltage-Fed	$T_A = +25^\circ C$	—	—	10	mA
			$T_A = 0^\circ$ to $+70^\circ C$	—	—	13	mA
Supply Voltage	V_{CC}	$I_S = 10mA$, Current-Fed		19	21	24	V
			$I_{CC} = 30mA$, Current-Fed	20	—	30	V
Low Supply Protection							
Pin1 Threshold				8.0	9.0	10.5	V

