

# Type: CMD6D11B


#### **◆ Product Description**


- 7.8×7.0mm Max.(L×W),1.2mm Max. Height.
- Inductance range:  $4.7 \sim 150 \,\mu$  H
- Rated current range: 180mA~1.3A.
- 4 Terminal pins' type gives a flexible design as transformers(SEPIC,ZETA circuit) and inductors.
- In addition to the standards versions used as power inductors shown here, custom designs as transformers(SEPIC,ZETA circuit) and inductors are also available.




- · Magnetically unshielded construction.
- Ideally used in portable devices such as Mobilephone, DSC/DVC, MP3, PDA, etc as DC-DC Converter inductors, specially suitable for White LED drive.
- RoHS Compliance


## **♦** Dimensions (mm)








## ◆ Land Pattern (mm)



# Schematics(Bottom)





# Type: CMD6D11B

## **♦** Specification

| Part No.<br>※    | Stamp | Inductance<br>( µ H) [Within]<br>100kHz/1V | D.C.R.(m Ω )<br>Max.(Typ.)<br>(at 20°C) | Saturation<br>Current (mA)<br>(at 20℃)※1 | Temperature<br>Rise current<br>(mA) ※2 |
|------------------|-------|--|---|--|--|
| CMD6D11BNP-4R7M□ | 4R7   | 4.7±20%                                    | 100(80)                                 | 1300                                     | 1400                                   |
| CMD6D11BNP-6R8M□ | 6R8   | 6.8±20%                                    | 140(115)                                | 1050                                     | 1050                                   |
| CMD6D11BNP−100M□ | 100   | 10±20%                                     | 200(160)                                | 850                                      | 850                                    |
| CMD6D11BNP−150M□ | 150   | 15±20%                                     | 310(250)                                | 650                                      | 650                                    |
| CMD6D11BNP-220M□ | 220   | 22±20%                                     | 460(370)                                | 550                                      | 520                                    |
| CMD6D11BNP−330M□ | 330   | 33±20%                                     | 670(540)                                | 450                                      | 420                                    |
| CMD6D11BNP−470M□ | 470   | 47±20%                                     | 980(790)                                | 380                                      | 350                                    |
| CMD6D11BNP−680M□ | 680   | 68±20%                                     | 1500(1190)                              | 310                                      | 260                                    |
| CMD6D11BNP−101M□ | 101   | 100±20%                                    | 2400(1880)                              | 250                                      | 210                                    |
| CMD6D11BNP−151M□ | 151   | 150±20%                                    | 3100(2450)                              | 210                                      | 180                                    |

# **※** Description of Part Name

- X1.Saturation current: The DC current at which the inductance decreases to 90% of it's initial value.
- &2.Temperature rise current: The DC current at which the temperature rise is  $\triangle t = 40 \,\degree$ .(Ta=20 $\degree$ C)