



ELECTRONICS, INC.
44 FARRAND STREET
BLOOMFIELD, NJ 07003
(973) 748-5089
<http://www.nteinc.com>

NTE1437 Integrated Circuit VIR Signal Processor

Description:

The NTE1437 is an integrated circuit designed for color TV VIR (Vertical Interval Reference) signal processing circuits (with auto tint compensation circuit).

Features:

- Incorporating VIR signal discriminator color control, tint control and Y signal amplifier on a single chip, easier for compact set design.
- Reduction in external components
- No adjustment required

Absolute Maximum Ratings: ($T_A = +25^\circ\text{C}$ unless otherwise specified)

Supply Voltage, V_{8-21}	14.4V
Supply Voltage, V_{17-21}	6.1V
Circuit Voltage, V_{5-21}	0 to 14.4V
Circuit Voltage, V_{6-21}, V_{7-21}	-3 to +6V
Circuit Voltage, $V_{10-21}, V_{12-21}, V_{18-21}$	0 to V_{8-21} V
Circuit Voltage, V_{24-21}	0V
Circuit Current, I_5	0 to 20mA
Circuit Current, I_9	-1 to +3mA
Circuit Current, I_{20}	-3 to +1mA
Circuit Current, I_{23}	-3 to 0mA
Power Dissipation, P_D	630mW
Operating Ambient Temperature Range, T_{opr}	-20° to +70°C
Storage Temperatuere Range, T_{stg}	-20° to +150°C

Note *. + and - are flow-in and flow-out currents to/from the circuit, respectively.

Electrical Characteristics: ($T_A = +25^\circ\text{C}$ unless otherwise specified)

Parameter		Symbol	Test Conditions	Min	Typ	Max	Unit
Circuit Current		I ₈	$V_{8-21} = 12\text{V}$ $V_{17-21} = 5.1\text{V}$	20	25.5	31	mA
		I ₁₇		5	12	19	mA
Output Voltage (Tint Manual)	"H" Level	V _{9-21(H)}		10.3	11	11.7	V
	"L" Level	V _{9-21(L)}		0.6	1.3	2.0	V
Output Voltage (Color Manual)	"H" Level	V _{20-21(H)}		9.5	10.2	10.9	V
	"L" Level	V _{20-21(L)}		0	-	0.3	V
Output Voltage (Tint Auto)	"H" Level	V _{11-21(H)}		9.5	10.2	10.9	V
	"L" Level	V _{11-21(L)}		0.4	1.7	2.7	V
Output Voltage (Color Auto)	"H" Level	V _{19-21(H)}		10.1	10.9	11.7	V
	"L" Level	V _{19-21(L)}		0.4	1.8	3.1	V
Voltage Amplification (Y Amp.)		A _Y	Pin 4 output (SW 1:1) for Pin 1 video signal input (1V _{p-p})	1.75	1.95	2.15	times
VIR Directional Level		V _(VIR)	Pin 2 VIR signal level (SW 1:1) at the start of LED ON	0.23	0.28	0.33	V
Pulse Width (19H)		t _w	19H pulse width of Pins 14 & 16 (SW 1:2)	7	12	17	μs
Sensitivity	Tint Manual Control	S ₍₁₎	Differential voltage ratio between Pins 9 & 12	0.83	0.94	1.05	times
	Color Manual Control	S ₍₂₎	Differential voltage ratio between Pins 20 & 18 (SW 1:2)	0.86	0.97	1.08	times
	Tint Auto Control	S ₍₃₎	Differential voltage ratio between Pins 9 & 13 (SW 1:1)	40	43	46	dB
	Color Auto Control	S ₍₄₎	Differential voltage ratio between Pins 20 & 15 (SW 1:2)	41.5	44.5	47.5	dB
	Tint Pre-Emphasis Control	S ₍₅₎	Differential voltage ratio between Pins 9 & 10 (SW 1:1)	-1.5	-1.3	-1.1	times

Pin Connection Diagram

(Front View)



