

# OTS-2V4A Optiva® Standard, 2 Composite Video and 4 Audio

## Composite Video and Audio Transmission

 $2\rightarrow$ 

The OTS-2V4A provides for the digital transmission of 2 Channels of Composite Video and 4 Channels of Analog Audio.

Video

#### System Design



Audio


All units come in an insert card version. The cards can be inserted into our 16-slot, 19" rack-mountable card cage (OT-CC-16-100) or one of our smaller Optiva Desktop Card Racks (OT-DTCR Series).

The Optiva® Desktop Card Racks can handle one, two or four insert cards, creating compact, mountable, stand alone systems. The use of separate OT-DTCR enclosures allows for future flexibility and expansion as all cards are hot-swappable and can be used in any enclosure. Each one of our card housing units operate with an appropriate power supply. See "Accessories" for power supply specifications.

#### Optiva® Upgrade Path

This system can be purchased without an optical port as an add-on to an existing Optiva® system daisy-chain. (See "Non-Optical Version" below).

The Optiva® bandwidth requirement of this system is 722 Mbps.



#### **Features**

• Composite Video and Analog Audio over one fiber

Optiva

Optiva'

OTS-2VR4AR

- 12-Bit Digital Transmission (Video)
- TDM Single Wavelength
- True DC restoration
- Compatible with MDM-7000 Series for WDM and CWDM multiplexing
- No EMI or RFI and no ground loops
- Stand alone or rack-mount
- Ideal for Professional AV applications

#### Versions Available\*

Wavelength (nm) & Fiber	Transmit**	Receive**	Optical Connector	Optical Budget (dB)	Range*** (km)	Form Factor
1310 Multimode	OTS-2VT4AT-A1-XX-IC	OTS-2VR4AR-A1-XX-IC	ST, FC, LC or SC	10	3	IC (2-slots)
1310 Singlemode	OTS-2VT4AT-A2-XX-IC	OTS-2VR4AR-A2-XX-IC	ST, FC, LC or SC	7	10	IC (2-slots)
1310 Singlemode (D)	OTS-2VT4AT-A2D-XX-IC	OTS-2VR4AR-A2D-XX-IC	ST, FC, LC or SC	12	20	IC (2-slots)
1550 Singlemode	OTS-2VT4AT-A3-XX-IC	OTS-2VR4AR-A3-XX-IC	ST, FC, LC or SC	17	40	IC (2-slots)
1550 Singlemode (D)	OTS-2VT4AT-A3D-XX-IC	OTS-2VR4AR-A3D-XX-IC	ST, FC, LC or SC	25	60	IC (2-slots)
1270-1610 SM (CWDM)	OTS-2VT4AT-L4-XX-IC	OTS-2VR4AR-L4-XX-IC	ST, FC, LC or SC	Varies	20-70	IC (2-slots)
Non-Optical Version	OTS-2VT4AT-NOC-IC	OTS-2VR4AR-NOC-IC	N/A	N/A	N/A	IC (2-slots)

Analog Audio Codes - To indicate your Analog Audio impedance preference, please use the following instead of "A" in the model number: "AB" = Input Balanced 600 Ohm, Output Balanced 600 Ohm; "ABH" = Input Balanced Hi-Z, Output Balanced Low-Z; and "AUH" = Input Unbalanced Hi-Z, Output Unbalanced Low-Z.

<sup>• (</sup>Audio Only)

<sup>\*</sup> Contact Opticomm for other versions available.

<sup>\*\*</sup> XX indicates the type of optical connector. Each of ST, FC, LC or SC are available.

<sup>\*\*\*</sup> Chromatic dispersion and additional losses should be taken into account.

# Composite Video, Audio & Data

Video

Standard SMPTE 170M; RS-250C (Short Haul)

Bit Resolution 12-Bit Digital Transmission

Level 1.0 Volt p-p
Bandwidth 5.5 MHz
Differential Gain < 2%
Differential Phase < 0.7°

Passband Ripple  $< \pm 0.2$  dB to 5.5 MHz

Chroma/Luma Delay <12ns

Compatibility NTSC, PAL, SECAM

Signal to Noise Ratio > 67 dB

Connector BNC (IEC 60169-8)

Analog Audio Impedance Options:

Level 6 dBm In/Out Input Output

Bandwidth 20 Hz to 20 KHz

Signal to Noise Ratio > 80 dB

Harmonia Distortion > 0.19

Unbalanced Hi-Z

Unbalanced Low-Z

Unbalanced Low-Z

Total Harmonic Distortion < 0.1%
Signal Coding 24-bit

General

Connector Micro DB25

Dimensions & Weight Insert Card (IC): 6.3" L x 0.8" W x 4.0" H 11 oz

Operating temperature -20° C to +55° C

Storage temperature -40° C to +85° C

Humidity 0 to 95% non-condensing

Operating voltage 9-12 V<sub>DC</sub>

Consumption < 7w per insert card

System Latency Less than 1ms (Audio <10ms)

**Local Monitoring** LED Status Indication

**Remote Monitoring** Compatible with OptivaView TM

SNMP Management Suite

Optiva™ Configurable Communication Platform

Network Management

SDI & HD-SDI

Composite Video, Audio & Data

RGB/VGA/DVI

Audio/FSK/Intercom

Data (Ethernet/Serial/USB)

CATV/RF & L-Band

Optical Switching, Routing & Redundancy

Passive Multiplexing Solutions

Enclosures, Racks & Frames

Power Supplies & Accessories











MADE IN THE USA

### **Sample Configuration**

