

**FAST SWITCHING DEVICE - Fast Recovery Diodes - Stud Types**

Old Part Number	Data Sheet Available	New Part Number	V <sub>RRM</sub> Range (Note 3) (V)	I <sub>F(AV)</sub> at T <sub>sink</sub> 55°C (A)	I <sub>F(RMS)</sub> Max. (at T <sub>sink</sub> ) (A)	I <sub>F</sub> Max. (at T <sub>sink</sub> ) (A)	Typical Reverse Recovered Charge and Typical Reverse Recovery @ T <sub>J</sub> Max (50% Chord)				I <sub>FSM(1)</sub> 10ms V <sub>R</sub> £60% V <sub>RRM</sub> (Note 2) (A)	I <sub>FSM(2)</sub> 10ms V <sub>R</sub> £10V (Note 2) (A)	I <sup>2</sup> t <sub>(2)</sub> 10ms (A <sup>2</sup> s)	I <sub>RRM</sub> @ T <sub>J</sub> Max (mA)	V <sub>o</sub> r @ T <sub>J</sub> Max. (Note 1) (V) (mW)		V <sub>FM</sub> at I <sub>FM</sub> @ T <sub>J</sub> Max (Note 1) (V) (A)		T <sub>J</sub> Max (°C)	R <sub>th</sub> j-c		R <sub>th</sub> c-hs (K/W)	Wt (typ) (g)	Mounting Torque (kgfm <sup>-1</sup> )	Outline No. (Note 4)
							O <sub>ra</sub> (nC)	t <sub>rr</sub> (ms)	I <sub>FM</sub> (A)	di/dt (A/ms)					d.c.sine (K/W)	120° Rect (K/W)									
SM20-25MCN094	N	M0130SL200-250	1600-2500	130	170 (70°C)	170 (45°C)	240	2.60	1000	150	2240	2450	30.0 x 10 <sup>3</sup>	20	1.29	1.54	1.72	280	125	0.3	0.36	0.08	85	1.15 - 1.44	100A303
SM20-25MCR094	N	M0130RL200-250	1600-2500	130	170 (70°C)	170 (45°C)	240	2.60	1000	150	2240	2450	30.0 x 10 <sup>3</sup>	20	1.29	1.54	1.72	280	125	0.3	0.36	0.08	85	1.15 - 1.44	
SM12-18PHN100	N	M0139SR120-180	1200-1800	139	175 (72°C)	175 (48°C)	68	1.00	1000	100	2450	2700	36.5 x 10 <sup>3</sup>	20	1.24	1.28	1.60	280	125	0.3	0.4	0.08	85	1.15 - 1.44	100A294
SM12-18PHR100	N	M0139RR120-180	1200-1800	139	175 (72°C)	175 (48°C)	68	1.00	1000	100	2450	2700	36.5 x 10 <sup>3</sup>	20	1.24	1.28	1.60	280	125	0.3	0.4	0.4	85	1.15 - 1.44	
SM20-25PHN134	N	M0268SP200-250	1600-2500	268	400 (59°C)	400 (35°C)	173	2.80	1000	150	4250	4670	109 x 10 <sup>3</sup>	20	1.21	1.20	1.77	470	125	0.13	0.14	0.04	250	1.15 - 1.44	100A297
SM20-25PHR134	N	M0268RP200-250	1600-2500	268	400 (59°C)	400 (35°C)	173	2.80	1000	150	4250	4670	109 x 10 <sup>3</sup>	20	1.21	1.20	1.77	470	125	0.13	0.14	0.04	250	1.15 - 1.44	
SM20-25PHN144	N	M0280SP200-250	1600-2500	280	400 (63°C)	400 (39°C)	255	2.80	1000	150	4500	4950	122 x 10 <sup>3</sup>	20	1.28	0.92	1.71	470	125	0.13	0.14	0.04	250	1.15 - 1.44	100A281
SM20-25PHR144	N	M0280RP200-250	1600-2500	280	400 (63°C)	400 (39°C)	255	2.80	1000	150	4500	4950	122 x 10 <sup>3</sup>	20	1.28	0.92	1.71	470	125	0.13	0.14	0.04	250	1.15 - 1.44	
SM12-14PHN170	N	M0336SP120-140	800-1400	336	400 (77°C)	400 (57°C)	137	1.80	1000	200	4500	4950	122 x 10 <sup>3</sup>	20	1.02	0.70	1.35	470	125	0.13	0.14	0.04	250	2.77 - 2.5	100A280
SM12-14PHR170	N	M0336RP120-140	800-1400	336	400 (77°C)	400 (57°C)	137	1.80	1000	200	4500	4950	122 x 10 <sup>3</sup>	20	1.02	0.70	1.35	470	125	0.13	0.14	0.04	250	2.77 - 2.5	
SM12-18PHN174	N	M0334SP120-180	1200-1800	334	400 (76°C)	400 (58°C)	293	2.30	1000	200	4500	4950	122 x 10 <sup>3</sup>	20	1.00	0.74	1.35	470	125	0.13	0.14	0.04	250	2.77 - 2.5	100A280
SM12-18PHR174	N	M0334RP120-180	1200-1800	334	400 (76°C)	400 (58°C)	293	2.30	1000	200	4500	4950	122 x 10 <sup>3</sup>	20	1.00	0.74	1.35	470	125	0.13	0.14	0.04	250	2.77 - 2.5	

The information contained herein is confidential and is protected by Copyright. The information may not be used or disclosed except with the written permission of and in the manner permitted by the proprietors Westcode Semiconductors Limited. In the interest of product improvement, Westcode reserves the right to change specifications at any time without prior notice.

- Note 1 V<sub>o</sub> Threshold Voltage  
r Slope resistance ) for conduction loss and heatsink calculations. (T<sub>J</sub> = 125°C)
- Note 2 I<sub>FSM</sub> (8.3ms) = I<sub>FSM</sub> (10ms) x 1.066 I<sup>2</sup>t (8.3ms) = I<sup>2</sup>t (10ms) x 0.943 at initial temperature T<sub>J</sub> max.
- Note 3 A blocking voltage derating factor of 0.13% per degree centigrade is applicable for T<sub>J</sub> below 25°C
- Note 4 Leaded types, code changes from SP/RP (PHN/R), SN/RN (HHN/R) or SR/RR (PXN/R) . Lead length 135mm (base of hexagon to centre of lug hole).