



6/24/04

Errata: CS3302 Rev C Errata

(Reference CS3302 data sheet revision DS596PP2 dated JUN '03)

Erratum #1: Integrated anti-alias filter resistor tolerance.

Description:

The integrated anti-alias filter resistors are specified as $750 \Omega \pm 30\%$. However, this full tolerance results in a variable phase delay between channels of a synchronous system.

Work Around:

Short term - resistor test limits tightened to $605 \Omega \pm 6\%$ @ -40°C and $675 \Omega \pm 5\%$ @ 85°C .

Long term - new CS3302A device removes internal resistors and requires external resistors.

Erratum #2: Relative gain accuracy.

Description:

Relative gain accuracy specified as $\pm 0.4\%$ typical, $\pm 0.8\%$ max. Many acquisition systems require better relative gain accuracy.

Work Around:

Production test limits tightened to $\pm 0.2\%$ max.

Erratum #3: Voltage noise test limit in 0.1 Hz - 10 Hz bandwidth.

Description:

Low-frequency noise specified as $1 \mu\text{V}$ peak-to-peak typical, $1.5 \mu\text{V}$ peak-to-peak max. Statistical variability of the low-frequency noise measurement requires an increased max test specification.

Work Around:

Production test limit increased to $3 \mu\text{V}$ peak-to-peak max. $1 \mu\text{V}$ peak-to-peak typical specification is not affected.

CONTACTING CIRRUS LOGIC SUPPORT

For a complete listing of direct Distributor, Sales, and Sales Representative contacts, visit the Cirrus Logic website at <http://www.cirrus.com/>