



Silicon Schottky Diode


- General-purpose diode for high-speed switching
- Circuit protection
- Voltage clamping
- High-level detecting and mixing




BAS170W
BAS70-02L
BAS70-02W




BAS70




BAS70-04
BAS70-04W




BAS70-04S




BAS70-05
BAS70-05W



BAS70-06
BAS70-06W



BAS70-07
BAS70-07W
BAS70-07L4



Type	Package	Configuration	L_S (nH)	Marking
BAS170W	SOD323	single	1.8	white 7
BAS70	SOT23	single	1.8	73s
BAS70-02L *	TSLP-2-1	single, leadless	0.4	F
BAS70-02W	SCD80	single	0.6	73
BAS70-04	SOT23	series	1.8	74s
BAS70-04S	SOT363	dual series	1.6	74s
BAS70-04W	SOT323	series	1.4	74s
BAS70-05	SOT23	common cathode	1.8	75s
BAS70-05W	SOT323	common cathode	1.4	75s
BAS70-06	SOT23	common anode	1.8	76s
BAS70-06W	SOT323	common anode	1.4	76s
BAS70-07	SOT143	parallel pair	2	77s
BAS70-07L4*	TSLP-4-4	parallel pair, leadless	0.4	E
BAS70-07W	SOT343	parallel pair	1.8	77s

* Preliminary

Maximum Ratings at $T_A = 25^\circ\text{C}$, unless otherwise specified

Parameter	Symbol	Value	Unit
Diode reverse voltage	V_R	70	V
Forward current	I_F	70	mA
Non-repetitive peak surge forward current $t \leq 10\text{ms}$	I_{FSM}	100	
Total power dissipation BAS70, BAS70-07, $T_S \leq 72^\circ\text{C}$ BAS70-02L, BAS70-07L4, $T_S \leq 117^\circ\text{C}$ BAS70-02W, $T_S \leq 107^\circ\text{C}$ BAS70-04, BAS70-06, $T_S \leq 48^\circ\text{C}$ BAS70-04S/W/-06W, BAS170W, $T_S \leq 97^\circ\text{C}$ BAS70-05, $T_S \leq 22^\circ\text{C}$ BAS70-05W, $T_S \leq 90^\circ\text{C}$ BAS70-07W, $T_S \leq 114^\circ\text{C}$	P_{tot}	250 250 250 250 250 250 250 250	mW
Junction temperature	T_j	150	
Operating temperature range	T_{op}	-55 ... 125	
Storage temperature	T_{stg}	-55 ... 150	

Thermal Resistance

Parameter	Symbol	Value	Unit
Junction - soldering point ¹⁾ BAS70, BAS70-07 BAS70-02L, BAS70-07L4 BAS70-02W BAS70-04, BAS70-06 BAS70-04S/W, BAS70-06W BAS70-05 BAS70-05W BAS70-07W BAS170W	R_{thJS}	≤ 310 ≤ 130 ≤ 170 ≤ 410 ≤ 210 ≤ 510 ≤ 240 ≤ 145 ≤ 190	K/W

¹⁾For calculation of R_{thJA} please refer to Application Note Thermal Resistance


Electrical Characteristics at $T_A = 25^\circ\text{C}$, unless otherwise specified

Parameter	Symbol	Values			Unit
		min.	typ.	max.	
DC Characteristics					
Breakdown voltage $I_{(BR)} = 10 \mu\text{A}$	$V_{(BR)}$	70	-	-	V
Reverse current $V_R = 50 \text{ V}$	I_R	-	-	0.1	μA
Forward voltage $I_F = 1 \text{ mA}$ $I_F = 10 \text{ mA}$ $I_F = 15 \text{ mA}$	V_F	300 600 750	375 705 880	410 750 1000	mV
Forward voltage matching ¹⁾ $I_F = 10 \text{ mA}$	ΔV_F	-	-	20	
AC Characteristics					
Diode capacitance $V_R = 0, f = 1 \text{ MHz}$	C_T	-	1.5	2	pF
Forward resistance $I_F = 10 \text{ mA}, f = 10 \text{ kHz}$	r_f	-	34	-	Ω
Charge carrier life time $I_F = 25 \text{ mA}$	τ_{rr}	-	-	100	ps

¹⁾ ΔV_F is the difference between lowest and highest V_F in a multiple diode component.


Diode capacitance $C_T = f(V_R)$

$f = 1\text{MHz}$




Forward resistance $r_f = f(I_F)$

$f = 10\text{kHz}$




Reverse current $I_R = f(V_R)$

$T_A = \text{Parameter}$




Forward current $I_F = f(V_F)$

$T_A = \text{Parameter}$




Forward current $I_F = f(T_S)$

BAS70, BAS70-07




Forward current $I_F = f(T_S)$

BAS70-02L, BAS70-07L4




Forward current $I_F = f(T_S)$

BAS70-02W




Forward current $I_F = f(T_S)$


BAS70-04, BAS70-06




Forward current $I_F = f(T_S)$
 BAS70-04S/W, BAS70-06W, BAS170W




Forward current $I_F = f(T_S)$
 BAS70-05



Forward current $I_F = f(T_S)$
 BAS70-05W




Forward current $I_F = f(T_S)$
 BAS70-07W




Forward current $I_F = f(T_S)$

BAS170W



Permissible Puls Load $R_{thJS} = f(t_p)$


BAS70



Permissible Pulse Load


$I_{Fmax} / I_{FDC} = f(t_p)$

BAS70



Permissible Puls Load $R_{thJS} = f(t_p)$


BAS70-02L, BAS70-07L4



Permissible Pulse Load


$I_{Fmax} / I_{FDC} = f(t_p)$

BAS70-02L, BAS70-07L4



Permissible Puls Load $R_{thJS} = f(t_p)$


BAS70-02W



Permissible Pulse Load


$I_{Fmax} / I_{FDC} = f(t_p)$

BAS70-02W



Permissible Puls Load $R_{thJS} = f(t_p)$


BAS70-04, BAS70-06



Permissible Pulse Load


$I_{Fmax} / I_{FDC} = f(t_p)$

BAS70-04, BAS70-06



Permissible Puls Load $R_{thJS} = f(t_p)$


BAS70-04S



Permissible Pulse Load


$I_{Fmax} / I_{FDC} = f(t_p)$

BAS70-04S



Permissible Puls Load $R_{thJS} = f(t_p)$


BAS70-04W, BAS70-06W



Permissible Pulse Load


$$I_{Fmax} / I_{FDC} = f(t_p)$$

BAS70-04W, BAS70-06W



Permissible Puls Load $R_{thJS} = f(t_p)$


BAS70-05



Permissible Pulse Load


$$I_{Fmax} / I_{FDC} = f(t_p)$$

BAS70-05



Permissible Puls Load $R_{thJS} = f(t_p)$


BAS70-05W



Permissible Pulse Load


$I_{Fmax} / I_{FDC} = f(t_p)$

BAS70-05W



Permissible Puls Load $R_{thJS} = f(t_p)$


BAS70-07W



Permissible Pulse Load


$I_{Fmax} / I_{FDC} = f(t_p)$

BAS70-07W



Permissible Puls Load $R_{thJS} = f(t_p)$


BAS170W



Permissible Pulse Load

$$I_{Fmax} / I_{FDC} = f(t_p)$$

BAS170W



**Published by Infineon Technologies AG,
St.-Martin-Strasse 53,
81669 München**

**© Infineon Technologies AG 2004.
All Rights Reserved.**

Attention please!

The information herein is given to describe certain components and shall not be considered as a guarantee of characteristics.

Terms of delivery and rights to technical change reserved.

We hereby disclaim any and all warranties, including but not limited to warranties of non-infringement, regarding circuits, descriptions and charts stated herein.

Information

For further information on technology, delivery terms and conditions and prices please contact your nearest Infineon Technologies Office (www.infineon.com).

Warnings

Due to technical requirements components may contain dangerous substances. For information on the types in question please contact your nearest Infineon Technologies Office.

Infineon Technologies Components may only be used in life-support devices or systems with the express written approval of Infineon Technologies, if a failure of such components can reasonably be expected to cause the failure of that life-support device or system, or to affect the safety or effectiveness of that device or system. Life support devices or systems are intended to be implanted in the human body, or to support and/or maintain and sustain and/or protect human life. If they fail, it is reasonable to assume that the health of the user or other persons may be endangered.