



## Low Power Dual Operational Amplifiers

### Features

- Wide Supply Operation Range +4.5V to +19.5V
- Input Common Voltage Range Beyond the Rails
- Rail-to-Rail Output Voltage Swing
- Low Input Offset Voltage 3mV (Typical)
- Wide Bandwidth (unit gain) 30MHz
- Low Quiescent Current: 2mA per Amplifier
- Large DC Voltage Gain 85dB (Typical)
- Slew-Rate 30V/μs
- Unit-Gain Stable

### Applications

- Portable Equipment
- LCD-TV Equipment
- Battery-Powered Equipment
- ASIC Input or Output Amplifier
- Low Power/Low Voltage Applications

### General Description

The G1579 consists of two independent, high gain, internally frequency compensated operational amplifiers which were designed to operate from a single power supply over a wide range of voltages. Operation from split power supplies is also possible. The input common mode range of the G1579 can be beyond the rails, and the G1579 are with rail-to-rails output voltage swing. The quiescent current is 2mA per amplifier.

The G1579 also feature fast slewing and settle-times, as well as high output drive capability of 300mA (source/sink). These features make these amplifiers ideal for use as reference buffers for TFT-LCD. Other applications include battery power, portable devices, and anywhere low power consumption is important.

The G1579 is housed in a MSOP-8 package.

### Ordering Information

ORDER NUMBER	MARKING	TEMP. RANGE	PACKAGE
G1579P81U	G1579	-40°C~ +85°C	MSOP-8

Note: P8: MSOP-8

1: Bonding Code

U: Tape & Reel

### Pin Configuration

