

# Single Digit LED Numeric Display


### LAP-401 D / N Series

LAP-401 D / N series are the numberical display units featuring ROHM's in-house 4-element(AlGaInP) high-brightness LED dies.Their luminous intensity is top class in the industry while degradation is considerably slow, which helps to keep illumination vividness almost unchanged and the image of sets high over a long period of time.

#### Features

- 1) 10.16mm for letter height, single-line LED numerical displays.
- About 10 times more luminous intensity than the conventional products by use of 4-element LED dies. (in case of orange color)
- The same luminous intensity as the conventional products at their 1/10 of current, which contributes lots to energy-saving of sets.
- 4) Light-leakage from segments probable with the small display packages is very rare.
- 5)Both anode common type and cathode common type are available in lineup for each color.

#### •Dimensions (Unit : mm)



#### Selection guide

Emitting color Common	Red	Orange	Yellow	Green
Anode	LAP-401VD	LAP-401DD	LAP-401YD	LAP-401MD
Cathode	LAP-401VN	LAP-401DN	LAP-401YN	LAP-401MN


#### Pin assignments


Pi

n No.		
1	+ <u>a</u> +	10
2	+ /f/ /b/ +	9
3	+ g +	8
4	+ e c +	7
5	+ +	6
	D.P	

Pin No.	Function
1	Common
2	Segment "f"
3	Segment "g"
4	Segment "e"
5	Segment "d"
6	Common
7	D.P
8	Segment "c"
9	Segment "b"
10	Segment "a"

#### Inner circuit (anode common)





Downloaded from: http://www.datasheetcatalog.com/

#### ●Absolute maximum ratings (Ta=25°C)

Parameter	Symbol	Red	Orange	Yellow	Green	Unit	
	- ,	LAP-401VD / VN	LAP-401DD / DN	LAP-401YD / YN	LAP-401MD / MN		
Power dissipation	PD	448	448	448	448	mW	
Power dissipation	PD / seg	56	56	56	56	mW	
Forward current	lF	20	20	20	20	mA	
Peak forward current	IFP	60 * <sup>1</sup>	60 *1	60 * <sup>1</sup>	60 *1	mA	
Reverse voltage	VR	5	5	5	5	V	
Operating temperature	Topr		-25 to	o +75		°C	
Storage temperature	Tstg		-30 to	o +85		°C	
1 D L							

\*1 Pulse width 1ms Duty 1 / 5

#### •Electrical characteristics (Ta=25°C)

Parameter	Symbol	Conditions	R	ed	Ora	inge	Yel	low	Gre	een	Unit
			Тур.	Max.	Тур.	Max.	Тур.	Max.	Тур.	Max.	
Forward voltage	VF	I <sub>F</sub> =10mA	1.9	2.6	1.9	2.6	1.9	2.6	1.9	2.6	V
Reverse current	IR	Vr=3V	_	100	_	100	_	100	_	100	μΑ
Peak wavelength	λρ	I <sub>F</sub> =10mA	650	_	605	-	590	-	572	-	nm
Spectral line half width	Δλ	I <sub>F</sub> =10mA	20	_	20	-	20	_	20	-	nm

○ The products are not radiations resistant.

#### •Luminous intensity

Color	λ⊳ (nm)	Туре	Min.	Тур.	Unit	
Red	650	LAP-401VD	14	36	mcd	
Rea	000	LAP-401VN	14	30	mcu	
Orongo	605	LAP-401DD	50	250	mad	
Orange	600	LAP-401DN	56	250	mcd	
Yellow	590	LAP-401YD	90	450	mod	
reliow	590	LAP-401YN	90	450	mcd	
Croon	570	LAP-401MD	26	100	mad	
Green	572	LAP-401MN	36	100	mcd	

Downloaded from: http://www.datasheetcatalog.com/

#### •Electrical and optical characteristic curve




Fig.1 Forward Current - Forward Voltage




Fig.3 Relative Luminous Intensity -Case Temperature(°C)




Fig.5 Derating






Fig.2 Relative Luminous Intensity -Forward Current





	g or reproduction of this document, in part or in whole, is permitted without the ROHM Co.,Ltd.
The conten	t specified herein is subject to change for improvement without notice.
"Products"	t specified herein is for the purpose of introducing ROHM's products (hereinaft ). If you wish to use any such Product, please be sure to refer to the specification be obtained from ROHM upon request.
illustrate th	of application circuits, circuit constants and any other information contained here e standard usage and operations of the Products. The peripheral conditions mu to account when designing circuits for mass production.
However, s	was taken in ensuring the accuracy of the information specified in this documer should you incur any damage arising from any inaccuracy or misprint of suc , ROHM shall bear no responsibility for such damage.
examples of implicitly, a other partie	cal information specified herein is intended only to show the typical functions of ar of application circuits for the Products. ROHM does not grant you, explicitly ny license to use or exercise intellectual property or other rights held by ROHM ar es. ROHM shall bear no responsibility whatsoever for any dispute arising from the technical information.
equipment	ets specified in this document are intended to be used with general-use electron or devices (such as audio visual equipment, office-automation equipment, commu vices, electronic appliances and amusement devices).
The Produc	ts specified in this document are not designed to be radiation tolerant.
	M always makes efforts to enhance the quality and reliability of its Products, ay fail or malfunction for a variety of reasons.
against the failure of ar shall bear r	sure to implement in your equipment using the Products safety measures to guar possibility of physical injury, fire or any other damage caused in the event of th y Product, such as derating, redundancy, fire control and fail-safe designs. ROH to responsibility whatsoever for your use of any Product outside of the prescribe of in accordance with the instruction manual.
system whi may result instrument, controller c of the Proc	cts are not designed or manufactured to be used with any equipment, device of ch requires an extremely high level of reliability the failure or malfunction of whice in a direct threat to human life or create a risk of human injury (such as a medic transportation equipment, aerospace machinery, nuclear-reactor controller, fuel or other safety device). ROHM shall bear no responsibility in any way for use of ar lucts for the above special purposes. If a Product is intended to be used for an al purpose, please contact a ROHM sales representative before purchasing.
be controlle	d to export or ship overseas any Product or technology specified herein that ma ed under the Foreign Exchange and the Foreign Trade Law, you will be required ense or permit under the Law.



Thank you for your accessing to ROHM product informations. More detail product informations and catalogs are available, please contact us.

## ROHM Customer Support System

http://www.rohm.com/contact/

Downloaded from: http://www.datasheetcatalog.com/