

S3A THRU S3M

3.0 AMPS. Surface Mount Rectifiers



Voltage Range 50 to 1000 Volts Current 3.0 Amperes

SMC/DO-214AB

Features

- ♦ For surface mounted application
- Glass passivated junction chip.
- Low forward voltage drop
- High current capability
- ♦ Easy pick and place
- High surge current capability
- Plastic material used carries Underwriters Laboratory Classification 94V-O
- High temperature soldering:
- ♦ 260°C / 10 seconds at terminals

Mechanical Data

- Case: Molded plasticTerminals: Solder plated
- ♦ Polarity: Indicated by cathode band
- Packaging: 16mm tape per EIA STD RS-481
- Weight: 0.21 gram

.129(3.27) .118(3.0) .245(6.22) .220(5.59) .220(5.59) .220(6.60) .012(31) .006(15) .008(20) .030(0.76)

Dimensions in inches and (millimeters)

Maximum Ratings and Electrical Characteristics

Rating at 25°C ambient temperature unless otherwise specified.

Single phase, half wave, 60 Hz, resistive or inductive load.

For capacitive load, derate current by 20%

if of capacitive load, defate current by 20%								
Symbol	S3A	S3B	S3D	S3G	S3J	S3K	S3M	Units
V_{RRM}	50	100	200	400	600	800	1000	V
V_{RMS}	35	70	140	280	420	560	700	V
V_{DC}	50	100	200	400	600	800	1000	V
I _(AV)	3.0							Α
I _{FSM}	100							Α
V _F	1.15							>
I_	10.0							uA
^{IR} 250							uA	
$R\theta_{JL}$	13							℃ /W
$R\theta_{JA}$	47							
Trr	2.5							uS
Cj	60							pF
TJ	-55 to +150							Ç
Tstg	-55 to +150							Ų
	$\begin{tabular}{c c} Symbol \\ \hline V_{RRM} \\ \hline V_{RMS} \\ \hline V_{DC} \\ \hline I_{(AV)} \\ \hline I_{FSM} \\ \hline V_{F} \\ \hline I_{R} \\ \hline R_{\theta JL} \\ R_{\theta JA} \\ \hline Trr \\ \hline Cj \\ \hline T_{J} \\ \hline \end{tabular}$	Symbol S3A V _{RRM} 50 V _{RMS} 35 V _{DC} 50 I _(AV) I _{FSM} V _F I _R R θ _{JA} Trr Cj T _J	Symbol S3A S3B V _{RRM} 50 100 V _{RMS} 35 70 70 70 70 70 70 70 7	Symbol S3A S3B S3D V _{RRM} 50 100 200 V _{RMS} 35 70 140 V _{DC} 50 100 200 I _(AV) I _{FSM} V _F I _R R θ _{JA} Trr Cj T _J -58	$\begin{array}{ c c c c c c } \hline \textbf{Symbol} & \textbf{S3A} & \textbf{S3B} & \textbf{S3D} & \textbf{S3G} \\ \hline V_{RRM} & 50 & 100 & 200 & 400 \\ \hline V_{RMS} & 35 & 70 & 140 & 280 \\ \hline V_{DC} & 50 & 100 & 200 & 400 \\ \hline I_{(AV)} & & & & & & & & \\ \hline I_{FSM} & & & & & & & \\ \hline V_F & & & & & & & \\ \hline I_R & & & & & & & \\ \hline I_R & & & & & & & \\ \hline I_R & & & & & & & \\ \hline I_R & & & & & & & \\ \hline I_R & & & & & & & \\ \hline I_R & & & & & & & \\ \hline I_R & & & & & \\ \hline I_R & & & & & & \\ \hline I_R & & & & & \\ I_R & & & & & \\ \hline I_R & & & & \\ \hline I_R & & & & & \\ I_R & & & & & \\ \hline I_R & & & & \\ \hline I_R & & & & & \\ \hline I_R & & & & & \\ \hline I_R & & & & \\ I_R & & & & & \\ \hline I_R & & & & \\ I_R & & & \\$	$ \begin{array}{ c c c c c c c c c c c c c c c c c c c$	$ \begin{array}{ c c c c c c c c c c c c c c c c c c c$	$ \begin{array}{ c c c c c c c c c c c c c c c c c c c$

Notes: 1. Reverse Recovery Test Conditions: I_F=0.5A, I_R=1.0A, I_{RR}=0.25A

- 2. Measured at 1 MHz and Applied V_R =4.0 Volts
- 3. Measured on P.C. Board with 0.6 x 0.6" (16 x 16mm) Copper Pad Areas.



