

# Power Transformer Chassis Mount: Quick Pack

## FD6-20

## **Description:**

The FD6-20 Quick Pack small power transformer offers a significant reduction in size and weight over a standard transformer. This transformer can be used for a wide variety of applications. It is bobbin wound for reduced size and small operating space.

### Electrical Specifications (@25C):

Maximum Power: 30.0VA

Input Voltage:

Series: 230VAC@50/60Hz Parallel: 115VAC@50/60Hz Output Voltage: 20.0VCT@1.5A

Hipot: 2500VAC primary to secondary; 1500VAC windings to core.

#### Construction:

Split bobbing non concentric winding eliminates costly electrostatic shielding. Termination is suitable for quick connects or soldering. Built with UL Class B Insulation System.

### Safety:

UL: File E53148, UL 5085-1 and 2 (formerly UL 506), General Purpose.



#### **Dimensions:**


А	В	С	D	Е	F	G
1.937	2.812	3.250	1.687	2.312	.187 Dia	1.062

Notes: 1. Units: inches.

2. Terminal size: .187" X 0.021".

3. Weight: 1.10 lbs

#### Schematic:



**Input (115V):** Input 1 & 2

Connect 1&4, 2&5


Input (230V): Input 1 & 5


Connect 2&4

**RoHS Compliance:** As of manufacturing date February 2005, all standard products meet the requirements of 2011/65/EU, known as the RoHS initiative..

\* Upon printing, this document is considered "uncontrolled". Please contact Triad Magnetics' website for the most current version.







Web: www.TriadMagnetics.com Phone 951-277-0757 Fax 951-277-2757

460 Harley Knox Blvd. Perris, California 92571

Output: 6 & 10

Publish Date: December 4, 2013