


Switchmode/ High Frequency Rod Core Inductors

FIRCH-5

Description:

Triad high current rod core inductors provide cost effective energy storage. By conditioning the output signal, the inductor smoothes out the current waveform to provide a more stable current. These low cost inductors are designed to be compatible with automated P.C.B. installation.




Outline Dimensions:

- A. Dimensions: As figure show Unit: In inch B. PIN DIM. : As figure show
- C. WT Lbs. : 0.03 Lbs.

Type No.	+/- 15%	DC Rated	Max. DC Resistance	Lead
	Inductance uH	Current	(mOhms)	Diameter
FRICH-5	5.90	5.70A	18.50	0.032"

Inductance at 20KHz to 200KHz Rated current 40C temperature rise.



* Upon printing, this document is considered "uncontrolled". Please contact Triad Magnetics' website for the most current version.

web: www.TriadMagnetics.com	460 Harley Knox Blvd.	Publish Date: December 4, 2013
Phone 951-277-0757	Perris, California 92571	
Fax 951-277-2757		

