

Electro-optical Characteristics

(Ta= 25°C)

Parameter		Symbol	Conditions	MIN.	TYP.	MAX.	Unit	
Input	Forward voltage	S11MD5T/S21MD4TV S21MD3TV	$I_F = 20\text{mA}$	-	1.2	1.4	V	
			$I_F = 30\text{mA}$					
	Reverse current	I_R	$V_R = 3\text{V}$	-	-	10^{-5}	A	
Output	Repetitive peak OFF-state current	I_{DRM}	$V_{DRM} = R_{\text{rated}}$	-	-	10^{-6}	A	
	ON-state voltage	S11MD5T S21MD3TV/S21MD4TV	$I_T = 0.1\text{A}$	-	1.3	2.0	V	
				-	1.7	2.5	V	
	Holding current	I_H	$V_D = 6\text{V}$	0.1	1	3.5	mA	
	Critical rate of rise of OFF-state voltage	S11MD5T/S21MD4TV S21MD3TV	dV/dt	$V_{DRM} = 1/\sqrt{2}$ Rated	100	-	-	V/ μs
500					-	-	V/ μs	
Zero-cross voltage	S21MD4TV	V_{OX}	Resistance load $I_F = 15\text{mA}$	-	-	35	V	
Transfer characteristics	Minimum trigger current	I_{FT}	$V_D = 6\text{V}$ $R_L = 100\Omega$	-	-	10	mA	
	Isolation resistance	R_{ISO}	DC500V 40 to 60% RH	5×10^{10}	10^{11}	-	Ω	
	Turn-on time	S11MD5T S21MD3TV S21MD4TV	t_{on}	$V_D = 6\text{V}, I_F = 20\text{mA}^{*4}$ $R_L = 100\Omega$	-	80	200	μs
					-	-	100	μs
-					20	50	μs	

*4 **S21MD3TV** : $I_F=30\text{mA}$

Fig. 1 RMS ON-state Current vs. Ambient Temperature




Fig. 2 Forward Current vs. Ambient Temperature




Fig. 3 Forward Current vs. Forward Voltage




Fig. 4 Minimum Trigger Current vs. Ambient Temperature




Fig. 5 Relative Repetitive Peak OFF-state Voltage vs. Ambient Temperature




Fig. 6-a ON-state Voltage vs. Ambient Temperature (S11MD5T)




Fig. 6-b ON-state Voltage vs. Ambient Temperature (S21MD3TV/S21MD4TV)




Fig. 7 Holding Current vs. Ambient Temperature




Fig. 8-a Repetitive Peak OFF-state Current vs. OFF-state Voltage




Fig. 8-b Repetitive Peak OFF-state Current vs. OFF-state Voltage




Fig. 9-a Repetitive Peak OFF-state Current vs. Ambient Temperature




Fig. 9-b Repetitive Peak OFF-state Current vs. Ambient Temperature




Fig.10 Turn-on Time vs. Forward Current




Fig.11 Zero-cross Voltage vs. Ambient Temperature






Fig.12 ON-state Current vs. ON-state Voltage



Basic Operation Circuit

Medium/High Power Triac Drive Circuit



Note) Please use on condition of the triac for power triggers.
Zero-cross circuit is applied to **S21MD4TV**.

- Please refer to the chapter “Precautions for Use.”