

Structure Silicon Monolithic Integrated Circuit
 Product Series System Motor Driver for Portable MD
 Type **BD6607KN**

- Features
- Operates at low power supply voltage (VCC=1.8V min.)
 - Incorporates two, 3-phase half-bridge driver circuits (low ON resistance power DMOS 0.85Ω typ.)
 - Incorporates two H-bridge driver circuits (low ON resistance power DMOS 0.70Ω typ.)
 - Incorporates two comparator circuits for motor BEMF voltage detection
 - Incorporates a standby circuit (current at standby 0μA)
 - Incorporates thermal shutdown circuit

○Absolute maximum ratings (Ta=25°C)

Parameter	Symbol	Limits	Unit
Power supply voltage for control circuit	VCC	7	V
Power supply voltage for driver	VM	7	V
Power supply voltage for pre-driver circuit	VG	15	V
Input voltage	VIN	0~VCC	V
Driver output current	Iomax.	*1000	mA
Power dissipation	Pd	**1250	mW
Operating temperature range	Topr	-25~+75	°C
Storage temperature range	Tstg	-55~+150	°C
Junction temperature	Tjmax	150	°C

* Must not exceed Pd or ASO, Tjmax=150°C.

** Reduced by 10mW/°C over Ta=25°C, when mounted on a glass epoxy board (70mmx70mmx1.6mm).

○Operating conditions (Ta=-25~+75°C)

Parameter	Symbol	Min.	Typ.	Max.	Unit
Power supply voltage for control circuit	VCC	1.8	2.4	5.0	V
Power supply voltage for driver	VM	0.9	1.2	5.0	V
Power supply voltage for pre-driver circuit	VG	VM+5	-	12	V
Input voltage for logic signal *1	VIL	0	-	VCC	V
Input voltage for analog signal *2	VIA	0	-	VM	V

*1 : 1 STALL, ST1, ST2, FI1, RI1, FI2, RI2, UI1, VI1, WI1, PWM1, UI2, VI2, WI2, PWM2 pins

*2 : CPU1, CPUV1, CPW1, CPCOM1, CPUI2, CPV2, CPW2, CPCOM2 pins

This product described in this specification is not judged whether it applies to COCOM regulations.

Please confirm in case of export.

This product is not designed for protection against radioactive rays.

○Electrical characteristics

(Unless otherwise specified, Ta=25°C, VCC=2.4V, VM=1.2V, VG=6.8V)

Parameter	Symbol	Limit			Unit	Conditions
		Min.	Typ.	Max.		
Control circuit current at standby	ICCST	-	-	1	μA	STALL=L(*1)
Driver power supply current at standby	IMST	-	-	1	μA	STALL=L(*1)
Pre-driver power supply current at standby	IGST	-	-	1	μA	STALL=L(*1)
Power supply current of control circuit at no signal	ICCN	-	4	10	μA	STALL=L(*1)
Power supply current of pre-driver at no signal	IGN	-	100	160	μA	STALL=L(*1)
Power supply current of control circuit at operation	ICC	-	8	15	μA	STALL=H,ST1=ST2=L(*2)
Power supply current of pre-driver at operation	IG	-	0.7	0.95	mA	STALL=H,ST1=ST2=L(*2)
【Logic input】						
Logic H level input voltage	VIH	VCC x0.8	-	-	V	
Logic L level input voltage	VIL	-	-	VCC x0.2	V	
Logic H level input current	IIH	-	-	1	μA	FI, RI, UI, VI, WI, PWM pins
Logic L level input current	IIL	-1	-	-	μA	FI, RI, UI, VI, WI, PWM pins
ST pin pull-down resistance	RST	0.33	0.6	1.0	MΩ	applied to STALL, ST1,ST2 pins
【BEMF voltage detection comparator】						
Comparator input offset voltage	VOS	-5	-	5	mV	
Comparator input current	ICP	-1	-	1	μA	
Comparator H level output voltage	VOH	VCC x0.8	-	-	V	Isource=500μA
Comparator L level output voltage	VOL	-	-	VCC x0.2	V	Isink=500A
【Power MOS】						
H-bridge output ON resistance	RON1,2	-	0.7	1.30	Ω	upper and lower ON resistance in total
Half-bridge output ON resistance	RONU,V,W	-	0.85	1.55	Ω	upper and lower ON resistance in total

* 1 : Each input pin=L or H

* 2 : PWM1, PWM2 pins=176.4kHz, each H-bridge input pin= 88.2kHz, each 3-phase half-bridge input pin=100Hz

©This product is not designed for protection against radioactive rays.

○Notes on the use

- (1) Absolute maximum ratings
If the input voltage or the operating temperature range exceeds absolute maximum ratings, IC may be damaged. No destruction mode (e.g., short-circuiting or open) can be specified in that case. If such special mode as will exceed absolute maximum ratings is assumed, take the physical safety measures, such as a fuse.
- (2) Power supply lines
The regenerated current by BEMF of the motor will return. Therefore, take measures, such as the insertion of a capacitor between the power supply and GND as the pass of the regenerated current. Determine the capacitance in full consideration of all the characteristics of the electrolytic capacitor, because the electrolytic capacitor may lose some capacitance at low temperatures.
- (3) Ground potential
Ensure a minimum GND pin potential in all operating conditions.
- (4) Design for heat
Use the design for heat that allows for a sufficient margin in light of the power dissipation (Pd) in actual using conditions.
- (5) Operation in strong magnetic field
Use caution when using the IC in the strong magnetic field as doing so may cause the IC to malfunction.
- (6) ASO
When using the IC, make settings so that the output transistors for the motor will not be used under conditions in excess of the absolute maximum ratings and ASO.
- (7) Thermal shutdown circuit
This IC incorporates thermal shutdown circuit(TSD circuit).
When the chip temperature becomes the one shown in below, TSD circuit operates and makes the coil output to motor open. It is designed to shut the IC off from runaway thermal operation. It is not designed to protect the IC or guarantee its operation. Do not continue to use the IC after operating this circuit or use the IC in an environment where the operation of this circuit is assumed.

TSD ON temperature[°C] (typ.)	Hysteresis temperature [°C] (typ.)
175	25

- (8) Ground wiring pattern
When having both small signal and large current GND, it is recommended to isolate the two GND patterns, placing a single ground point at the application's reference point so that the pattern wiring resistance and voltage variations caused by large currents do not cause voltage variations of the small signal GND. Be careful not to change the GND wiring pattern of any external parts, either.

Notes

- No technical content pages of this document may be reproduced in any form or transmitted by any means without prior permission of ROHM CO.,LTD.
- The contents described herein are subject to change without notice. The specifications for the product described in this document are for reference only. Upon actual use, therefore, please request that specifications to be separately delivered.
- Application circuit diagrams and circuit constants contained herein are shown as examples of standard use and operation. Please pay careful attention to the peripheral conditions when designing circuits and deciding upon circuit constants in the set.
- Any data, including, but not limited to application circuit diagrams information, described herein are intended only as illustrations of such devices and not as the specifications for such devices. ROHM CO.,LTD. disclaims any warranty that any use of such devices shall be free from infringement of any third party's intellectual property rights or other proprietary rights, and further, assumes no liability of whatsoever nature in the event of any such infringement, or arising from or connected with or related to the use of such devices.
- Upon the sale of any such devices, other than for buyer's right to use such devices itself, resell or otherwise dispose of the same, no express or implied right or license to practice or commercially exploit any intellectual property rights or other proprietary rights owned or controlled by
- ROHM CO., LTD. is granted to any such buyer.
- Products listed in this document are no antiradiation design.

The products listed in this document are designed to be used with ordinary electronic equipment or devices (such as audio visual equipment, office-automation equipment, communications devices, electrical appliances and electronic toys).

Should you intend to use these products with equipment or devices which require an extremely high level of reliability and the malfunction of which would directly endanger human life (such as medical instruments, transportation equipment, aerospace machinery, nuclear-reactor controllers, fuel controllers and other safety devices), please be sure to consult with our sales representative in advance.

About Export Control Order in Japan

Products described herein are the objects of controlled goods in Annex 1 (Item 16) of Export Trade Control Order in Japan.

In case of export from Japan, please confirm if it applies to "objective" criteria or an "informed" (by MITI clause) on the basis of "catch all controls for Non-Proliferation of Weapons of Mass Destruction.