

## SANYO Semiconductors DATA SHEET

ExPD (Excellent Power Device)

# TN6R03—Switching Regulator IC for RCC **Method Power Supplies Applications**

#### **Features**

- · Original contorol IC for Delay RCC-type.
- · High voltage power MOSFET with current sense.
- · Overload protection.
- · Only few external components required.
- Small Full-Isolation package: TO-220FI5H.

#### **Specifications**

#### Absolute Maximum Ratings at Ta=25°C

Parameter	Symbol	Conditions	Ratings	Unit
Drain-to-Source Voltage	VDS		650	V
Drain Current (DC)	ΙD		4.5	Α
Drain Current (Pulse)	IDP	PW≤10μs, duty cycle≤1%	13.5	Α
IC Input Voltage	VIN		30	V
Allowable Power Dissipation	Do		2.0	W
Allowable Fower Dissipation	ole Power Dissipation PD	Tc=25°C	30	W
Operating Temperature	Topr		-25 to +125	°C
Junction Temperature	Tj		150	°C
Storage Temperature	Tstg		-55 to +150	°C

#### Electrical Characteristics at Ta=25°C

Parameter	Symbol	ymbol Conditions	Ratings			Unit
	Symbol		min	typ	max	Onit
[MOSFET]						
Drain-to-Source Breakdown Voltage	V(BR)DSS	I <sub>D</sub> =1mA, V <sub>DELAY</sub> =0	650			V
Zero-Gate Voltage Drain Current	IDSS	V <sub>DS</sub> =650V, V <sub>DELAY</sub> =0			1.0	mA
Cutoff Voltage	VGS(off)	VDS=10V, ID=1mA	3.0		4.0	V
Static Drain-to-Source On-State Resistance	R <sub>DS</sub> (on)	I <sub>D</sub> =2.3A, V <sub>DELAY</sub> =15V		1.55	2.0	Ω
Input Capacitance	Ciss	V <sub>DS</sub> =20V, f=1MHz		1150		pF
Output Capacitance	Coss	V <sub>DS</sub> =20V, f=1MHz		200		pF
[IC]						
Restriction of Drive Voltage	VIN(OV)	I <sub>IN</sub> =1mA, V <sub>FB</sub> =0	30			V
Detection Voltage of Feedback and Overload Amplifier	V <sub>FB</sub>	V <sub>DELAY</sub> , V <sub>IN</sub> =10V, I <sub>IN</sub> =50mA		2.0		V


- Any and all SANYO products described or contained herein do not have specifications that can handle applications that require extremely high levels of reliability, such as life-support systems, aircraft's control systems, or other applications whose failure can be reasonably expected to result in serious physical and/or material damage. Consult with your SANYO representative nearest you before using any SANYO products described or contained herein in such applications.
- SANYO assumes no responsibility for equipment failures that result from using products at values that exceed, even momentarily, rated values (such as maximum ratings, operating condition ranges, or other parameters) listed in products specifications of any and all SANYO products described or contained herein.

### **Recommend Operating Conditions** at Ta=25°C


Parameter	Symbol	Conditions	Ratings	Unit
IC Input Voltage	VIN		±10 to ±25	V
Operating Frequency	Fosc		20 to 200	kHz

#### **Package Dimensions**

unit : mm 2226



### **Block Diagram**




#### **Pin Functions**


Pin No.	Symbol	Function
1	FB	Input for feedback voltage and current sense
2	DELAY	Input for timing signal
3	DRAIN	Power MOSFET Drain
4	VIN	Input for Start-up voltage and drive voltage
5	SOURCE(GND)	Power MOSFET Source (Ground)

#### **Sample Application Circuit**


#### [Feedback control]





#### [Semi-regulated control]



#### **TN6R03**







- Specifications of any and all SANYO products described or contained herein stipulate the performance, characteristics, and functions of the described products in the independent state, and are not guarantees of the performance, characteristics, and functions of the described products as mounted in the customer's products or equipment. To verify symptoms and states that cannot be evaluated in an independent device, the customer should always evaluate and test devices mounted in the customer's products or equipment.
- SANYO Electric Co., Ltd. strives to supply high-quality high-reliability products. However, any and all semiconductor products fail with some probability. It is possible that these probabilistic failures could give rise to accidents or events that could endanger human lives, that could give rise to smoke or fire, or that could cause damage to other property. When designing equipment, adopt safety measures so that these kinds of accidents or events cannot occur. Such measures include but are not limited to protective circuits and error prevention circuits for safe design, redundant design, and structural design.
- In the event that any or all SANYO products(including technical data, services) described or contained herein are controlled under any of applicable local export control laws and regulations, such products must not be exported without obtaining the export license from the authorities concerned in accordance with the above law.
- No part of this publication may be reproduced or transmitted in any form or by any means, electronic or mechanical, including photocopying and recording, or any information storage or retrieval system, or otherwise, without the prior written permission of SANYO Electric Co., Ltd.
- Any and all information described or contained herein are subject to change without notice due to product/technology improvement, etc. When designing equipment, refer to the "Delivery Specification" for the SANYO product that you intend to use.
- Information (including circuit diagrams and circuit parameters) herein is for example only; it is not guaranteed for volume production. SANYO believes information herein is accurate and reliable, but no guarantees are made or implied regarding its use or any infringements of intellectual property rights or other rights of third parties.

This catalog provides information as of October, 2004. Specifications and information herein are subject to change without notice.