•

TLA 0814 is a 1:1 line matching transformer with the following features.


- Low cost.
- Conforming to FCC part 68 and CS03 regulations.
- Split primary and secondary windings.
- · DC capability.


## **Applications**

Interfacing of Telecommunications equipment to telephone lines where DC loop current handling capability is required.



## **MECHANICAL**





## **ELECTRICAL**

TLA 0814 has the following electrical performance when terminated with 600  $\Omega$  impedance and 100mA DC in the primary or the secondary winding.

| Frequency Response  |              | $\pm1.0~\mathrm{dB}$              | 200 - 5000 Hz            |
|---------------------|--------------|-----------------------------------|--------------------------|
| Insertion Loss      |              | < 1.25 dB                         | @ 1000 Hz                |
| Winding resistance  | Pri.<br>Sec. | nom. 53 $\Omega$ nom. 71 $\Omega$ | pins 1 - 4<br>pins 5 - 8 |
| Dielectric Strength |              | 1500 Vrms                         |                          |