

1.2GHz IF Converter w/AGC and Synthesizer



The ISL3787 is a highly integrated, UHF2, Half Duplex IF Converter, PLL Synthesizer and VCO IC device. It is part of the Intersil PRISM® V, 5GHz radio chipset.


The ISL3787 directly interfaces with the ISL3877 Wireless LAN Integrated Media Access Controller with Baseband Processor. Adding Intersil's ISL3687 5GHz RF/IF Converter with Integrated Synthesizer allows operation with a single SAW filter for both Transmit and Receive IF to Baseband functions. The addition of a power amplifier completes a Wireless LAN radio application for the 802.11a 5GHz standard.

The ISL3787 combines all the necessary IF to Baseband functions into a QFN Plastic Package suitable for miniPCI and PCMCIA applications.

Ordering Information

PART NUMBER	TEMP. RANGE (°C)	PACKAGE	PKG. DWG. #
ISL3787IR	-40 to 85	56 Lead QFN	L56.8 X 8
ISL3787IR-TK	-40 to 85	Tape and Reel	

Simplified Block Diagram



Features

- Frequency of Operation, RXin/TXout300 to 1200MHz
- Frequency of Operation, TXin/RXout10 to 30MHz
- Receive Voltage Gain78dB
- Wide Dynamic AGC Control.76dB
- Transmit Power Control Range40dB
- Integrated Antialiasing and Preshaping Filters
- Integrates a VCO and a Synthesizer PLL
- Low Supply Operation2.7-3.3V

Applications

- High Data Rate Wireless LAN IEEE 802.11a Systems
- PCI, miniPCI and PCMCIA Wireless LAN Adapters
- Spread Spectrum WLAN RF Modems
- TDMA or CSMA Packet Protocol Radios
- PCN/Wireless PBX/Wireless Local Loop

Pinout

