



VCO Product Specification

Model: VCO-219TC **Rev:** B **Date:** 12/11/2003

Customer:

Operating Temperature Range: (-55 ° to 100 ° C)

Parameter	Min	Typ	Max	Units	X	Remarks
Frequency Range -	3000		4800	MHz	X	
Tuning Voltage:						
3000 MHz	0	1.1		Vdc	X	
4800 MHz		14.5	20	Vdc	X	
Tuning Sensitivity:						
3000 MHz	89	118	148	MHz/V	X	Typical Linearity 3.0:1
3450 MHz	127	169	211	MHz/V	X	
3900 MHz	136	182	227	MHz/V	X	
4350 MHz	101	135	169	MHz/V	X	
4800 MHz	44	59	74	MHz/V	X	
Output Power -	-2.5	0.5	3.5	dBm	X	
Output Phase Noise:						
10 kHz		-81	-75	dBc/Hz	X	
100 kHz		-103	-97	dBc/Hz	X	
1000 kHz		-123	-117	dBc/Hz	X	
Power Supply -	14.5	15	15.5	Volts		
Supply Current -		18	23	mA	X	
Harmonic Suppression:						
2nd Harmonic		-25	-10	dBc	X	
3rd Harmonic		-30	-10	dBc	X	
Spurious (Non-Harmonic) -			-80	dBc		
Frequency Pushing - 14.5 TO 15.5 Volts		3	6	MHz p-p		
Frequency Pulling - 12 dBRL		16	22	MHz p-p		
Tuning Port Capacitance -		22		pF		
Output Impedance -		50		Ω		
Modulation:						
Bandwidth	15000	25000		kHz		Zg=50 Ohms

Package Information

Package Type:	SMT-2	Drawing Number:	A21959
Dimensions:	0.45 x 0.45 x 0.17 inches	Drawing Revision:	B

Comments

X Indicates parameter to be tested 100% in production

Also available in TO-8.

Performance tests and ratings for Sirenza Microdevices' products were performed internally by Sirenza and measured using specific computer systems and/or components and reflect the approximate performance of the the products as measured by those tests. Any difference in circuit implementation, test software, or test equipment may affect actual performance. The information provided herein is believed to be reliable at press time and Sirenza Microdevices assumes no responsibility for the use of this information. All such use shall be entirely at the user's own risk. Prices and specifications for Sirenza Microdevices' products are subject to change without notice. Buyers should consult Sirenza Microdevices' standard terms and conditions of sale for Sirenza's limited warranty with regard to its products. These products may be patented or include patented technology. No patent rights or licenses to any of the circuits described herein are implied or granted to any third party. Sirenza Microdevices does not authorize or warrant any product for use in life-support devices and/or systems.