




URS CORES



URS core is used in flying-back transformers in small TV sets and monitors. Round leg allows easy winding, also of strip conductors Because of the high voltages involved, the round shape helps to prevent corona effect

Features:

1. High Saturation Magnetic Flux Density (Bs)
2. Low Core Loss

Application of

1. Transformer for Power Supply
2. Fly Back Transformer for TV set and Monitor,Line filter transformers, Common mode choke, TV flyback transformers

Type	Dimensions(mm)							Ae(mm ²)	Ie(mm)
	A	B	C	D	E	F			
URS18.5	18.5±0.5	11.4±0.2	10.0±0.5	7.0±0.2	7.5±0.5	7.4±0.2	38.0	43.5	