# RENESAS HD74LVCZ16245A

# 16-bit Bidirectional Transceivers with 3-state Outputs

REJ03D0375–0200 (Previous ADE-205-233 (Z)) Rev.2.00 Aug. 20.2004

### Description

The HD74LVCZ16245A has sixteen two direction buffers, for the fittest at two direction bus lines with three state outputs in a 48 pin package. When (DIR) is high, data flows from the A inputs to the B outputs, and when (DIR) is low, data flows from the B inputs to the A outputs. A and B bus are separated by making enable input ( $\overline{G}$ ) high level.

When V<sub>CC</sub> is between 0 and 1.5 V, the device is in the high impedance state during power up or power down.

Low voltage and high-speed operation is suitable at battery drive product (note type personal computer) and low power consumption extends the life of a battery for long time operation.

### Features

- $V_{CC} = 2.7$  to 5.5 V
- All inputs  $V_{IH}$  (Max) = 5.5 V (@V<sub>CC</sub> = 0 to 5.5 V)
- All inputs / outputs  $V_{I/O}$  (Max) = 5.5 V (@V<sub>CC</sub> = 0 V or output off state)
- Typical V<sub>OL</sub> ground bounce < 0.8 V (@V<sub>CC</sub> = 3.3 V, Ta = 25°C)
- Typical V<sub>OH</sub> undershoot > 2.0 V (@V<sub>CC</sub> = 3.3 V, Ta =  $25^{\circ}$ C)
- High impedance state during power up and power down
- Power off disables outputs, permitting live insertion
- High output current  $\pm 24$  mA (@V<sub>CC</sub> = 3.0 to 5.5 V)
- Ordering Information

Part Name	Package Type	Package Code	Package Abbreviation	Taping Abbreviation (Quantity)
HD74LVCZ16245ATEL	TSSOP-48 pin	TTP-48DBV	Т	EL (1,000 pcs/reel)

#### **Function Table**

In	nute
m	puts

G	DIR	Operation	
L	L	B data to A bus	
L	Н	A data to B bus	
Н	X	Z	

H: High level

L: Low level

X: Immaterial

Z: High impedance



### **Pin Arrangement**

1DIR 1		48 1G
1B1 2		47 1A1
1B2 3		46 1A2
GND 4		45 GND
1B3 5		44 1A3
1B4 6		43 1A4
V <sub>CC</sub> 7		42 V <sub>CC</sub>
1B5 8		41 1A5
1B6 9		40 1A6
GND 10		39 GND
1B7 <u>11</u>		38 1A7
1B8 12		37 1A8
2B1 13		36 2A1
2B2 14		35 2A2
GND 15		34 GND
2B3 <u>16</u>		33 2A3
2B4 17		32 2A4
V <sub>CC</sub> 18		31 V <sub>CC</sub>
2B5 19		30 2A5
2B6 20		29 2A6
GND 21		28 GND
2B7 22		27 2A7
2B8 23		26 2A8
2DIR 24		25 2G
	(Top view)	

# **Absolute Maximum Ratings**

Item Symbol Ratings		Ratings	Unit	Conditions		
Supply voltage	V <sub>CC</sub>	–0.5 to 7.0	V			
Input voltage	VI	–0.5 to 7.0	V			
Input / output voltage	V <sub>I/O</sub>	–0.5 to 7.0	V	Output "Z" or V <sub>CC</sub> : OFF		
		–0.5 to V <sub>CC</sub> +0.5		Output "H" or "L"		
Input diode current	I <sub>IK</sub>	-50	mA	V <sub>1</sub> < 0		
Output diode current	Ι <sub>ΟΚ</sub>	-50	mA	V <sub>0</sub> < 0		
Output current	lo	±50	mA			
V <sub>CC</sub> , GND current	I <sub>CC</sub> or I <sub>GND</sub>	±100	mA			
Storage temperature	Tstg	-65 to 150	°C			

Note: The absolute maximum ratings are values, which must not individually be exceeded, and furthermore, no two of which may be realized at the same time.


RENESAS

# **Recommended Operating Conditions**

Item	Symbol	Ratings	Unit	Conditions
Supply voltage	V <sub>CC</sub>	2.7 to 5.5	V	At operation
Input voltage	VI	0 to 5.5	V	
Input / output voltage	V <sub>I/O</sub>	0 to 5.5	V	Output "Z" or V <sub>CC</sub> : OFF
		0 to V <sub>CC</sub>		Output "H" or "L"
Output current	I <sub>ОН</sub>	-12	mA	$V_{CC} = 2.7 V$
		-24 <sup>*1</sup>		$V_{CC}$ = 3.0 to 5.5 V
	IOL	12	mA	$V_{CC} = 2.7 V$
		24 <sup>*1</sup>		$V_{CC}$ = 3.0 to 5.5 V
Input rise / fall time	t <sub>r</sub> , t <sub>f</sub>	0 to 6	ns / V	
Operating temperature	Та	-40 to +85	°C	

Note: 1. Duty cycle  $\leq 50\%$ 

# Logic Diagram



# **Electrical Characteristics**

							$(Ta = -40 \text{ to } 85^{\circ}C)$
Item	Symbol	V <sub>cc</sub> (V)	Min	Тур	Мах	Unit	Test Conditions
Input voltage	VIH	2.7 to 3.6	2.0			V	
		4.5 to 5.5	V <sub>CC</sub> ×0.7	_		_	
	VIL	2.7 to 3.6	_		0.8	V	
		4.5 to 5.5			V <sub>CC</sub> ×0.3		
Output voltage	V <sub>OH</sub>	2.7 to 5.5	V <sub>CC</sub> -0.2			V	I <sub>OH</sub> = -100 μA
		2.7	2.2				I <sub>OH</sub> = -12 mA
		3.0	2.4				
		3.0	2.2				I <sub>OH</sub> = -24 mA
		4.5	3.8				
	V <sub>OL</sub>	2.7 to 5.5			0.2	V	I <sub>OL</sub> = 100 μA
		2.7			0.4		I <sub>OL</sub> = 12 mA
		3.0			0.55		I <sub>OL</sub> = 24 mA
		4.5			0.55		
Input current	I <sub>IN</sub>	0 to 5.5	_	_	±5	μA	$V_{IN} = 0$ to 5.5 V
Off state output	I <sub>OZ</sub>	2.7 to 5.5	_	_	±5	μA	$V_{OUT} = 0$ to 5.5 V
current	IOZPU	0 to 1.5	_	_	±5		V <sub>OUT</sub> = 0.5 to 5.5 V,
	IOZPD	1.5 to 0			±5		Output enable = don't care
Output leak current	I <sub>OFF</sub>	0	_	_	±5	μΑ	$V_{IN}$ or $V_O = 5.5 V$
Quiescent supply	Icc	2.7 to 3.6	_	_	225	μΑ	$V_{IN} = 3.6$ to 5.5 V <sup>*1</sup> , $I_0 = 0$
current		2.7 to 5.5	_	_	350		$V_{IN} = V_{CC} \text{ or } GND$
	$\Delta I_{CC}$	2.7 to 3.6	_	_	500	μΑ	$V_{IN}$ = one input at (V <sub>CC</sub> -0.6) V,
							other inputs at $V_{CC}$ or GND
Input capacitance	CIN	3.3	_	4.1	—	рF	$V_{IN} = V_{CC}$ or GND
Input / output capacitance	C <sub>I/O</sub>	3.3	—	9.2	_	pF	$V_{OUT} = V_{CC} \text{ or } GND$

Note: 1. This applies in the disabled state only.

## **Switching Characteristics**


							$(Ta = -40 \text{ to } 85^{\circ}C)$	
							FROM	то
Item	Symbol	V <sub>cc</sub> (V)	Min	Тур	Max	Unit	(Input)	(Output)
Propagation delay time	t <sub>PLH</sub>	2.7		_	5.2	ns	A or B	B or A
	t <sub>PHL</sub>	3.3±0.3	1.0	_	4.6			
		5.0±0.5	_	_	4.0			
Output enable time	t <sub>ZH</sub>	2.7	_	_	7.3	ns	G	A or B
	t <sub>ZL</sub>	3.3±0.3	1.5	_	6.3			
		5.0±0.5	_	_	5.2			
Output disable time	t <sub>HZ</sub>	2.7	_	_	7.5	ns	G	A or B
	t <sub>LZ</sub>	3.3±0.3	1.5	_	6.9			
		5.0±0.5			6.0			
Between output pin skew *1	t <sub>OSLH</sub>	2.7	_	_	_	ns		
	t <sub>OSHL</sub>	3.3±0.3	_	_	1.0			
		5.0±0.5	_	_	1.0			

Note: 1. This parameter is characterized but not tested.

 $t_{OSLH} = |t_{PLHm} - t_{PLHn}|, t_{OSHL} = |t_{PHLm} - t_{PHLn}|$ 




### **Test Circuit**




3. S1 : Input–Output change switch.






when enabled by the output control.

### Power up / down Characteristics



# **Package Dimensions**




RENESAS

### Renesas Technology Corp. Sales Strategic Planning Div. Nippon Bldg., 2-6-2, Ohte-machi, Chiyoda-ku, Tokyo 100-0004, Japan

Keep safety first in your circuit designs! 1. Renesas Technology Corp. puts the maximum effort into making semiconductor products better and more reliable, but there is always the possibility that trouble may occur with them. Trouble with semiconductors may lead to personal injury, fire or property damage. Remember to give due consideration to safety when making your circuit designs, with appropriate measures such as (i) placement of substitutive, auxiliary circuits, (ii) use of nonflammable material or (iii) prevention against any malfunction or mishap.

- Notes regarding these materials 1. These materials are intended as a reference to assist our customers in the selection of the Renesas Technology Corp. product best suited to the customer's application; they do not convey any license under any intellectual property rights, or any other rights, belonging to Renesas Technology Corp. or a third party. 2. Renesas Technology Corp. assumes no responsibility for any damage, or infringement of any third-party's rights, originating in the use of any product data, diagrams, charts, programs, algorithms, or circuit application examples contained in these materials. 3. All information contained in these materials, including product data, diagrams, charts, programs and algorithms represents information on products at the time of publication of these materials, and are subject to change by Renesas Technology Corp. without notice due to product improvements or other reasons. It is therefore recommended that customers contact Renesas Technology Corp. or an authorized Renesas Technology Corp. product distributor for the latest product information before purchasing a product listed herein.

- therefore recommended that customers contact Renesas Technology Corp. or an authorized Renesas Technology Corp. product distributor for the latest product information before purchasing a product listed herein.
  The information described here may contain technical inaccuracies or typographical errors.
  Renesas Technology Corp. assumes no responsibility for any damage, liability, or other loss rising from these inaccuracies or errors.
  Please also pay attention to information published by Renesas Technology Corp. by various means, including the Renesas Technology Corp. Semiconductor home page (http://www.renesas.com).
  4. When using any or all of the information contained in these materials, including product data, diagrams, charts, programs, and algorithms, please be sure to evaluate all information as total system before making a final decision on the applicability of the information and products.
  5. Renesas Technology Corp. emiconductors are not designed or manufactured for use in a device or system that is used under circumstances in which human life is potentially at stake. Please contact Renesas Technology Corp. or an authorized Renesas Technology Corp. product distributor when considering the use of a product contained herein for any specific purposes, such as apparatus or systems for transportation, vehicular, medical, aerospace, nuclear, or undersea repeater use. use.
- use.
   6. The prior written approval of Renesas Technology Corp. is necessary to reprint or reproduce in whole or in part these materials.
   7. If these products or technologies are subject to the Japanese export control restrictions, they must be exported under a license from the Japanese government and cannot be imported into a country other than the approved destination. Any diversion or reexport contrary to the export control laws and regulations of Japan and/or the country of destination is prohibited.
   8. Please contact Renesas Technology Corp. for further details on these materials or the products contained therein.





http://www.renesas.com

### **RENESAS SALES OFFICES**

#### Renesas Technology America, Inc.

450 Holger Way, San Jose, CA 95134-1368, U.S.A Tel: <1> (408) 382-7500 Fax: <1> (408) 382-7501

Renesas Technology Europe Limited. Dukes Meadow, Millboard Road, Bourne End, Buckinghamshire, SL8 5FH, United Kingdom Tel: <44> (1628) 585 100, Fax: <44> (1628) 585 900

Renesas Technology Europe GmbH Dornacher Str. 3, D-85622 Feldkirchen, Germany Tel: <49> (89) 380 70 0, Fax: <49> (89) 929 30 11

Renesas Technology Hong Kong Ltd. 7/F., North Tower, World Finance Centre, Harbour City, Canton Road, Hong Kong Tel: <852> 2265-6688, Fax: <852> 2375-6836

Renesas Technology Taiwan Co., Ltd. FL 10, #99, Fu-Hsing N. Rd., Taipei, Taiwan Tel: <886> (2) 2715-2888, Fax: <886> (2) 2713-2999

Renesas Technology (Shanghai) Co., Ltd. 26/F., Ruijin Building, No.205 Maoming Road (S), Shanghai 200020, China Tel: <86> (21) 6472-1001, Fax: <86> (21) 6415-2952

Renesas Technology Singapore Pte. Ltd. 1, Harbour Front Avenue, #06-10, Keppel Bay Tower, Singapore 098632 Tel: <65> 6213-0200, Fax: <65> 6278-8001