Neon Indicator Lamps

	Part	Old R of	Design Current	Maximum Breakdown Voltage	
Configuration	Part Number	Old Ref. Number	mA	VAC	VDC
G-10 D.C. Bayonet Base			_		
A B	L5A	NE-32	8.0	65	90
<u>•</u>					
S-11 Medium Screw Base	104	NE EC	F 0	60	0.5
A B	J9A J5A	NE-56 NE-30	5.0 8.0	60	85 85
S-14 Medium S crew Base		1	1		
A	R2A	NE-34	18.0	65	90
	W1A	AR-1	18.0	80	115
B	R6A	NE-40	30.0	65	90
S-14 D.C. Bayonet Skirted Base					
A	R9A	NE-42	30.0	65	90

Footnotes

- Life value is to approximately 50% of initial light output. Values shown apply to use on AC unless otherwise shown. Life on DC is approximately 60% of AC values when DC current is equal to RMS AC value. When equal DC and RMS AC voltages and equal
- resistances are utilized, life will be approximately the same.
- For DC operation of high brightness lamps use a minimum of 150 circuit volts. Maximum initial breakdown voltage 95 VAC, 135 VDC in light.
- 3. Tinned leads.
- 4. High brightness.
- 5. Formed tip.
- 6. Dark effect reduced.
- 7. Lamp drops through a Ø.310" cylinder of .500" minimum length.

147 Central Avenue Hackensack, NJ 07601 Phone: (201) 489-8989 Fax: (201) 489-6911 18703 Dix Toledo Road Brownstown, MI 48193 Saret Zone Franca, Edifico B Alajuela Costa Rica