

General Description

The MAX5216PMB1 peripheral module provides the necessary hardware to interface the MAX5216 16-bit DAC to any system that utilizes Pmod[™]-compatible expansion ports configurable for SPI communication. The IC is a single-channel, low-power, buffered voltage-output DAC. The reference voltage for the DAC is provided by a 2.5V output version of the MAX6029 voltage reference (0.15% initial accuracy, 30ppm/°C). Digital noise is minimized by having SPI input buffers powered down after completion of each serial input frame.

Refer to the MAX5216 IC data sheet for detailed information regarding operation of the IC.

Ordering Information appears at end of data sheet.

Features

- High-Accuracy 16-Bit DAC with On-Board Precision Voltage Reference
- Low Gain and Offset Errors
- Buffered Voltage Output Directly Drives 10kΩ Loads
- Optional External Voltage Reference (Jumper Selectable)
- ♦ 6-Pin Pmod-Compatible Connector (SPI)
- Example Software Written in C for Portability
- RoHS Compliant
- Proven PCB Layout
- Fully Assembled and Tested

MAX5216PMB1 Peripheral Module



Pmod is a trademark of Digilent Inc.

M/XI/N

Maxim Integrated Products 1

For pricing, delivery, and ordering information, please contact Maxim Direct at 1-888-629-4642, or visit Maxim's website at www.maxim-ic.com.

| Comp | onent | List |
|------|-------|------|
|------|-------|------|

| DESIGNATION | QTY | DESCRIPTION |
|-------------|-----|---|
| C1 | 1 | 10μF ±10%, 10V X5R ceramic capacitor (0603) TDK C2012X5R1A106K/1.25 |
| C2 | 1 | 1μF ±10%, 10V X7R ceramic capacitor (0603) TDK C1608X7R1A105K |
| C3, C4, C5 | 3 | 0.1µF ±10%, 16V X7R ceramic capacitors (0603) Murata GRM188R71C104KA01D |
| F1 | 1 | 4.7µF EMI filter (3-terminal capacitor) Murata NFM21PC475B1A3D |
| J1 | 1 | 6-pin right-angle male header |

| DESIGNATION | QTY | DESCRIPTION |
|-------------|-----|--|
| J2 | 1 | 4-pin straight male header |
| JP1 | 1 | 3-pin straight male header |
| R1, R2, R3 | 3 | 150 Ω ±5% resistors (0603) |
| R4 | 1 | 4.7k Ω ±5% resistor (0603) |
| U1 | 1 | 16-bit buffered single DAC (8 μMAX®) Maxim MAX5216GUA+ |
| U2 | 1 | Ultra-precision series voltage reference (5 SOT23) Maxim MAX6029EUK25+ |
| | 1 | Shorting jumper |
| | 1 | PCB: EPCB5216PM1 |

Component Suppliers

| SUPPLIER | PHONE | WEBSITE |
|--|--------------|-----------------------------|
| Murata Electronics North America, Inc. | 770-436-1300 | www.murata-northamerica.com |
| TDK Corp. | 847-803-6100 | www.component.tdk.com |

Note: Indicate that you are using the MAX5216PMB1 when contacting these component suppliers.

Detailed Description

SPI Interface

The MAX5216PMB1 peripheral module can plug directly into a Pmod-compatible port (configured for SPI) through connector J1. For information on the SPI protocol, refer to the MAX5214/MAX5216 IC data sheet.

J1 provides connection of the module to the Pmod host. See Table 1.

Connector J2 provides connection to the IC pins.

Jumper JP1 allows the user to select between reference voltages for the DAC IC (see Table 3).

Reference Voltage

The MAX5216PMB1 peripheral module contains a MAX6029 precision voltage reference for the REF input of the IC. The MAX6029 outputs a 2.5V reference.

Software and FPGA code

Example software and drivers are available that execute directly without modification on several FPGA development boards that support an integrated or synthesized microprocessor. These boards include the Digilent

 μMAX is a registered trademark of Maxim Integrated Products, Inc.

Table 1. Connector J1 (2-WireCommunication)

| PIN | SIGNAL | DESCRIPTION |
|-----|--------|--|
| 1 | SS | Chip enable. Assert low to enable the SPI interface. |
| 2 | MOSI | MAX5216 serial-data input |
| 3 | N.C. | Not connected |
| 4 | SCK | MAX5216 serial-clock input |
| 5 | GND | Ground |
| 6 | VCC | Power supply |

Table 2. Connector J2

| PIN | SIGNAL | DESCRIPTION |
|-----|--------|--|
| 1 | DACOUT | Buffered DAC output |
| 2 | CLR | Active-low asynchronous digital-clear input. Drive low to clear contents of the DAC registers and set the DAC output to zero. |
| 3 | VREFIN | DAC reference voltage input |
| 4 | GND | Ground |



Nexys 3, Avnet LX9, and Avnet ZEDBoard, although other platforms can be added over time. Maxim provides complete Xilinx ISE projects containing HDL, Platform Studio, and SDK projects. In addition, a synthesized bit stream, ready for FPGA download, is provided for the demonstration application.

Table 3. Jumper JP1 (Reference VoltageSelection)

| PINS | SELECTION |
|------|---|
| 2-1 | REF provided by on-board MAX6029EUK25 voltage reference |
| 2-3 | REF provided by user through pin 3 of connector J2 |

The software project (for the SDK) contains several source files intended to accelerate customer evaluation and design. These include a base application (maximModules.c) that demonstrates module functionality and uses an API interface (maximDeviceSpecificUtilities.c) to set and access Maxim device functions within a specific module.

The source code is written in standard ANSI C format, and all API documentation including theory/operation, register description, and function prototypes are documented in the API interface file (maximDeviceSpecificUtilities.h & .c).

The complete software kit is available for download <u>www.maxim-ic.com</u>. Quick start instructions are also available as a separate document.



Figure 1. MAX5216PMB1 Peripheral Module Schematic



Figure 2. MAX5216PMB1 Peripheral Module Component Placement Guide—Component Side



Figure 3. MAX5216PMB1 Peripheral Module PCB Layout—Component Side



Figure 4. MAX5216PMB1 Peripheral Module PCB Layout—Inner Layer 1 (Ground)





Figure 5. MAX5216PMB1 Peripheral Module PCB Layout—Inner Layer 2 (Power)



Figure 6. MAX5216PMB1 Peripheral Module PCB Layout—Solder Side



Figure 7. MAX5216PMB1 Peripheral Module Component Placement Guide—Solder Side



Ordering Information

| PART | ТҮРЕ | |
|--------------|-------------------|--|
| MAX5216PMB1# | Peripheral Module | |

#Denotes RoHS compliant.

Revision History

| REVISION | REVISION | DESCRIPTION | PAGES |
|----------|----------|-----------------|---------|
| NUMBER | DATE | | CHANGED |
| 0 | 5/12 | Initial release | — |

Maxim cannot assume responsibility for use of any circuitry other than circuitry entirely embodied in a Maxim product. No circuit patent licenses are implied. Maxim reserves the right to change the circuitry and specifications without notice at any time.

Maxim Integrated Products, 120 San Gabriel Drive, Sunnyvale, CA 94086 408-737-7600 ____

© 2012 Maxim Integrated Products

Maxim is a registered trademark of Maxim Integrated Products, Inc.