

PWA_(M)D-1W5&PWB_(M)D-1W5 Series

1.5W, WIDE INPUT, ISOLATED & REGULATED DUAL/SINGLE OUTPUT DIP DC-DC CONVERTER





multi-country patent protection RoHS

FEATURES

Wide input voltage(4:1)

Operating Temperature: -40°C to +85°C

1500VDC Input/Output Isolation

Short Circuit Protection(automatic recovery)

Internal SMD construction

No external component required

No Heat Sink Required **Industry Standard Pinout**

Five-sided shielding package(PWA/B_MD)

MTBF>1,000,000 hours RoHS Compliance

APPLICATIONS

The PWA_(M)D-1W5&PWB_(M)D-1W5 Series are specially designed for applications where a wide range input voltage power supplies are isolated from the input power supply in a distributed power supply system on a circuit board.

These products apply to:

- 1) Where the voltage of the input power supply is wide range (voltage range≤ 4:1);
- 2) Where isolation is necessary between input and output (Isolation Voltage≤1500VDC);
- 3) Where the regulation of the output voltage and the output ripple noise are demanded.


	Input			Output				
Part Number	Voltage (VDC)			No-load	Voltage	Current (mA)		Efficiency (%,typ.)
	Nominal	Range	Max*	(mA)(typ)	(VDC)	Max		
PWA2405(M)D-1W5		9.0-36	40	16	±5	±150	±15	74
PWA2412(M)D-1W5					±12	±63	±6	78
PWA2415(M)D-1W5					±15	±50	±5	79
PWB2403(M)D-1W5	24				3.3	500	50	72
PWB2405(M)D-1W5	24				5	300	30	74
PWB2409(M)D-1W5					9	167	17	76
PWB2412(M)D-1W5					12	125	12	78
PWB2415(M)D-1W5					15	100	10	80
PWA4805(M)D-1W5		18-72	80	8	±5	±150	±15	74
PWA4812(M)D-1W5	8 0				±12	±63	±6	78
PWA4815(M)D-1W5					±15	±50	±5	80
PWB4803(M)D-1W5	40				3.3	500	50	72
PWB4805(M)D-1W5	48				5	300	30	74
PWB4809(M)D-1W5					9	167	17	76
PWB4812(M)D-1W5					12	125	12	78
PWB4815(M)D-1W5					15	100	10	80
192								

^{*} Input voltage over it may cause permanent damage to the device.

Note: The load shouldn't be less than 10%, otherwise ripple will increase dramatically.

Operation under 10% load will not damage the converter; However, they may not meet all specification listed.

MODEL SELECTION PWA2412D-1W5



MORNSUN Science & Technology co.,Ltd.

Address: 2th floor 6th building, Huangzhou Industrial District, Guangzhou, China

Tel: 86-20-38601850 Fax: 86-20-38601272

Http://www.mornsun-power.com

OUTPUT SPECIFIC	ATIONS				
Item	Test Conditions	Min	Тур	Max	Units
Output Power	See below products program	0.15		1.5	W
Positive Voltage accuracy	Refer to recommended circuit		±1	±3	
Negative Voltage accuracy	Refer to recommended circuit		±3	±5	%
Load Regulation	From 10% to 100% load		±0.5	±2*	70
Line Regulation	Input voltage from low to high		±0.2	±0.75	
Temperature Drift	Refer to recommended circuit			±0.03	%/°C
Ripple**	20MHz bandwidth		20	50	mVp-p
Noise**	ise** 20MHz bandwidth		50	100	шур-р
Switching Frequency	100% load, nominal input voltage		300		KHz
** 1 * * * * * * * * * * * * * * * * *	11 1 . 504				


^{*} Dual output models unbalanced load: ±5%

- 1. All specifications measured at T_A=25°C, humidity<75%, nominal input voltage and rated output load unless otherwise specified.
- 2. See below recommended circuits for more details


^{**}Test ripple and noise by "parallel cable" method. See detailed operation instructions at Testing of Power Converter section, application notes.

COMMON SPECIFICATION						
Item	Test Conditions	Min	Тур	Max	Units	
Storage humidity				95	%	
Operating temperature		-40		85		
Storage Temperature		-55		125	°c	
Temp. rise at full load			15			
Lead temperature	1.5mm from case for 10 seconds			300		
Isolation voltage	Tested for 1 minute and 1mA max	1500			VDC	
Isolation resistance	Test at 500VDC	1000			ΜΩ	
Isolation capacitance			100		PF	
Cooling	Free air convection					
Case material	D: Plastic(UL94-V0); MD: Steel, nickel plated					
Short circuit protection	Continuous, automatic recovery					
MTBF		100			K hours	
Weight			15		g	

TYPICAL CHARECTERISTICS




OUTLINE DIMENSIONS & FOOTPRINT DETAILS



First Angle Projection +

RECOMMENDED FOOTPRINT Top view,grid:2.54mm(0.1inch) diameter:1.00mm(0.039inch)



FOOTPRINT DETAILS

NC:No Connection

Pi	n	Single	Dual
2,	3	GND	GND
9		NC	0V
10,	15	NC	NC
1	1	NC	-Vo
14	1	+Vo	+Vo
16	3	0V	0V
22,	23	Vin	Vin


APPLICATION NOTE

Requirement On Output Load

In order to ensure the product operate efficiently and reliably, in addition to a max load (namely full load), a minimum load is specified for this kind of DC/DC converter. Make sure the specified range of input voltage is not exceeded, the minimum output load no less than 10% load. If the actual load is less than the specified minimum load, the output ripple may increase sharply while its efficiency and reliability will reduce greatly. If the actual output power is very small, please add an appropriate resistor as extra loading, or contact our company for other lower output power products.

Recommended Circuit

All the PWA_(M)D-1W5 & PWB_(M)D-1W5 Series have been tested according to the following recommended testing circuit before leaving factory. (See Figure 1).



If you want to further decrease the input/output ripple, you can increase capacitance properly or choose capacitors with low ESR. However, the capacitance should not be too high, or may cause start-up problem. For every channel of output, provided the safe and reliable operation is ensured, the greatest capacitance of its filter capacitor sees (Table 1).If you want to use the products in high EMI, please choose our metal packaged products (PWA_MD-1W5 & PWB_MD-1W5). General:

Cin: 24V&48V 10µF-47µF

Cout: 10µF/100mA


Output External Capacitor Table (Table 1)

Catput External Capacitor rabio (rabio 1)					
Single Vout	Cout	Daul Vout	Cout		
(VDC)	(uF)	(VDC)	(uF)		
3.3	2200	±5	680		
5	1000	±12	330		
9	680	±15	220		
12	470				
15	330				

Input Current

When it is used in unregulated power supply,be sure that the fluctuating range of the power supply and the rippled voltage do not exceed the module standard. Input current of power supply should afford the startup current of this kind of DC/DC module. (See figure 2)

General: Ip ≤1.4*lin-max



No parallel connection or plug and play.