TECHNICAL DATA DATA SHEET 4710, REV. -

# HERMETIC POWER SCHOTTKY RECTIFIER 200°C Maximum Operation Temperature

**DESCRIPTION:** A 200-VOLT, 3/6 AMP, POWER SCHOTTKY RECTIFIER IN A HERMETIC TO-254 PACKAGE.


MAXIMUM RATINGS ARE	ALL RATINGS ARE $@$ T <sub>C</sub> = 25 °C UNLESS OTHERWISE SPECIFIED.				
RATING		SYMBOL	MAX.	UNITS	
PEAK INVERSE VOLTAGE		PIV	200	Volts	
MAXIMUM DC OUTPUT CURRENT (@ T <sub>C</sub> =100 <sup>O</sup> C) (Single, Doubler)		Ι <sub>Ο</sub>	3	Amps	
MAXIMUM DC OUTPUT CURRENT (@ T <sub>C</sub> =100 <sup>O</sup> C) (Common Cathode, Common Anode)		lo	6	Amps	
MAXIMUM NONREPETITIVE FORWARD SURGE CURRENT (t=8.3ms, Sine)		I <sub>FSM</sub>	55	Amps	
MAXIMUM JUNCTION CAPACITANCE	(V <sub>r</sub> =5V)	C <sub>T</sub>	60	pF	
MAXIMUM THERMAL RESISTANCE		$R_{ extsf{ heta}JC}$	3.17	°C/W	
MAXIMUM OPERATING TEMPERATURE RANGE		Top/Tstg	-65 to + 200	°C	
MAXIMUM STORAGE TEMPERATURE RANGE		Top/Tstg	-65 to + 200	°C	


### **ELECTRICAL CHARACTERISTICS**

CHARACTERISTIC		SYMBOL	MAX.	UNITS
MAXIMUM FORWARD VOLTAGE DROP, Pulsed ( $I_f = 3 \text{ Amps}$ )				
	$T_J = 25 \ ^{\circ}C$	V <sub>f</sub>	1.02	Volts
	T <sub>J</sub> = 125 °C		0.86	
MAXIMUM REVERSE CURRENT (I <sub>r</sub> @ 200 V PIV)				
	$T_J = 25 \ ^{\circ}C$	l <sub>r</sub>	0.07	mA
	T <sub>J</sub> = 125 °C		1.6	

## SENSITRON

#### TECHNICAL DATA DATASHEET 4710, REV. -





#### **PINOUT TABLE**

PINOUTTABLE				
ТҮРЕ	PIN 1	PIN 2	PIN 3	
SINGLE RECTIFIER	CATHODE	ANODE	ANODE	
DUAL RECTIFIER, COMMON CATHODE (P)	ANODE 1	COMMON CATHODE	ANODE 2	
DUAL RECTIFIER, COMMON ANODE (N)	CATHODE 1	COMMON ANODE	CATHODE 2	
DUAL RECTIFIER, DOUBLER (D)	ANODE			
Curves shown are for bare die only.		•		
Typical Forward Characteristics		Typical Reverse Characteristics		
10 <sup>0</sup> 10 <sup>1</sup> 10 <sup>1</sup> 10 <sup>-1</sup> 10 <sup>-1</sup> 10 <sup>-1</sup> 10 <sup>-1</sup>	Instantaneous Reverse Current - k (mA) Instantaneous Reverse Current - k (mA) 0	200 °C 175 °C 150 °C 125 °C 125 °C 100 °C 75 °C 50 °C 25 °C 40 80 120 160 20 Reverse Voltage - ¥ (V) Typical Junction Capacitance		
	Junction Capacitance - C <sub>T</sub> (pF)			
	Ction Cap			
Forward Voltage Drop - ¥ (V)		Reverse Voltage - ¥ (V)	00 240	
221 WEST INDUSTRY COURT • DEER PARK, NY     World Wide Web Site - http://www.sens				

World Wide Web Site - http://www.sensitron.com • E-mail Address - sales@sensitron.com •



#### **TECHNICAL DATA**

#### DISCLAIMER:

1- The information given herein, including the specifications and dimensions, is subject to change without prior notice to improve product characteristics. Before ordering, purchasers are advised to contact the Sensitron Semiconductor sales department for the latest version of the datasheet(s).

2- In cases where extremely high reliability is required (such as use in nuclear power control, aerospace and aviation, traffic equipment, medical equipment, and safety equipment), safety should be ensured by using semiconductor devices that feature assured safety or by means of users' fail-safe precautions or other arrangement.

3- In no event shall Sensitron Semiconductor be liable for any damages that may result from an accident or any other cause during operation of the user's units according to the datasheet(s). Sensitron Semiconductor assumes no responsibility for any intellectual property claims or any other problems that may result from applications of information, products or circuits described in the datasheets.
4- In no event shall Sensitron Semiconductor be liable for any failure in a semiconductor device or any secondary damage resulting from use at a value exceeding the absolute maximum rating.

5- No license is granted by the datasheet(s) under any patents or other rights of any third party or Sensitron Semiconductor.
6- The datasheet(s) may not be reproduced or duplicated, in any form, in whole or part, without the expressed written permission of Sensitron Semiconductor.

7- The products (technologies) described in the datasheet(s) are not to be provided to any party whose purpose in their application will hinder maintenance of international peace and safety nor are they to be applied to that purpose by their direct purchasers or any third party. When exporting these products (technologies), the necessary procedures are to be taken in accordance with related laws and regulations.