

## **ELECTRICAL SPECIFICATIONS:**

1.0 TURNS RATIO: (P6-P8-P3) : (J6-J3) (P2-P7-P1) : (J2-J1)

: 1CT : 1 +/-3% : 1CT : 1.4  $\pm /-3\%$ 

2.0 INDUCTANCE: (P6-P3) (P2-P1)

: 200uH MIN. @ 0.01V, 10KHz : 100uH MIN. @ 0.01V. 10KHz

3.0 LEAKAGE INDUCTANCE: P6-P3 (WITH J6 AND J3 SHORT) : 0.3uH MAX. @ 1MHz P2-P1 (WITH J2 AND J1 SHORT) : 0.3uH MAX. @ 1MHz

4.0 INTERWINDING CAPACITANCE: (P6,P3) TO (J6,J3) (P2,P1) TO (J2,J1)

: 10pf MAX @ 1MHz : 10pf MAX. @ 1MHz

5.0 DC RESISTANCE: (J6-J3)=(J2-J1)

(P6-P8)=(P8-P3) (P2-P7)=(P7-P1)

: 1.0 ohms Max. : 0.3 ohms Max. : 0.3 ohms Max.

6.0 DIELECTRIC WITHSTAND: (P6,P3) TO (J6,J3) (P2,P1) TO (J2,J1)

: 1500VAC : 1500VAC NOTES

1.0 PINS WITHOUT ELECTRICAL CONNECTION ARE OMITTED.

Bel Stewart Connector 11118 Susquehanna Trail, South

Glen Rock, Pa 17327-9199 717.234.7512

http://www.stewartconnector.com


SHEET 1 OF 3 DRAWING NO.

SI - 50133


THIS DRAWING AND THE SUBJECT MATTER SHOWN THEREON ARE CONFIDENTIAL AND PROPERTY OF BEL STEWART CONNECTOR AND SHALL NOT BE REPRODUCED, COPIED, OR USED IN ANY MANNER WITHOUT PRIOR WRITTEN CONTENT OF BEL STEWART CONNECTOR. THE SUBJECT MATTER MAY BE PATENTED OR A PATENT MAY BE PENDING.


STANDARD LED	WAVELENGTH	* Forward V (MAX)	(TYP)
RED	635 nm	2.5 V	2.1 V
YELLOW	590 nm	2.5 V	2.1 V


\* WITH A FORWARD CURRENT OF 20 mA



P.C.B. RECOMMENDED HOLE LAYOUT SEEN FROM COMPONENT SIDE TOLERANCE ±.003 [0.08] UNLESS OTHERWISE SPECIFIED







## NOTES:

- TOLERANCES COMPLY WITH F.C.C. DIMENSION REQUIREMENTS
- DIMENSIONS SHOWN WITH "\*" TO BE CENTRAL ABOUT CENTER LINE
- DIMENSIONS SHOWN ARE SUBJECT TO CHANGE WITHOUT NOTICE.
- PIN NOT ELECTRICALLY CONNECTED MAYBE OMITTED.
   SEE ELECTRICAL DRAWING FOR OMITTED PINS.
- 50 MICRO-INCH SELECTIVE GOLD PLATING CT750006

Bel Stewart Connector
11118 Susquehanna Trail, South


11118 Susquehanna Trail, Soutl Glen Rock, Pa 17327-9199 717.234.7512 MagJack

http://www.stewartconnector.com


THIS DRAWING AND THE SUBJECT MATTER SHOWN THEREON ARE CONFIDENTIAL AND PROPERTY OF BEL STEWART CONNECTOR AND SHALL NOT BE REPRODUCED, COPIED, OR USED IN ANY MANNER WITHOUT PRIOR WRITTEN CONTENT OF BEL STEWART CONNECTOR. THE SUBJECT MATTER MAY BE PATENTED OR A PATENT MAY BE PENDING.

SHEET DRAWING NO.

SI-50133 REV.C



PANEL GROUNDING BEAM DEFLECTION S.O.S. = SUGGESTED OPENING SIZE



POINT OF CONTACT WITH PANEL - .080 -- .275 MAX

THE SUGGESTED PANEL OPENING IS INTENDED TO GIVE THE USER THE ABILITY TO HAVE REASONABLE JACK / PANEL CLEARANCES YET MAINTAIN RELIABLE GROUNDING CAPABILITY. THESE VARIABLES CAN BE ADJUSTED IN EITHER DIRECTION BUT MAY CARRY SOME CONSEQUENCES IN THE FORM OF LOWER MATING FORCES OR TIGHTER ASSEMBLY TOLERANCES. FORCE VALUES ON THE GRAPH ARE GENERAL AVERAGES TAKEN AT THE POINT OF CONTACT SHOWN ABOVE. THE SUGGESTED PANEL OPENING INCLUDES APPROXIMATELY .020 CLEARANCE ON THE SIDES AND TOP AND .013 ON THE BOTTOM, AT PANEL OPENING.

.000 (TOP OF PCB TO BOTTOM OF OPENING) -.010 MAX. RADIUS(4)

SUGGESTED PANEL OPENING

CT720034X1/24-001302

**Bel Stewart Connector** 11118 Susquehanna Trail, South Glen Rock, Pa 17327-9199

717.234.7512

http://www.stewartconnector.com

SHEET 3 OF 3 DRAWING NO.

SI - 50133

THIS DRAWING AND THE SUBJECT MATTER SHOWN THEREON ARE CONFIDENTIAL AND PROPERTY OF BEL STEWART CONNECTOR AND SHALL NOT BE REPRODUCED, COPIED, OR USED IN ANY MANNER WITHOUT PRIOR WRITTEN CONTENT OF BEL STEWART CONNECTOR. THE SUBJECT MATTER MAY BE PATENTED OR A PATENT MAY BE PENDING.