



# 10 Amp SCHOTTKY BARRIER RECTIFIERS

FBR1035& 1045

### **Description**

### **Mechanical Dimensions**






#### **Features**

- HIGH CURRENT CAPABILITY WITH LOW V<sub>F</sub>
- SUPERIOR METAL PROCESS
- HIGH SURGE VOLTAGE AND TRANSIENT PROTECTION
- MEETS UL SPECIFICATION 94V-0

Electrical Characteristics @ 25°	C.	FBR1035 & 1045		Units
Maximum Ratings		FBR1035	FBR1045	
Peak Repetitive Reverse VoltageV <sub>RRM</sub>		35	45	Volts
Working Peak Reverse VoltageV <sub>RWM</sub>		35	45	Volts
DC Blocking Voltage $V_{\rm DC}$		35	45	Volts
RMS Reverse Voltage $V_{R(rms)}$		24	31	Volts
Average Forward Rectified Current $I_{F(av)}$ $T_c = 110^{\circ}C$			10	Amps
Repetitive Peak Forward Surge CurrentI <sub>FM</sub>			20	Amps
Non-Repetitive Peak Forward Surge CurrentI <sub>FSM</sub> @ Rated Load Conditions, ½ Wave, 60HZ, Single Phase			150	Amps
Forward VoltageV <sub>F</sub> @ I <sub>F</sub> = 20 Amps, 25°C @ I <sub>F</sub> = 20 Amps, 125°C @ I <sub>F</sub> = 10 Amps, 125°C			.84	Volts Volts Volts
$ \begin{array}{cccccccccccccccccccccccccccccccccccc$	= 25°C =125°C		.1	mAmps mAmps
Operating Temperature Range $T_J$		65	5 to 150	°C
Storage Temperature RangeT <sub>STRG</sub>		65	i to 175	°C



# 10 Amp SCHOTTKY BARRIER RECTIFIERS



- NOTES: 1. Measured @ 1 MHZ and applied reverse voltage of 4.0V.
  - 2. Thermal Resistance Junction to Case, Jedec Method.
  - 3. When Mounted to heat sink, from body.