# **HF9113**

### **TO-5 HERMETICALLY SEALED RELAY** WITH COIL TRANSIENT SUPPRESSION



#### Features

- Failure rate can be Level M
- Internal diode for coil transient suppression protection
- High ambient applicability
- All metal welded construction
- Hermetically welded and marked by laser

Conform to GJB65B-99 ( Equivalent to MIL-R-39016)

AMBIENT ADAPTABILITY								
Ambient Grade		I		II	III			
Ambient Tem	nperature	-55°C to 85°C	-65°C to 125°C		-65°C to 125°C			
Humidity				•	98%, 40°C			
Low Air Pres	sure				4.4KPa			
Vibration	Frequency	10Hz to 2000Hz	1	0Hz to 2000Hz	10Hz to 3000Hz			
Resistance	Acceleration	196m/s²		196m/s²	294m/s <sup>2</sup>			
Shock Resist	tance	735m/s <sup>2</sup>						
Random Vibration		40(m/s²)²/Hz						
Acceleration		490m/s²						
Implementation Standard		GJB65B-99 (MIL-R-39016)						
CONTAC	CT DATA							
Ambient Grade		I		II	III			
Arrangement		2 Form C						
Contact Material		Gold/Platinum/Palladium/Silver alloy		Gold/Platinum/Palladium/Silver alloy(Gold plated)				
Contact	Initial	125mΩ		100mΩ	100mΩ			
Resistance (n	nax.) After Life	250mΩ		200mΩ	200mΩ			
Failure Rate					Level L and M available			

## **Contact Ratings**

	Ambient Grade	Contact Load Type		Electrical Life (min.)	
	I	1.0A 28Vd.c.	Resistive	1 x 10 <sup>5</sup> OPS	
		1.0A 28Vd.c.	Resistive	1 x 10 <sup>5</sup> ops	
	II	0.1A 115Va.c.	Resistive	1 x 10 <sup>5</sup> ops	
	11	0.2A 28Vd.c. 320mH Inductive		1 x 10 <sup>5</sup> OPS	
		0.1A 28Vd.c.	Lamp	1 x 10 <sup>5</sup> ops	
		1.0A 28Vd.c.	Resistive	1 x 10⁵ ops	
		0.1A 115Va.c.	Resistive	1 x 10 <sup>5</sup> OPS	
	III	0.2A 28Vd.c. 320mH	Inductive	1 x 10 <sup>5</sup> OPS	
		0.1A 28Vd.c.	Lamp	1 x 10 <sup>5</sup> OPS	
		50μA 50mVd.c.	Low Level	1 x 10⁵ ops	



SPECIFICATION								
Ambient Grade		I	II	III				
Insulation Resistance (min.)		1000MΩ (at 500Vd.c.)	10000MΩ (at 500Vd.c.)	10000MΩ (at 500Vd.c.)				
	Between open contacts	500Vr.m.s.	500Vr.m.s.	500Vr.m.s.				
Dielectric	Between contacts & coil	500Vr.m.s.	500Vr.m.s.	500Vr.m.s.				
Strength min. (Normal condition)	Between contacts & cover	500Vr.m.s.	500Vr.m.s.	500Vr.m.s.				
(**************************************	Between contacts sets	500Vr.m.s.	500Vr.m.s.	500Vr.m.s.				
	Between coil & cover	500Vr.m.s.	500Vr.m.s.	500Vr.m.s.				
Dielectric Strength min. (Low air pressure condition)		125Vr.m.s.	125Vr.m.s.	125Vr.m.s.				
Leakage Rate		1 Pa•cm³/s	1 x 10 <sup>-2</sup> Pa•cm <sup>3</sup> /s	1 x 10 <sup>-3</sup> Pa•cm <sup>3</sup> /s				
Operate Time (max	.)	2ms						
Release Time (max	·.)	4ms						
Mounting Style		In-line package						
Terminals		PCB						
Work Position		Any position						
Weight		2.55g						

COIL DATA	
Norminal Coil Power	Approx. 0.5W

	Coil Version Vd.c.								
	Coi Vo	oltage 25°C				−65°C to 125°C			
	Nominal	Max	Pick-up Voltage max	Hold Voltage max	Drop-out Voltage min	Coil Resistance (1±10%) Ω	Pick-up Voltage max	Hold Voltage max	Drop-out Voltage min
	005	5.8	2.7	1.4	0.22	50	3.5	2.3	0.15
	006	8	3.5	2.0	0.28	98	4.5	3.2	0.18
_	009	12	5.3	3.0	0.54	220	6.8	4.9	0.35

390

880

9.0

13.5

18.0

6.5

10.0

13.0

0.40

0.58

0.89

0.63

0.91

 027
 32
 14.2
 8.0
 1.37
 1560

 Notes: We can offer many kinds of of coil voltage under the requirement of users.

4.0

6.0

7.0

10.5

#### **ORDERING INFORMATION**


24

012


018

	HF9113	-012	L	01	I				
Туре									
Coil Voltage	Coil Voltage 5, 6, 9, 12, 18, 27Vd.c.								
L: Failure rate level L (level III products available)  M: Failure Rate  M: Failure rate level M (level III products available)  Nil: Without failure rate requirement(level I, II products available)									
<b>Terminals Length</b> 01: 5mm 02: 12.5mm 03: 38mm									
Ambient Grade I : level I II : level II Nil: level III									

#### **Outline Dimensions**



#### Wiring Diagram



(Bottom View)

# 

Disclaimer

This datasheet is for the customers' reference. All the specifications are subject to change without notice.

We could not evaluate all the performance and all the parameters for every possible application. Thus the user should be in a right position to choose the suitable product for their own application. If there is any query, please contact Hongfa for the technical service. However, it is the user's responsibility to determine which product should be used only.

 $\ensuremath{\mathbb{C}}$  Xiamen Hongfa Electroacoustic Co., Ltd. All rights of Hongfa are reserved.