# HOA1180 Reflective Sensor

#### FEATURES

- Choice of phototransistor or photodarlington output
- · High sensitivity

DESCRIPTION

- Wide operating temperature range (- 55°C to +100°C)
- 12.0 in.(305 mm) min. 28 AWG PVC insulated wire leads

The HOA1180 series consists of an infrared emitting

(HOA1180-003), encased side- by- side on converging

optical axes in a black thermoplastic housing. The detector responds to radiation from the IRED only when

a reflective object passes within its field of view. The

components. For additional component information see

Housing material is polyester. Housings are soluble in

chlorinated hydrocarbons and ketones. Recommended

HOA1180 series employs metal can packaged

diode and an NPN silicon phototransistor

(HOA1180-001, - 002) or photodarlington




INFRA-24.TIF

### OUTLINE DIMENSIONS in inches (mm)

Tolerance

3 plc decimals ±0.010(0.25) 2 plc decimals ±0.020(0.51)



cleaning agents are methanol and isopropanol.

SE1450, SD1440, and SD1410.

Wire color code and functions are:

- All devices IRED anode - Red IRED cathode - Black
- HOA1180-001 Collector - Brown Emitter - Black
- HOA1180-002 Collector - Orange Emitter - Black
- HOA1180-003 Collector - Yellow Emitter - Black

Honeywell

DIM\_035.ds4

Honeywell reserves the right to make changes in order to improve design and supply the best products possible.

## 236

# **HOA1180**

**Reflective Sensor** 

ELECTRICAL CHARACTERISTICS (25°C unless otherwise noted)						
PARAMETER	SYMBOL	MIN	TYP	MAX	UNITS	TEST CONDITIONS
IR EMITTER						
Forward Voltage	Vf			1.6	V	l <sub>F</sub> =20 mA
Reverse Leakage Current	I <sub>R</sub>			10	μA	V <sub>R</sub> =3 V
DETECTOR Collector-Emitter Breakdown Voltage HOA1180-001, -002 HOA1180-003	V(BR)CEO	30 15			V	Ic=100 μΑ
Emitter-Collector Breakdown Voltage	V(BR)ECO	5.0			V	I <sub>E</sub> =100 μΑ
Collector Dark Current HOA1180-001, -002 HOA1180-003	Iceo			100 250	nA	V <sub>CE</sub> =10 V I⊧=0
COUPLED CHARACTERISTICS On-State Collector Current HOA1180-001 HOA1180-002 HOA1180-003	Ic(on)	0.04 0.16 2.0			mA	V <sub>CE</sub> =5 V I <sub>F</sub> =30 mA
Collector-Emitter Saturation Voltage HOA1180-001 HOA1180-002 HOA1180-003	Vce(sat)			0.4 0.4 1.1	V	l <sub>F</sub> =30 mA <sup>(1)</sup> lc=5 μA lc=20 μA lc=250 μA
Rise And Fall Time HOA1180-001, -002 HOA1180-003	t <sub>r</sub> , t <sub>f</sub>		15 75		μs	Vcc=5 V, lc=1 mA RL=1000 Ω RL=100 Ω

Notes 1. Test surface is a front surface mirror (polished aluminum, 85% reflectance) located 0.50 in.(12.7 mm) from the front surface of the device.

#### ABSOLUTE MAXIMUM RATINGS

(25°C Free-Air Temperature unless otherwise noted)


Operating Temperature Range -55°C to 100°C Storage Temperature Range Soldering Temperature (5 sec) 240°C IR EMITTER Power Dissipation Reverse Voltage Continuous Forward Current DETECTOR Collector-Emitter Voltage Emitter-Collector Voltage Power Dissipation Collector DC Current

-55°C to 125°C

75 mW (1) 3 V 50 mA TRANS. DARLINGTON 30 V 15 V 5 V 5 V 75 mW <sup>(1)</sup> 75 mW <sup>(1)</sup>

30 mA

30 mA



Honeywell reserves the right to make changes in order to improve design and supply the best products possible.

# Honeywell