TOSHIBA CMOS Digital Integrated Circuit Silicon Monolithic

TC74AC393P,TC74AC393F,TC74AC393FN,TC74AC393FT

Dual Binary Counter

The TC74AC393 is an advanced high speed CMOS 4-BIT BINARY COUNTER fabricated with silicon gate and double-layer metal wiring C²MOS technology.

It achieves the high speed operation similar to equivalent Bipolar Schottky TTL while maintaining the CMOS low power dissipation.


It contains two independent counter circuits in one package, so that counting or frequency division of eight binary bits can be achieved with one IC.

This device changes state on the negative going transition of the $\overline{\text{CLOCK}}$ pulse. The counter can be reset to "0" (QA to QD = "L") by a high at the CLEAR input regardless of other inputs.

All inputs are equipped with protection circuits against static discharge or transient excess voltage.


Features

- High speed: $f_{max} = 180 \text{ MHz}$ (typ.) at $V_{CC} = 5 \text{ V}$
- Low power dissipation: $I_{CC} = 8 \mu A \pmod{at Ta} = 25^{\circ}C$
- High noise immunity: V_{NIH} = V_{NIL} = 28% V_{CC} (min)
- Symmetrical output impedance: |IOH| = IOL = 24 mA (min)
 - Capability of driving 50 Ω transmission lines.
- Balanced propagation delays: $t_{pLH} \simeq t_{pHL}$
- Wide operating voltage range: V_{CC} (opr) = 2 to 5.5 V
- Pin and function compatible with 74F393



<u>TOSHIBA</u>

Pin Assignment



IEC Logic	: Symbol
------------------	----------


1CLR <u>(2)</u> 1 <u>CK</u> <u>(1)</u>	CTRDIV 16 CT = 0 CT +	(3) (4) 1QB (5) 1QC (6) 1QD
2CLR <u>(12)</u> 2 CK <u>(13)</u>	>	(11) 2QA (10) 2QB (9) 2QC (8) 2QD

Truth Table

Inp	uts	Outputs					
CK	CLR	QA QB QC QE					
Х	Н	L	L	L	L		
\neg	L	Count Up					
	L	No Change					


X: Don't care

Timing Chart



<u>TOSHIBA</u>

System Diagram



Absolute Maximum Ratings (Note 1)

Characteristics	Symbol	Rating	Unit
Supply voltage range	V _{CC}	-0.5 to 7.0	V
DC input voltage	V _{IN}	-0.5 to V _{CC} + 0.5	V
DC output voltage	V _{OUT}	-0.5 to V _{CC} + 0.5	V
Input diode current	lıк	±20	mA
Output diode current	IOK	±50	mA
DC output current	IOUT	±50	mA
DC V _{CC} /ground current	ICC	±200	mA
Power dissipation	PD	500 (DIP) (Note 2)/180 (SOP/TSSOP)	mW
Storage temperature	T _{stg}	−65 to 150	°C

Note 1: Exceeding any of the absolute maximum ratings, even briefly, lead to deterioration in IC performance or even destruction.

Using continuously under heavy loads (e.g. the application of high temperature/current/voltage and the significant change in temperature, etc.) may cause this product to decrease in the reliability significantly even if the operating conditions (i.e. operating temperature/current/voltage, etc.) are within the absolute maximum ratings and the operating ranges.

Please design the appropriate reliability upon reviewing the Toshiba Semiconductor Reliability Handbook ("Handling Precautions"/Derating Concept and Methods) and individual reliability data (i.e. reliability test report and estimated failure rate, etc).

Note 2: 500 mW in the range of Ta = -40 to 65°C. From Ta = 65 to 85°C a derating factor of -10 mW/°C should be applied up to 300 mW.

Operating Ranges (Note)

Characteristics	Symbol	Rating	Unit	
Supply voltage	V _{CC}	2.0 to 5.5	V	
Input voltage	VIN	0 to V _{CC}	V	
Output voltage	V _{OUT}	0 to V _{CC}	V	
Operating temperature	T _{opr}	-40 to 85	°C	
Input rise and fall time	dt/dV	0 to 100 (V _{CC} = 3.3 ± 0.3 V)	200/	
	uvuv	0 to 20 (V _{CC} = 5 \pm 0.5 V)	ns/V	

Note: The operating ranges must be maintained to ensure the normal operation of the device. Unused inputs must be tied to either VCC or GND.

Electrical Characteristics

DC Characteristics

Characteristics	Symbol		Test Conditio	n		٦	Га = 25°С)		a = 0 85°C	Unit
Characteristics	Cymbol				V _{CC} (V)	Min	Тур.	Max	Min	Max	Onit
					2.0	1.50	_	_	1.50	_	
High-level input voltage	VIH		_		3.0	2.10	—	_	2.10	—	V
					5.5	3.85	—	—	3.85	—	
					2.0	_	—	0.50	_	0.50	
Low-level input voltage	VIL		_		3.0	—	—	0.90	—	0.90	V
Ũ					5.5	_	—	1.65		1.65	
					2.0	1.9	2.0		1.9	-	
		V _{IN} = V _{IH} or V _{IL}	I _{OH} = −50 µA		3.0	2.9	3.0	—	2.9	—	
High-level output	V _{OH}				4.5	4.4	4.5		4.4	-	v
voltage			I _{OH} = −4 mA		3.0	2.58	—		2.48	-	v
			I _{OH} = −24 mA		4.5	3.94	—	—	3.80	—	
			I _{OH} = −75 mA	(Note)	5.5	_	—		3.85	-	
					2.0	—	0.0	0.1	—	0.1	
		V _{IN} = V _{IH} or	I _{OL} = 50 μA		3.0	_	0.0	0.1	—	0.1	
Low-level output	V _{OL}				4.5	—	0.0	0.1	-	0.1	v
voltage	VOL	VIL	I _{OL} = 12 mA		3.0	—	—	0.36	—	0.44	v
			I _{OL} = 24 mA		4.5	_	—	0.36	—	0.44	
			I _{OL} = 75 mA	(Note)	5.5	_	—	_	_	1.65	
Input leakage current	I _{IN}	V _{IN} = V _{CC} or GND		5.5	_	—	±0.1	_	±1.0	μA	
Quiescent supply current	ICC	V _{IN} = V _C	_C or GND		5.5	_	_	8.0	_	80.0	μA

Note: This spec indicates the capability of driving 50 Ω transmission lines.

One output should be tested at a time for a 10 ms maximum duration.

Timing Requirements (input: t_r = t_f = 3 ns)

Characteristics	Symbol	Test Condition		Ta = 25°C	Ta = −40 to 85°C	Unit
			$V_{CC}(V)$	Limit	Limit	
Minimum pulse width	t _{w (H)}		3.3 ± 0.3	7.0	7.0	20
(CK)	t _{w (L)}	—	5.0 ± 0.5	5.0	5.0	ns
Minimum pulse width	4		3.3 ± 0.3	7.0	7.0	20
(CLR)	^t w (H)	—	5.0 ± 0.5	5.0	5.0	ns
Minimum removal time t _{rem} —		3.3 ± 0.3	6.0	6.0		
	^t rem	—	5.0 ± 0.5	3.0	3.0	ns

AC Characteristics (C_L = 50 pF, R_L = 500 Ω , input: t_r = t_f = 3 ns)

Characteristics	Symbol Test Condition		Ta = 25°C			Ta = −40 to 85°C		Unit	
			V _{CC} (V)	Min	Тур.	Max	Min	Max	
Propagation delay time	t _{pLH}	_	3.3 ± 0.3	_	8.0	13.2 8.3	1.0	15.0	ns
(CK - QA)	t _{pHL}		5.0 ± 0.5	-	5.0	8.3	1.0	9.5	
Propagation delay time	t _{pLH}	_	3.3 ± 0.3	—	10.1	16.7	1.0	19.0	ns
(CK - QB)	t _{pHL}		5.0 ± 0.5	_	5.9	10.5	1.0	12.0	
Propagation delay time	t _{pLH}	_	3.3 ± 0.3	_	12.0	20.2	1.0	23.0	ns
(CK - QC)	t _{pHL}		5.0 ± 0.5	—	6.8	12.3	1.0	14.0	
Propagation delay time	t _{pLH}	_	3.3 ± 0.3		13.0	23.0	1.0	26.0	ns
(CK - QD)	t _{pHL}		5.0 ± 0.5	—	7.5	13.2	1.0	15.0	-
Propagation delay time	t _{pHL}	_	3.3 ± 0.3	_	8.0	13.2	1.0	15.0	ns
(CLR-Q _n)	p		5.0 ± 0.5	_	5.1	8.8	1.0	10.0	
Maximum clock	f _{max}	_	3.3 ± 0.3	65	125		65	—	MHz
frequency	illidx	—	5.0 ± 0.5	100	160		100	—	
Input capacitance	C _{IN}	—		—	5	10	-	10	pF
Power dissipation capacitance	C _{PD}		(Note)	_	36	_	_	_	pF

Note: C_{PD} is defined as the value of the internal equivalent capacitance which is calculated from the operating current consumption without load.


Average operating current can be obtained by the equation:

 $I_{CC (opr)} = C_{PD} \cdot V_{CC} \cdot f_{IN} + I_{CC}/2$ (per counter)

Package Dimensions

DIP14-P-300-2.54

Unit : mm




Weight: 0.96 g (typ.)



Package Dimensions


SOP14-P-300-1.27A

Unit: mm



Weight: 0.18 g (typ.)

Package Dimensions (Note)




Note: This package is not available in Japan.

Weight: 0.12 g (typ.)

Package Dimensions

TSSOP14-P-0044-0.65A

Unit: mm



Weight: 0.06 g (typ.)

RESTRICTIONS ON PRODUCT USE

20070701-EN GENERAL

- The information contained herein is subject to change without notice.
- TOSHIBA is continually working to improve the quality and reliability of its products. Nevertheless, semiconductor devices in general can malfunction or fail due to their inherent electrical sensitivity and vulnerability to physical stress. It is the responsibility of the buyer, when utilizing TOSHIBA products, to comply with the standards of safety in making a safe design for the entire system, and to avoid situations in which a malfunction or failure of such TOSHIBA products could cause loss of human life, bodily injury or damage to property.
 In developing your designs, please ensure that TOSHIBA products are used within specified operating ranges as set forth in the most recent TOSHIBA products specifications. Also, please keep in mind the precautions and conditions set forth in the "Handling Guide for Semiconductor Devices," or "TOSHIBA Semiconductor Reliability Handbook" etc.
- The TOSHIBA products listed in this document are intended for usage in general electronics applications (computer, personal equipment, office equipment, measuring equipment, industrial robotics, domestic appliances, etc.).These TOSHIBA products are neither intended nor warranted for usage in equipment that requires extraordinarily high quality and/or reliability or a malfunction or failure of which may cause loss of human life or bodily injury ("Unintended Usage"). Unintended Usage include atomic energy control instruments, airplane or spaceship instruments, transportation instruments, traffic signal instruments, combustion control instruments, medical instruments, all types of safety devices, etc.. Unintended Usage of TOSHIBA products listed in his document shall be made at the customer's own risk.
- The products described in this document shall not be used or embedded to any downstream products of which manufacture, use and/or sale are prohibited under any applicable laws and regulations.
- The information contained herein is presented only as a guide for the applications of our products. No responsibility is assumed by TOSHIBA for any infringements of patents or other rights of the third parties which may result from its use. No license is granted by implication or otherwise under any patents or other rights of TOSHIBA or the third parties.
- Please contact your sales representative for product-by-product details in this document regarding RoHS compatibility. Please use these products in this document in compliance with all applicable laws and regulations that regulate the inclusion or use of controlled substances. Toshiba assumes no liability for damage or losses occurring as a result of noncompliance with applicable laws and regulations.