

February 2008

Marking: AB

**SOT-923F** 


# MMBT3906SL

## **PNP Epitaxial Silicon Transistor**

## **Features**

- · General purpose amplifier transistor.
- Ultra small surface mount package for all types(max 0.43mm tall)
- Suitable for general switching & amplification
- · Well suited for portable application
- As complementary type, NPN MMBT3904SL is recommended.
- Pb free





<sup>1.</sup> These ratings are limiting values above which the serviceability of any semiconductor device may be impaired.

## Thermal Characteristics\* Ta=25°C unless otherwise noted

Symbol	Parameter	Max	Unit		
P <sub>C</sub>	Collector Power Dissipation, by R <sub>θJA</sub>	227	mW		
$R_{\theta JA}$	Thermal Resistance, Junction to Ambient	550	°C/W		
* Minimum land pad.					

Electrical Characteristics\* T<sub>a</sub>=25°C unless otherwise noted

Symbol	Parameter	Test Condition	Min.	Max.	Unit
BV <sub>CBO</sub>	Collector-Base Breakdown Voltage	$I_C = -10\mu A, I_E = 0$	-40		V
BV <sub>CEO</sub>	Collector-Emitter Breakdown Voltage	$I_C = -1 \text{mA}, I_B = 0$	40		V
BV <sub>EBO</sub>	Emitter-Base Breakdown Voltage	$I_E = -10\mu A, I_C = 0$	-5		V
I <sub>CEX</sub>	Collector Cut-off Current	$V_{CE} = -30V, V_{EB(OFF)} = -0.3V$		-50	nA
h <sub>FE</sub>	DC Current Gain	$V_{CE} = 1V$ , $I_{C} = -0.1 \text{mA}$ $V_{CE} = 1V$ , $I_{C} = -1 \text{mA}$ $V_{CE} = 1V$ , $I_{C} = -10 \text{mA}$ $V_{CE} = 1V$ , $I_{C} = -50 \text{mA}$ $V_{CE} = 1V$ , $I_{C} = -100 \text{mA}$	60 80 100 60 30	300	
V <sub>CE</sub> (sat)	Collector-Emitter Saturation Voltage	$I_C = -10\text{mA}, I_B = -1\text{mA}$ $I_C = -50\text{mA}, I_B = -5\text{mA}$		-0.25 -0.4	V V
V <sub>BE</sub> (sat)	Base-Emitter Saturation Voltage	$I_C = -10\text{mA}, I_B = -1\text{mA}$ $I_C = -50\text{mA}, I_B = -5\text{mA}$	-0.65	-0.85 -0.95	V V
f <sub>T</sub>	Current Gain Bandwidth Product	$V_{CE} = -20V, I_{C} = -10mA, f = 100MHz$	250		MHz
C <sub>ob</sub>	Output Capacitance	$V_{CB} = -5V, I_{E} = 0, f = 1MHz$		7.0	pF
C <sub>ib</sub>	Input Capacitance	$V_{EB} = -0.5V, I_{C} = 0, f = 1MHz$		15	pF
t <sub>d</sub>	Delay Time	$V_{CC} = -3V, I_{C} = -10mA$		35	ns
t <sub>r</sub>	Rise Time	I <sub>B1</sub> =- I <sub>B2</sub> = -1mA		35	ns
t <sub>s</sub>	Storage Time	]		225	ns
t <sub>f</sub>	Fall Time			75	ns

<sup>\*</sup> DC Item are tested by Pulse Test : Pulse Width≤300us, Duty Cycle≤2%

<sup>2.</sup> These are steady state limits. The factory should be consulted on applications involving pulsed or low duty cycle operations.

# **Typical Performance Characteristics**

Figure 1. DC Current Gain




Figure 2. Collector-Emitter Saturation Voltage




Figure 3. Base- Emitter Saturation Voltage




Figure 4. Collector- Base Leakage Current




Figure 5. Collector- Base Capacitance






Figure 6. Power Derating




# **Package Dimensions**

## **SOT-923F**

- Case : SOT-923F
- Case Material(Molded Plastic): KTMC1060SC
- UL Flammability classification rating: "V0"
- Moisture Sensitivity level per JESD22-A1113B : MSL 1
- Lead terminals solderable per MIL-STD7502026 /JESD22A121
- Lead Free Plating : Pure Tin(Matte)





Dimensions in Millimeters





#### **TRADEMARKS**

The following are registered and unregistered trademarks and service marks Fairchild Semiconductor owns or is authorized to use and is not intended to be an exhaustive list of all such trademarks.

ACEx<sup>®</sup> Green FPS™ Power247® SuperSOT™-8 POWEREDGE® Build it Now™ Green FPS™ e-Series™ SvncFET™ CorePLUS™ GTO™ Power-SPM™ The Power Franchise®  $\mathsf{PowerTrench}^{\mathbb{R}}$  $CROSSVOLT^{TM}$ i-Lo™ p wer CTL™ IntelliMAX™ Programmable Active Droop™ Current Transfer Logic™ ISOPLANAR™ OFFT® TinyBoost™ . TinyBuck™ EcoSPARK<sup>®</sup> MegaBuck™ QS<sup>TM</sup>  $\mathsf{TinyLogic}^{\circledR}$ MICROCOUPLER™ QT Optoelectronics™  $\bar{\mathsf{F}}$ airchild $^{\mathbb{R}}$ TINYOPTO™ MicroFET™ Quiet Series™ MicroPak™ Fairchild Semiconductor® RapidConfigure™ TinyPower™ FACT Quiet Series™ MillerDrive™ SMART START™ TinyPWM™ FACT<sup>®</sup> Motion-SPM™ SPM<sup>®</sup> TinyWire™  $\mathsf{FAST}^{\mathbb{R}}$ OPTOLOGIC® STEALTH™ µSerDes™ OPTOPLANAR® UHC® FastvCore™ SuperFET™ **FPS™** SuperSOT™-3 UniFET™ FRFFT® PDP-SPM™ VCX™ SuperSOT™-6

Power220®

#### DISCLAIMER

FAIRCHILD SEMICONDUCTOR RESERVES THE RIGHT TO MAKE CHANGES WITHOUT FURTHER NOTICE TO ANY PRODUCTS HEREIN TO IMPROVE RELIABILITY, FUNCTION, OR DESIGN. FAIRCHILD DOES NOT ASSUME ANY LIABILITY ARISING OUT OF THE APPLICATION OR USE OF ANY PRODUCT OR CIRCUIT DESCRIBED HEREIN; NEITHER DOES IT CONVEY ANY LICENSE UNDER ITS PATENT RIGHTS, NOR THE RIGHTS OF OTHERS. THESE SPECIFICATIONS DO NOT EXPAND THE TERMS OF FAIRCHILD'S WORLDWIDE TERMS AND CONDITIONS, SPECIFICALLY THE WARRANTY THEREIN, WHICH COVERS THESE PRODUCTS.

### LIFE SUPPORT POLICY

Global Power Resource<sup>SM</sup>

FAIRCHILD'S PRODUCTS ARE NOT AUTHORIZED FOR USE AS CRITICAL COMPONENTS IN LIFE SUPPORT DEVICES OR SYSTEMS WITHOUT THE EXPRESS WRITTEN APPROVAL OF FAIRCHILD SEMICONDUCTOR CORPORATION.

#### As used herein:

- Life support devices or systems are devices or systems which, (a) are intended for surgical implant into the body, or (b) support or sustain life, and (c) whose failure to perform when properly used in accordance with instructions for use provided in the labeling, can be reasonably expected to result in significant injury to the user.
- A critical component is any component of a life support device or system whose failure to perform can be reasonably expected to cause the failure of the life support device or system, or to affect its safety or effectiveness.

# PRODUCT STATUS DEFINITIONS Definition of Terms

Datasheet Identification	Product Status	Definition	
Advance Information	Formative or In Design	This datasheet contains the design specifications for product developme Specifications may change in any manner without notice.	
Preliminary	First Production	This datasheet contains preliminary data; supplementary data will be published at a later date. Fairchild Semiconductor reserves the right to make changes at any time without notice to improve design.	
No Identification Needed	Full Production	This datasheet contains final specifications. Fairchild Semiconductor reserves the right to make changes at any time without notice to improve design.	
Obsolete	Not In Production	This datasheet contains specifications on a product that has been discontinued by Fairchild semiconductor. The datasheet is printed for reference information only.	

Rev. I31