

E-Series 2-way 90° Power Divider 120 – 160 MHz



MAPD-008762-ES0001 V1

Features


- 2-way
- 90 Degree
- Surface Mount
- Tape and reel packaging available
- 260°C Reflow Compatible
- RoHS* compliant version of the MAPDES0001

Description

M/A-COM's MAPD-008762-ES0001 is a RoHS Compliant 2-way 90° power divider in a low cost, surface mount package. Ideally suited for high volume cellular, wireless applications.

The MAPD-008762-ES0001 is available in a SM-87 surface mount package and is designed to be utilized in both RoHS and standard reflow profiles. Parts are packaged in tape & reel.

SM - 87 Package



Pin Configuration

Pin No.	Function			
Input	1			
Port 1	3			
Port 2	6			
External 50 Ohms	4			
Not Connected	2,5			

Ordering Information

Part Number	Package		
MAPD-008762-ES0001	Tape and Reel (900 piece Reel)		

Absolute Maximum Ratings ^{1,2}

Parameter	Absolute Maximum			
Impedance	50 Ohms nominal			
RF Power	1 Watt			
Internal Load Dissipation	0.125 Watt			
Operating Temperature	-40°C to +85°C			
Storage Temperature	-55°C to +125°C			

1. Exceeding any one or combination of these limits may cause permanent damage to this device.

 M/A-COM does not recommend sustained operation near these survivability limits.

This PRELIMINARY Data Sheet contains information regarding a product M/A-COM has under development. Performance is based on measured results and target specifications. Commitment to produce in volume is not guaranteed.

* Restrictions on Hazardous Substances, European Union Directive 2002/95/EC.

1

ADVANCED: Data Sheets contain information regarding a product M/A-COM Technology Solutions is considering for development. Performance is based on target specifications, simulated results, and/or prototype measurements. Commitment to develop is not guaranteed. **PRELIMINARY:** Data Sheets contain information regarding a product M/A-COM Technology Solutions has under development. Performance is based on engineering tests. Specifications are typical. Mechanical outline has been fixed. Engineering samples and/or test data may be available. Commitment to produce in volume is not guaranteed.

- India Tel: +91.80.4155721 China Tel: +86.21.2407.1588
- Visit www.macomtech.com for additional data sheets and product information.

M/A-COM Technology Solutions Inc. and its affiliates reserve the right to make changes to the product(s) or information contained herein without notice.

[•] North America Tel: 800.366.2266 • Europe Tel: +353.21.244.6400



Technology Solutions

E-Series 2-way 90° Power Divider 120 – 160 MHz


MAPD-008762-ES0001 V1

Electrical Specifications: $T_A = 25^{\circ}C$, $Z_0 = 50\Omega$


Frequency Range 40 - 1000 MHz	Test Conditions	Nominal	Units	Min.	Тур.	Max.
Insertion Loss (Above 3dB)	120 - 160 MHz	—	dB	—	0.5	1.0
Isolation	120 - 160 MHz	—	dB	20	25	_
Amplitude Unbalance	120 - 160 MHz		dB	_	1.0	1.6
Phase Unbalance	120 - 160 MHz		0	_	1°	3°

Typical Performance Curves


Insertion Loss Port 1



Amplitude Unbalance



Isolation




2


ADVANCED: Data Sheets contain information regarding a product M/A-COM Technology Solutions is considering for development. Performance is based on target specifications, simulated results, and/or prototype measurements. Commitment to develop is not guaranteed. **PRELIMINARY:** Data Sheets contain information regarding a product M/A-COM Technology Solutions has under development. Performance is based on engineering tests. Specifications are typical. Mechanical outline has been fixed. Engineering samples and/or test data may be available.

Commitment to produce in volume is not guaranteed.

150.0 160.0 86.0 85.0 120.0



Phase Unbalance



- North America Tel: 800.366.2266
 Europe Tel: +353.21.244.6400
 India Tel: +91.80.4155721
 China Tel: +86.21.2407.1588
- Visit www.macomtech.com for additional data sheets and product information.

M/A-COM Technology Solutions Inc. and its affiliates reserve the right to make changes to the product(s) or information contained herein without notice.