

iant



E197852

Features

- Switching capacity up to 25A
- PC pins and quick connect terminals
- Uses include household appliances
- High inrush capability
- Strong resistance to shock and vibration

Contact Data

Contact Arrangement	1A = SPST N.O.
Contact Rating	25A @ 250VAC Resistive
	25A @ 277VAC General Purpose
	1-1/2hp @ 250VAC

Contact Resistance	< 50 milliohms initial		
Contact Material	AgSnO ₂		
Maximum Switching Power	6380VA		
Maximum Switching Voltage	300VAC		
Maximum Switching Current	25A		

Coil Data

		Ī					ī
Coil Voltage		Coil Resistance	Pick Up Voltage	Release Voltage	Coil Power	Operate Time	Release Time
VE	OC	Ω +/- 10%	VDC (max)	VDC (min)	W	ms	ms
			75% of rated	10% of rated			
Rated	Max	.9W	voltage	voltage			
5	6.5	28	3.75	.25			
6	7.8	40	4.50	.30			
9	11.7	90	6.75	.45	00	20	10
12	15.6	160	9.00	.60	.90	20	10
24	31.2	640	18.00	1.2			
48	62.4	2560	36.00	2.4			

General Data

Electrical Life @ rated load	100K cycles, typical
Mechanical Life	10M cycles, typical
Insulation Resistance	100M Ω min. @ 500VDC
Dielectric Strength, Coil to Contact	2000V rms min. @ sea level
Contact to Contact	1000V rms min. @ sea level
Shock Resistance	100m/s ² for 11 ms
Vibration Resistance	1.50mm double amplitude 10~40Hz
Terminal (Copper Alloy) Strength	10N
Operating Temperature	-30°C to +55°C
Storage Temperature	-40°C to +85°C
Solderability	260°C for 5 s
Weight	28g


Caution


1. The use of any coil voltage less than the rated coil voltage may compromise the operation of the relay.

1. Series	J119	1A	12VDC
J119			
2. Contact Arrangement 1A = SPST N.O.			
3. Terminal Options Blank = Quick Connect and PC pins P = PC Pins only			
4. Coil Voltage 5VDC 6VDC 9VDC 12VDC 24VDC 48VDC			

Dimensions


Units = mm






Schematics & PC Layouts

Bottom Views





** The contacts are connected to the quick connect terminals on top of the relay as well as the PC terminals