

# **ES2A THRU ES2J**

### SURFACE MOUNT SUPER FAST RECTIFIER

Reverse Voltage - 50 to 600 Volts Forward Current - 2.0 Ampere

#### **FEATURES**

- The plastic package carries Underwriters Laboratory Flammability Classification 94V-0
- For surface mounted applications
- Super fast switching for high efficiency
- Low reverse leakage
- Built-in strain relief, ideal for automated placement
- High forward surge current capability
- High temperature soldering guaranteed:
- 250 ℃/10 seconds at terminals

### **MECHANICAL DATA**

Case: JEDEC DO-214AA molded plastic body

Terminals: Solder plated, solderable per MIL-STD-750,


Method 2026

Polarity: Color band denotes cathode end

Mounting Position: Any

Weight: 0.005 ounce, 0.138 grams





#### MAXIMUM RATINGS AND ELECTRICAL CHARACTERISTICS

Ratings at 25°C ambient temperature unless otherwise specified. Single phase half-wave 60Hz, resistive or inductive load, for capacitive load current derate by 20%.

Characteristic	Symbol	ES2A	ES2B	ES2C	ES2D	ES2E	ES2G	ES2J	Unit
Peak Repetitive Reverse Voltage Working Peak Reverse Voltage DC Blocking Voltage	VRRM VRWM VR	50	100	150	200	300	400	600	V
RMS Reverse Voltage	VR(RMS)	35	70	105	140	210	280	420	V
Average Rectified Output Current  @T <sub>C</sub> = 100°C	lo	2.0							Α
Non-Repetitive Peak Forward Surge Current 8.3ms Single half sine-wave superimposed on rated load (JEDEC Method)	IFSM	50							А
Forward Voltage @I <sub>F</sub> = 2.0A	VFM	0.95 1.3 1.7				1.7	V		
Peak Reverse Current $@T_A = 25^{\circ}C$ At Rated DC Blocking Voltage $@T_A = 100^{\circ}C$	IRM	10 350							μA
Reverse Recovery Time (Note 1)	trr	35							nS
Typical Junction Capacitance (Note 2)	Cj	25 20					pF		
Operating and Storage Temperature Range	Тj, Tsтg	-55 to +150						°C	

Note: 1. Measured with IF = 0.5A, IR = 1.0A, IRR = 0.25A.

2. Measured at 1.0 MHz and applied reverse voltage of 4.0V D.C.



# **ES2A THRU ES2J**

## **RATINGS AND CHARACTERISTIC CURVES**




Fig. 5 Reverse Recovery Time Characteristic and Test Circuit