

**SPECIFICATION SHEET**  
**JFW MODEL 50PDA-040**  
**POWER DIVIDER ASSEMBLY**

JFW Industries, Inc.  
Phone: 317-887-1340  
sales@jfwindustries.com  
www.jfwindustries.com

Frequency Range	800-3000 MHz
Configuration	24 way power divider/combiner assembly
Impedance	50 Ohms nominal
VSWR	1.6:1 maximum
Insertion Loss (above 13.8 dB split)	1.9 dB maximum
Isolation	20 dB minimum
Amplitude Tracking	$\pm 0.9$ dB
Phase Tracking	$\pm 10^\circ$
RF Input Power (common port)	5 Watts average
RF Connector	SMA or N female

