

Note: The following chart is suggested connection table. It has not been verified yet.

Brandon

Connection Table of SANYO LM-CG53-22NTK

SANYO LM-CG53-22NTK		Flat Panel Connector	
PIN No.	FUNCTION	PIN No.	FUNCTION
CN1-1	FLM	36	FLM
CN1-2	NC	-	-
CN1-3	/DISP OFF	5	VCC (+5V)
CN1-4	CL1	38	LP
CN1-5	VSS	3	GND
CN1-6	CL2	35	SHFCLK
CN1-7	VSS	4	GND
CN1-8	UD0	20	P11
CN1-9	UD1	19	P10
CN1-10	UD2	18	P9
CN1-11	UD3	17	P8
CN1-12	UD4	12	P3
CN1-13	UD5	11	P2
CN1-14	UD6	10	P1
CN1-15	UD7	9	P0
CN2-1	LD0	24	P15
CN2-2	LD1	23	P14
CN2-3	LD2	22	P13
CN2-4	LD3	21	P12
CN2-5	LD4	16	P7
CN2-6	LD5	15	P6
CN2-7	LD6	14	P5
CN2-8	LD7	13	P4
CN2-9	VDD	6	VCC
CN2-10	VSS	33	GND
CN2-11	VSS	34	GND
CN2-12	VEE	Contrast Adjust ( about 26.5V)	
CN2-13	VEE	Contrast Adjust ( about 26.5V)	
CN2-14	VEE	Contrast Adjust ( about 26.5V)	

BIOS : Standard

Mating connector:

CN1: 15pin 51021-1500/MOLEX

CN2: 14pin 51021-1400/MOLEX